RIRussound. A-SRC1 A-BUS® LEARNING &

PRE-PROGRAMMED REMOTE CONTROL **USER GUIDE**



INTRODUCTION

The A-SRC1 Remote Control is designed for use with the Russound A-BUS A-C68 controller and system keypads (A-KP3, A-K5L and A-KSC). It is designed to operate source devices and the audio system keypads. The A-SRC1 controls up to seven devices (six A-BUS sources and one local source). For best results, please read and follow all the remaining instructions and keep this guide for future reference.

FEATURES AND FUNCTIONS

Note: S1 - S6, Vol +/-, Mute and Power are system commands and are the same for any source. All other buttons are dependent upon the device code associated with the source and may vary from device to device.

The following Key Charts provide a general description of button functions.

Kev Charts



device. Issues an S# command and changes the mode of the remote to control the source.


Select an A-BUS



Toggle the selected A-BUS zone power on or off. Has talkback LED for programming and confirmation.



Program sequences.



Press LAST to recall the last-viewed channel. Raise or lower the sound level. Press MUTE to turn the sound off or on.




Select local source.




Input (prefix) command for track,



Move the cursor in menu screens.




option. Performs "Enter" function for Press Enter to choose the high-lighted



(suffix command) for devices.







A-BUS "sleep" command



fast forward, skip forward, stop pause, or play tracks on disc.



Use Page Up/Down with cable or satellite boxes. Note: May have to learn in these functions.



Issues CCTV1 or CCTV2 command.



View the current channel and program information



Display the menu for the selected device.



Exit the selected device's menu, guide, or program without making a menu selection. Display the program guide for the selected



Change inputs on selected device.



Press LAST once to recall the last channel and to page back one screen in the main



Third-party command. Note: may have to learn in this function.



1 2 3 Directly enter channels (e.g., 09 or 31). Press OK to send channel number entries on some TV models

INSTALLING BATTERIES

- 1. On the back of the A-SRC1, push the tab and lift off the battery cover.
- 2. Obtain two (2) fully-charged AA alkaline batteries. Match the + and - marks on the batteries to the + and - marks in the battery case. then insert the new batteries.
- 3. Press the battery cover back into place. The tab should click when the cover is locked.
- 4. Test the unit by pressing Power and any mode key. If the batteries are inserted correctly, the LED will blink once.

PROGRAMMING A DEVICE

Note: S1 - S6, Vol +/-, Mute and Power are system commands and are the same for any source. All other buttons are dependent upon the device code associated with the source.

Before proceeding, find the codes for the devices you want to program in, under "Manufacturer's Codes" in this manual. To control Universal TV, VCR or DVD, Cable or Satellite Receivers, Amplifier or Tuner, and Auxiliary devices, follow these steps.

- Turn on the device (e.g., DVD player) and if needed, load media.
- Press a device key (S1 S6).
- Press and hold SETUP until the red LED blinks twice, then release.
- Enter the first five-digit code for your device. The LED blinks once as each digit is entered. If the code is valid, the LED blinks twice.
- Note: If the LED does not blink twice, repeat steps 2 to 4 and try entering the code again.
- Aim the remote at the device and press a function button. The device should in turn perform the requested function. If it does not, repeat steps 3-5, trying each code for your brand until you find a code that works. If you cannot find a code that works see "Searching for Your Code" in this manual.
- 6. Repeat steps 1-5 for the other devices you want to control. For future reference, write down each working device code.

SEARCHING FOR YOUR CODE

Note: S1 - S6, Vol +/-, Mute and Power are the same for any source. All other buttons are dependent upon the device code associated with the source.

If your device does not respond to the remote after trying all codes listed for your brand, or if your brand is not listed, try searching for your code:

- Press a device key once.
- Press and hold SETUP until the red LED blinks twice, then release.
- 3. Enter 9-9-1, then the device group number (see below). The LED blinks twice.
 - Cable (Cable Converters Video Accessories, Satellite Receivers)
 - TV (TVs)
 - VCR (VCRs, DVD players)
 - Audio (Audio Amplifiers, Audio Amp/Tuners. CD players)
- Aim the remote at the device and press POWER. The remote sends IR codes from its library to the selected device, starting with the most popular code first. If the device responds, go to step 6.
- 5. If the device does not respond, press CH+. the remote will try the next code. Continue until the device responds. Press CH- to try the previous code. 6. Press SETUP to lock in code. To search for
- other device codes, repeat steps 1-5. CHECKING THE CODES

If you have set up the remote using the procedure in "Searching for Your Code," you may need to find out which five-digit code is operating your equipment. For example, to find out which code is assigned to your TV:

- Press the S# key to which the TV is assigned.
- Press and hold SETUP until the red LED blinks twice, then release.
- 3. Enter 9 9 0. The LED blinks twice.
- 4. To view the code's first digit, press 1. Count the LED blinks (e.g., three blinks =3), and enter the number in the appropriate device list in step 6 of "Programming a Device." If a code digit is 0, the LED does not blink.
- Repeat step 4 for the remaining digits, using 2 for the second digit, and so on.
- 6. To check for other device codes, repeat steps 1-5, using the appropriate S# key.

USING LEARNING

The A-SRC1 includes a Learning feature so you can add functions that are unique to your home entertainment devices (e.g., VCR Tracking Up or Down). The following precautions apply.

- . The original remote controls must be in working order for learning to work properly.
- · Learned keys are mode specific, so each one can store a unique function for each mode
- Do not use the following keys for learning: Device Keys, SETUP, BACK, or Record. · Learning capacity is approximately 40 to 100 keys,
- depending on the code being learned. · Certain device codes are not learnable including multi-frequency types, some high frequency ones, and other unusual formats.
- · For optimum learning, avoid high levels of ambient light such as natural sunlight or energy-efficient fluorescent lights.
- Have the original remote controls handy before programming learning. Programming a learned key

Note: If more than 15 seconds pass between key presses, the remote exits programming

- Press and hold SETUP until LED flashes twice.
- Press 9 7 5.
- Press a device key once (e.g., S1 S6) to assign a mode for learning.
- 4. Place the A-SRC1 head-to-head (about 2" apart) from your original remote control. Also locate the key (on original remote control) that will serve as the teaching function.
- On the A-SRC1, press a key where the learned function will be stored. 6. On the original remote, press and hold the the
- key to be learned. The A-SRC1 LED will turn off.Continue holding the key on the original remote until the A-SRC1 LED blinks twice.

Note: If the LED displays one long blink, a learning error has occurred. Try repeating this step again until a successful capture occurs. If the function is still not captured, press and hold SETUP to exit programming. Review the learning precautions listed

above, or the Troubleshooting tips below, before beginning again at step 1.

7. To program another key for the same source, repeat steps 5-6. To program another device, repeat steps 1-6. Press and hold SETUP to exit program-

- Deleting a single learning key 1 Select a source
- 2. Press and hold SETUP until the LED flashed NOTE: If more than 15 seconds passes between key
- presses, the remote exits programming. 3. Press 9 7 6.
- 4. Press the key (twice) containing the learned function to be deleted. The remote blinks twice.
- 5 Repeat steps 2-4 for another key on the same source, or press and hold SETUP to exit program-

Deleting all learned keys in a specific mode 1. Press and hold SETUP until the LED blinks

- Note: if more than 15 seconds pass between key presses, the remote exits programming.
- 2. Press 9 7 6. 3. Press a device key twice (S1 - S6) to delete all the learned keys for that mode. The LED blinks
- 4. Repeat steps 1-3 for another set of keys for a device, or press and hold SETUP to exit program-

TROUBLESHOOTING

Problem: Remote does not control devices or commands are not working properly.

Solution: Try all listed codes for the device. make sure the device operates with an infrared remote control.

ADDITIONAL INFORMATION

The A-SRC1 does not have any user-serviceable parts. Opening the case, except for the battery cover, may cause permanent damage to the A-SRC1.

Russound is not responsible for typographical errors or omissions. A-BUS is a registered trademark of LeisureTech Electronics Ptv Ltd Australia

Copyright @2007 Russound, Inc. Russound, 5 Forbes Road, Newmarket, NH 03857 603-659-5170 www.russound.com

MANUFACTURER'S CODES

28-1257

Setup Codes for Audio Amplifiers

otup oou	oo ioi maalo miipiilioio
cuphase	30382
urus	30765
com	31100, 30577
wa	30406
dioSource	30011
l Canto Design	31583
se	30674
rver	30269
isse	31461,31462
rtis Mathes	30300
non	30160
ırabrand	31561
	30078
rman/Kardon	30892
C	30331
nwood	30356
rsun	31483
ft Coast	30892
noxx	31561
n	30269
gitech	31408
xman	30165
ngnavox	30269
ırantz	30892, 30321, 30269
rk Levinson	31483
kamichi	30321
C	30264
timus	30395,30300
nasonic	30521,30308
rasound	30246
ilips	30892, 30269
neer	30013, 30300
lk Audio	30892, 30269
Audio	31523
A	30300
alistic	30395
nsui	30321
ure	30264
ny	30689, 30220, 30815
undesign	30078,30211
chnics	30521,30308
ctor	30331
	55551

Wards Yamaha	30078, 30211, 30013 30354, 30143, 30133, 30504	Qish Quas
YBA	31502	Radi
Setup Cod	les for Audio Amp/Tuners	RCA
ADC	30531	
Adcom Aiwa	31616, 30616, 31617 31405, 30158, 30189, 31243, 31089,	Real Rege
niwa	31388, 30121, 30405, 31321, 31641, 31347	Rio
Akai Alco	30224, 30076, 31512, 31255	Saba
	31390 Works 31615, 31563	Sam Sans
AMW	31563,31615	Sany
Anam	31609, 31074, 30281	Scot
Apex Digital Arcam	31430,31257 31120	Shar Shar
Audiophase	31387	OTAL
Audiotronic	31189	Sher
Audiovox AVLight	31390,31627 30158	Shin
Bel Canto Desig		Shin
Bose	31229, 31253, 30639	Silso Soni
Brix Cambridga Sour	31602 ndworks 31477, 31370	Soni
Cambridge soul	30531	Sony
Carver	31189, 30189, 30042, 31089, 30008, 30360	
Casio Clarinette	30195	
Classic	30195 31352	Sour
Coby	31513, 31389, 31263	Stere
Compaq	31136	Sunf
Criterion Curtis	31420 31596	Tae I Teac
Curtis Mathes	30080	Tech
Daewoo	31250	
Dell Denon	31383 31360, 30004, 31104, 30771, 31311,	Tech Tho
	30273, 31142, 30301	Vent
Dynamic Bass	30360	Victo
Emerson Fisher	30424, 30255 31409, 30360, 30219, 31801, 30042	Ward Yam
Fonmix	31360	ram
Fosgate	31487	Yorx
Garrard Gateway	30424, 30281, 30463, 30146, 30440 31517, 31567	Zeni
GE	31379	Se
Glory Horse	31263	ABC
Go Video GoldStar	31532 30281	Alle
GPX	31299	Ame
Hafler	30146	Antr
Harman/Kardor	•••••••••••••••••••••••••••••••••••••••	Arch Belo
Hewlett Packard Hitachi	31181 31801,31273	Bell
Initial	31426	Bell
Inkel	30027, 30062, 30502, 30491	Cabl Cabl
Integra JBL	30135, 31298 30110, 31306, 30281	Cabl
JVC	30074, 31282, 31263, 31495, 31374	Cent
Kansai	30440	Citiz
Kenwood	31313, 31570, 31569, 30027, 31051, 30077, 30313, 31027, 30042, 30239,	Clea Clea
	30569, 31052, 30186, 30314	Colo
KLH	31412, 31390, 31428	Com
Koss Lasonic	30424, 30255, 31366 31798, 31510	Cont
Lasonic	31437	Daei
Lexicon	31076	Digi
Linn Lianid Vidaa	30189	Dire
Liquid Video Lloyd's	31497 30195	Dun East
LXI	30181	Eme
Magnavox	31189, 31269, 30189, 30128, 30391,	Ever
Marantz	30195, 31089, 31514, 30531 31189, 31269, 30039, 30189, 31089,	Focu Funa
	31289, 30200, 30128	Garr
MCS Momorov	30039, 30346 31506	GC I
Memorex Mitsubishi	31596 31393	Gehi
Modulaire	30195	Gem Gene
Musicmagic	31089	
NAD Nakamichi	30320 30347, 30097, 31555	Glob
NEC	30235	GMI Gold
Norcent	31389	Goo
Onkyo Optimus	30135, 31298, 30842, 30380, 31531 31023, 30801, 31074, 30080, 30186,	Han
ориниз	30531, 30797, 30042, 30181, 30440,	Hita Hyte
Ouiteo-	30738, 30849, 30177, 30219, 30670	Jasco
Oritron Panasonic	31497, 31366 31518, 30039, 31548, 31764, 30518,	Jebs
anuoome	31350, 31763, 30367, 31316, 31509,	Jerro
Donnorr	31633, 30309, 31288, 31363	Leor
Penney Philco	30195 31390	LG
Philips	31189, 31269, 30189, 31365, 31089,	Lins
-	31266, 31283, 30891, 31368, 30391,	Mag Men
Pioneer	31120, 31268 31023, 30150, 30630, 31184, 30080,	Moto
	30531, 31084, 31384, 30244,31343	Mov
Polaroid	31508	MS
Polk Audio	30189, 31289	Mult Nova

isheng	31609, 31390	NSC
uasar adioShack	30039 31263	Oak Optin
CA	31023, 31609, 31254, 30346, 30531,	Pace
	31154, 31511, 30080, 30530, 31074, 31390, 30054, 30360	Panas Panth
ealistic	30195, 30181, 30163	Parag
egent io	31437 31869, 31383	Philip
aba	31519	Pione
amsung	31500, 31295	Popul
ansui anyo	30189, 30346, 30193, 31089 30801, 30360, 31469, 30219, 31251	Pulsa Quasa
cott	30163, 30322	Radio
harp harper Image	31286, 30186, 31386, 31361 31545, 31556, 30797, 31409, 31416,	RCA
narper image	31549, 31385, 31411, 31546, 31723,	Realis Recot
hamira d	31263, 31410	Regal
herwood hinco	30491, 31423, 30062, 31077, 30502, 31653 31390	Reger
hinsonic	31426	Remb Runco
ilsonic	30176,31426	Sams
onic onic Blue	30281 31383,31869,31532	Scient
ony	31058, 31441, 31258, 31759, 30158,	Seam Signa
	31442, 31529, 31758, 31371, 31503, 31042, 31658, 31158, 31858, 31367,	Signa
	31406, 31458, 30168, 31558, 31131,	SL Ma
oundesign	31349, 31382 30670	Sony Spruc
tereophonics	31023	Starco
unfire	31313,30314,30313,31052	Starga
ae Kwang eac	30440 30163, 31267, 31074, 31528, 30463, 31390	Starqı Super
echnics	31308, 31518, 30039, 30518, 30309,	Super
echwood	31309, 30208 30281	Sylvar
horens	31189	Tandy Televi
enturer	31390,30849	Texsc
'ictor Vards	30074 30158, 30189, 30080, 30054	TFC Timel
amaha	30176, 30081, 31176, 31375, 30186,	Tocon
hev.	31331, 31276	Torx
orx enith	30195 31293,30857,30281,31869	Toshil Trans
	es for Cable Converters	Trista
BC BC	00003,00008,00014,00001,00007,	TS
IDC		
	00013,00011,00017	Tusa TV86
	00013,00011,00017 00315,00153	Tusa TV86 Unika
llegro mericast ntronix	00013,00011,00017 00315,00153 00899	TV86 Unika Unite
mericast .ntronix .rcher	00013, 00011, 00017 00315, 00153 00899 00207, 00022 00797, 00207, 00153, 00022	TV86 Unika Unite Unive
mericast ntronix rcher elcor	00013,00011,00017 00315,00153 00899 00207,00022 00797,00207,00153,00022 00056	TV86 Unika Unite
mericast .ntronix .rcher	00013, 00011, 00017 00315, 00153 00899 00207, 00022 00797, 00207, 00153, 00022	TV86 Unika Unite Unive V2 Viewr Views
mericast intronix ircher ielcor iell & Howell iell South able Star	00013,00011,00017 00315,00153 00899 00207,00022 00797,00207,00153,00022 00056 00014 00899 00056	TV86 Unika Unite Unive V2 View Views Vision
mericast intronix ircher ielcor iell & Howell iell South able Star abletenna	00013,00011,00017 00315,00153 00899 00207,00022 00797,00207,00153,00022 00056 00014 00899 00056 00022	TV86 Unika Unite Unive V2 Viewr Viewr Visior Vortes Zenitl
mericast intronix ircher ielcor iell & Howell iell South able Star	00013,00011,00017 00315,00153 00899 00207,00022 00797,00207,00153,00022 00056 00014 00899 00056	TV86 Unite Unive V2 View View Vision Vorte: Zentil
mericast .ntronix .rcher lelcor lell & Howell lell South able Star abletenna ableview lentury itizen	00013,00011,00017 00315,00153 00899 00207,00022 00096 000014 00899 00056 000022 00056 00022 00056 00022 000153 00315,00153	TV86 Unita Unite Unive V2 Viewn Views Vision Vorte Zenitl Zente
mericast .ntronix .rcher lelcor lell & Howell lell South able Star abletenna ableview lentury litizen learmaster	00013,00011,00017 00315,00153 00899 00207,00022 000797,00207,00153,00022 00006 00014 00899 00056 00022 00022 00022 00023 000153 00315,00153 00883	TV86 Unita Unite Unive V2 Viewr Viewr Visior Vorte Zenitl Zente Set
mericast .ntronix .rcher lelcor lell & Howell lell South able Star abletenna ableview lentury itizen	00013,00011,00017 00315,00153 00899 00207,00022 00096 000014 00899 00056 000022 00056 00022 00056 00022 000153 00315,00153	TV86 Unita Unite Unive V2 Views Vision Vorte: Zenitl Zente ADC Adcor Aiwa
mericast intronix richer elcor ell & Howell ell South fable Star abletenna ableteinna abletview entury itizen learmaster learMax olour Voice omtronics	00013,00011,00017 00315,00153 00899 00207,00022 00076,00153,00022 00014 00899 00056 00022 00022 00022 000153 00315,00153 00883 00883 00883 000025,00031	TV86 Unika Unite Unive V2 Viewr Vision Vorte Zenitt Zente ADC Adcor Aiwa Akai
mericast intronix rcher elcor ell & Howell ell South able Star abletenna ableview entury itizen learmaster learMax leolour Voice omtronics ontec	00013,00011,00017 00315,00153 00899 00207,00022 00797,00207,00153,00022 00056 00014 00899 000026 00012 00022 00022 00153 00315,00153 00883 00883 00883 00085,00031 00040	TV86 Unita Unite Unive V2 Viewr Visior Vorte Zenitl Zente ADC Adcor Aiwa Akai Audic
mericast intronix rcher elcor ell & Howell ell South able Star abletenna ableview entury itizen learmaster learMax olour Voice omtronics ontec	00013,00011,00017 00315,00153 00899 00207,00022 00076,00153,00022 00014 00899 00056 00022 00022 00022 000153 00315,00153 00883 00883 00883 000025,00031	TV86 Unika Unite Unive V2 Viewr Vision Vorte Zenitt Zente ADC Adcor Aiwa Akai
mericast intronix rcher ielcor iell & Howell iell South able Star abletenna ableview ientury itizen learmaster learmax iolour Voice omtronics ontec toolmax abaryung oligi	00013,00011,00017 00315,00153 00899 00207,00022 00096 000014 00899 000056 000022 00056 000022 00053 00315,00153 00315,00153 00883 00883 00883 00883 00883 00883 00883 00883 00883	TV86 Unika Unite Unive V2 Viewr Visior Vorte: Zenitl Zente ADC Adcor Aiwaa Akai Audic BSR Burm
mericast intronix rcher ielcor iell & Howell iell South able Star abletenna ableview entury ittizen learmaster learmax iolour Voice oontronics oontec oolmax oaeryung bigi	00013,00011,00017 00315,00153 00899 00207,00022 00079,00207,00153,00022 00006 00014 00899 00056 000022 00022 00022 00153 00315,00153 00883 00883 000883 000025,00031 00040 00019 00883 01877,00877,00477,00008 00637 00476	TV86 Unita Unita Unite Unive V2 Viewn Viewn Vision Vorte: Zenitl Zente Set ADC Adcor Aiwa Akai Audic Audic BSR
mericast intronix rcher elcor ell & Howell ell South able Star abletenna ableview entury itizen learmaster learMax olour Voice omtronics omtronics ontec toolmax abaeryung oligi birector bumont	00013,00011,00017 00315,00153 00899 00207,00022 00096 000014 00899 000056 000022 00056 000022 00053 00315,00153 00315,00153 00883 00883 00883 00883 00883 00883 00883 00883 00883	TV86 Unika Unite Unive V2 Viewr Vision Vorte: Zeniti Zente ADC Adcor Aiwa Akai Audic Audic BSR Burm Califo Carree
mericast intronix rcher ielcor iell & Howell iell South able Star iabletenna ableview ientury ittizen learmaster learmaster learmaster learmaster learmaster learmy ittizen intronics iontec oolmax iontec oolmax iontec oolmax iontec io	00013, 00011, 00017 00315, 00153 00899 00207, 00022 00096 000014 00899 000056 000022 00056 000022 000583 00315, 00153 00315, 00153 00883 00883 00883 000025, 00031 00040 00019 00883 00883 00883 00883 00065, 000797	TV86 Unika Unite Unive V2 Viewr Visior Vorte: Zeniti Zente ADC Adcor Aiwa Akai Audic Audic BSR Burm Califo Carree Carve Classi
mericast intronix rcher lector	00013,00011,00017 00315,00153 00899 00207,00022 00096 00014 00899 00056 000022 00022 00022 00153 00315,00153 00383 00883 000883 000025,00031 00040 00019 00883 01877,00877,00477,00008 00637 00476 00637 00002 000797	TV86 Unika Unite Unive V2 Viewr Vision Vorte: Zeniti Zente ADC Adcor Aiwa Akai Audic Audic BSR Burm Califo Carree
mericast intronix rcher elcor ell & Howell ell South able Star abletenna ableview entury itizen learmaster learMax olour Voice omtronics omtronics omtronics ointec toolmax abaeryung oligi pirector bumont astern merson verquest ocus	00013, 00011, 00017 00315, 00153 00899 00207, 00022 00096 000014 00899 000056 000022 00056 000022 000583 00315, 00153 00315, 00153 00883 00883 00883 000025, 00031 00040 00019 00883 00883 00883 00883 00065, 000797	TV86 Unika Unite Unive V2 Viewr Vision Vorte: Zenitl Zente Set ADC Adcor Aiwa Akai Audic Audic ESR Burm Califo Carre Carve Classi Crowr DAK DBX
mericast intronix rcher ielcor iell & Howell iell South able Star iabletenna ableview ientury ittizen learmaster learmaster learmaster learmaster olour Voice omtronics ontec oolmax baeryung birector humont asstern merson verquest ocus umai	00013,00011,00017 00315,00153 00899 00207,00022 00056 00014 00899 00022 00022 00022 00022 00022 00153 00315,00153 008183 00883 00025,00031 00040 00019 00883 01877,00877,00477,00008 00637 00476 00637 00002 00002 00002 00002 00002 000019 00019 00019 00019 0019	TV86 Unitak Unite Unive V2 Viewr Visior Vorte: Zenitil Zente ADC Adcor Aiwa Akai Audic Audic Audic Carre Carve Classi Crown DAK DBX Denoi
mericast intronix rcher cher elcor ell & Howell ell South able Star abletenna ableview entury ittizen learmaster learMax folour Voice oontronics oontec oolmax baeryung oigi firector bumont asstern merson werquest ocus uunai arrard GC Electronics	00013,00011,00017 00315,00153 00899 00207,00022 00797,00207,00153,00022 00006 00014 00899 00056 00022 00153 00315,00153 00883 00883 00025,00031 00040 00019 00883 01877,00877,00477,00008 00637 000476 00637 00040 00019 00080 000797 00040,00015 00400 00019 00019 00019 00019	TV86 Unika Unite Unive V2 Viewr Vision Vorte: Zenitl Zente Set ADC Adcor Aiwa Akai Audic Audic ESR Burm Califo Carre Carve Classi Crowr DAK DBX
mericast Intronix Ircher Icher Ielcor Iell & Howell Iell South Iable Star Iabletenna Iableview Ientury Itizen IearMax Iolour Voice Iomtronics Iontec Ionolmax Iolarer	00013,00011,00017 00315,00153 00899 00207,00022 00056 00014 00899 00022 00022 00022 00022 00022 00153 00315,00153 008183 00883 00025,00031 00040 00019 00883 01877,00877,00477,00008 00637 00476 00637 00002 00002 00002 00002 00002 000019 00019 00019 00019 0019	TV86 Unika Unite Unive V2 Viewr Visior Vorte: Zeniti Zente ADC Adcor Aiwa Akai Audic Audic Audic Carree Carve Classi Crowr DAK DBX Deno DKK DMX DMX Dyna
mericast intronix rcher icleor elleor ell & Howell ell South able Star abletenna ableview eentury itizen learmaster learmaster learmaster learmy itizen lear	00013, 00011, 00017 00315, 00153 00899 00207, 00022 00096 000014 00899 000056 000022 00022 00153 00315, 00153 00315, 00153 00883 00883 000883 000883 000029 00109 00883 01877, 00877, 00477, 00008 00637 00406 00637 00637 00637 00797 00040, 00015 00400 00019	TV86 Unita Unite Unive V2 Viewi Visior Vorte: Zenitil Zente Set ADC Adcor Aiwa Akai Audic Audic Audic Carre Carve Classi Crow DAK DBX Denoi DKK DMX Dyna Emer
mericast intronix rcher icleor ell & Howell ell South able Star abletenna ableview entury itizen learMax ololur Voice omtronics ontec oolmax aeryung oligi irector bumont astern merson werquest ocus unai arrard oC Electronics ichua eemini eneral Instrum	00013,00011,00017 00315,00153 00899 00207,00022 00797,00207,00153,00022 00056 00014 00899 000022 00022 00022 00153 00315,00153 00883 00883 00883 00883 00883 00025,00031 00040 00019 00883 01877,00877,00477,00008 00637 00476 00637 00002 00797 00040,00015 00400 00019 00153 00207,00056 00476	TV86 Unika Unite Unive V2 Viewr Visior Vorte: Zeniti Zente ADC Adcor Aiwa Akai Audic Audic Audic Carree Carve Classi Crowr DAK DBX Deno DKK DMX DMX Dyna
mericast intronix rcher ielcor iell & Howell iell South able Star iabletenna ableview ientury ittizen learmaster learmaster learmas iolour Voice iontronics iontec	00013, 00011, 00017 00315, 00153 00899 00207, 00022 000056 00014 00899 000056 000022 00022 00022 00153 00315, 00153 00315, 00153 00383 00883 000883 000025, 00031 00040 00019 00883 01877, 00877, 00477, 00008 00637 00476 00637 00406 000019 00153 00002 00002 00019 00153 000015 00406 00019 00153 00207, 00056 00476 00476 00476 00537 000019 00153 00207, 00056 00476 000797, 00015 ent 00476, 00810, 00276, 00003, 00014, 00011, 00015	TV86 Unitaka Unitet Unive V2 Viewn Vision Vortet Zenitil Zente Set ADC Adcor Aiwa Akai Audic Audic Audic Audic Carree Carve Classi Crown DAK DBX Deno DKK DMX Dyna Emer Fisher Garea GGE
mericast intronix rcher icher ielcor iell & Howell iell South able Star abletenna ableview entury ittizen learmaster learMax solour Voice footnet foot	00013, 00011, 00017 00315, 00153 00899 00207, 00022 00097, 00022 00006 00014 00899 000056 000022 00153 00315, 00153 00315, 00153 00883 00883 00025, 00031 00040 00019 00883 01877, 00877, 00477, 00008 00637 00476 00637 00040 00019 00153 00207, 00056 00476 00797, 00015 ent 00476, 00810, 00276, 00003, 00014, 000115 001327 00015, 00797 00144, 00040	TV86 Unita Unite Unive V2 Viewi Visior Vorte: Zenitl Zente Set ADC Adcor Aiwa Akai Audic Audic Audic Carre Carve Classi Crown DAK DBX Deno DKK DMX Dyna Emer Fisher Garra GE Gemi
mericast intronix rcher icleor ell & Howell ell South able Star abletenna ableview entury itizen learmaster learMax ololour Voice omtronics ontec oolours avaeryung oligi irrector bumont astern merson werquest ocus unai iarrard oC Electronics iehua iemini ieneral Instrum ilobal ioldStar ioodmind	00013, 00011, 00017 00315, 00153 00899 00207, 00022 000056 00014 00899 000056 000022 00022 00022 00153 00315, 00153 00315, 00153 00383 00883 000883 000025, 00031 00040 00019 00883 01877, 00877, 00477, 00008 00637 00476 00637 00406 000019 00153 00002 00002 00019 00153 000015 00406 00019 00153 00207, 00056 00476 00476 00476 00537 000019 00153 00207, 00056 00476 000797, 00015 ent 00476, 00810, 00276, 00003, 00014, 00011, 00015	TV86 Unitaka Unitet Unive V2 Viewn Vision Vortet Zenitil Zente Set ADC Adcor Aiwa Akai Audic Audic Audic Audic Carree Carve Classi Crown DAK DBX Deno DKK DMX Dyna Emer Fisher Garea GGE
mericast intronix rcher iclor ellor ell & Howell ell South able Star abletenna ableview entury itizen learmaster learmaster learmaster learmaster learmout l	00013, 00011, 00017 00315, 00153 00899 00207, 00022 000056 00014 00899 000056 000022 00022 00153 00315, 00153 00315, 00153 00315, 00153 00315, 00153 00383 00083 000883 000025, 00031 00040 00019 00883 01877, 00877, 00477, 00008 00637 00476 00637 00406 000019 00153 00207, 00056 00476 00476 00476 00476 00476 00476 00476 00797, 00015 ent 00476, 00810, 00276, 00003, 00014, 00011, 00015 001327 00015, 00797 00144, 00040 00797	TV86 Unitak Unite Unive V2 Viewr Visior Vorte: Zenitil Zente Set ADC Adcor Aiwa Akai Audic Audic Audic Audic BSR Burm Califo Carrec Carvec Classi Crown DAK DBX Deno DKK DMX DMX Dyna Emer Fishe Garra GE Gemi Genes Genes Gelds GPX
mericast intronix rcher icher ielcor iell & Howell iell South able Star iabletenna ableview entury ittizen learmaster learMax iolour Voice iomtronics iontec	00013, 00011, 00017 00315, 00153 00899 00207, 00022 00096 000014 00899 000022 00153 00315, 00153 00315, 00153 00315, 00153 00315, 00153 00315, 00153 00883 00883 00883 00883 00025, 00031 00040 00119 00883 01877, 00877, 00477, 00008 00637 00040 0019 00019 00019 00019 00019 00109	TV86 Unita Unite Unive V2 Viewi Views Vision Vorte: Zenitl Zente Adcor Adva Akai Audic Aud
mericast Intronix Ircher Ircher Ielcor Iell & Howell Iell South Iable Star Iabletenna Iableview Ientury Itizen Ielearmaster IelearMax Iololur Voice Iomitronics Ionics Ion	00013, 00011, 00017 00315, 00153 00899 00207, 00022 000056 00014 00899 000056 000022 00022 00153 00315, 00153 00315, 00153 00315, 00153 00315, 00153 00383 00083 000883 000025, 00031 00040 00019 00883 01877, 00877, 00477, 00008 00637 00476 00637 00406 000019 00153 00207, 00056 00476 00476 00476 00476 00476 00476 00476 00797, 00015 ent 00476, 00810, 00276, 00003, 00014, 00011, 00015 001327 00015, 00797 00144, 00040 00797	TV86 Unitak Unite Unive V2 Viewr Visior Vorte: Zenitil Zente Set ADC Adcor Aiwa Akai Audic Audic Audic Audic BSR Burm Califo Carrec Carvec Classi Crown DAK DBX Deno DKK DMX DMX Dyna Emer Fishe Garra GE Gemi Genes Genes Gelds GPX
mericast intronix rcher rcher elcor ell & Howell ell South able Star abletenna ableview entury itizen learmaster learmast	00013, 00011, 00017 00315, 00153 00899 00207, 00022 000056 000014 00899 000056 000022 00153 00315, 00153 00315, 00153 00315, 00153 00883 00883 00883 000883 000883 000900900900900900900900900090015000150	TV86 Unitak Unite Unive V2 Viewi Visior Vorte: Zenitil Zente Set ADC Adcor Aiwa Akai Audic
mericast intronix rcher rcher elcor ell & Howell ell South able Star abletenna ableview entury itizen learmaster learMax ololour Voice omtronics ontec oolour Voice omtronics oolour ableview entury itizen learmaster learMax ololour Voice omtronics oontec oolour voice oomtronics oothec oolours aberyung oligi irrector pumont astern merson werquest ocus unai iarrard oc Electronics iehua iemini ieneral Instrum ilobal imil iolodStar ioodmind iamlin liitachi jytex usco ebsee errold	00013, 00011, 00017 00315, 00153 00899 00207, 00022 00096 000014 00899 00006 00012 00015 00015 00015 00015 00083 00883 000883 000883 000883 000883 000883 00019 00019 000883 00019 00019 00083 000637 00016 000797 000109 0015 00153 00153 00015 001019 0019 0019 0019 0019 0019 0	TV86 Unika Unite Unive V2 Viewn Vision Vorte: Zenitt ADC Adcoor Aiwa Akai Audic Audic BSR Burm Califo Carre Carve Classi Crown DAK DBX Denoi DKK DMX Dyna Emer Fisher Garra GE Gemi Genes GoldS GPX Harm Hitac Inkel Inkel Integ
mericast intronix rcher icleor elleor ell & Howell ell South able Star abletenna ableview eentury itizen learmaster learmaster learmaster learmy itizen lear	00013, 00011, 00017 00315, 00153 00899 00207, 00022 000056 000014 00899 000056 000022 00153 00315, 00153 00315, 00153 00315, 00153 00883 00883 00883 000883 000883 000900900900900900900900900090015000150	TV86 Unitak Unite Unive V2 Viewi Visior Vorte: Zenitil Zente Set ADC Adcor Aiwa Akai Audic
mericast Intronix Ircher Ircher Ielcor Iell & Howell Iell South Ie	00013, 00011, 00017 00315, 00153 00899 00207, 00022 00097, 00207, 00153, 00022 00006 00014 00899 00056 00022 00153 00315, 00153 00315, 00153 00883 00883 00883 00025, 00031 00040 00019 00883 01877, 00877, 00477, 00008 00637 00406 00637 00002 00797 00040, 00015 00400 00019 00153 00207, 00056 00476 00797, 00015 00109 0019 0011, 00015 0011, 00015 00140, 00015 00019 0015, 00797 00144, 00810, 00276, 00003, 00014, 00011, 00015 000797 00015, 00315, 00153 00007 00015, 00315, 00153 00007 00015, 00315, 00153 00007 00015, 00315, 00153 00440 00079 00015, 00315, 00153 00440	TV86 Unitak Unitet Unive V2 Viewn Vision Vortet Zenitt Zentet ADC Adcoon Aiwa Akai Audic Audic BSR Burm Califo Carre Carve Classis Crown DAK DBX Denoi DKK DMX Dyna Emer Fisher Garra GE Gemi Gene GoldS GPX Harm Hitac Inkel Integ IVC Kenw
mericast intronix rcher rcher elcor ell & Howell elel South able Star abletenna ableview entury itizen learmaster learMax ololour Voice footner footner footner footner merson verquest ocus unai farrard for Electronics elchua teemini eneral Instrum lobal MI soldStar foodmind tamlin titachi tytex tyses een eon G G insay fagnavox	00013, 00011, 00017 00315, 00153 00899 00207, 00022 00797, 00207, 00153, 00022 00006 00014 00899 000056 000014 00899 000022 00022 00153 00315, 00153 00315, 00153 00883 00883 00883 00883 00025, 00031 00040 00019 00883 01877, 00877, 00477, 00008 00637 00476 00637 00002 00797 00040, 00015 00153 00207, 00056 00476 00797, 00015 00109 0011, 00015 01327 00014, 00011 00015 01327 00015, 00797 00144, 00040 00797 00144, 00040 00797 00144, 00040 00797 00144, 00040 00797 00144, 00011 000079 00015, 00315, 00153 00476 00797 00015, 00315, 00153 00400 00015, 00315, 00153 00400 000100011, 00015	TV86 Unitak Unite Unive V2 Viewn Vision Vorte: Zenitil Zente Set ADC Adcorr Aiwa Akai Audic BSR Burm Califo Carrer Carve Classi Crown DAK DBX Deno DKK MDX Dyna Emer Fishete Gemi Gene GoldS GPX Harm Hitad Inkel Integr JVC Kenw
mericast Intronix Ircher Ircher Ielcor Iell & Howell Iell South Ie	00013, 00011, 00017 00315, 00153 00899 00207, 00022 00097, 00207, 00153, 00022 00006 00014 00899 00056 00022 00153 00315, 00153 00315, 00153 00883 00883 00883 00025, 00031 00040 00019 00883 01877, 00877, 00477, 00008 00637 00406 00637 00002 00797 00040, 00015 00400 00019 00153 00207, 00056 00476 00797, 00015 00109 0019 0011, 00015 0011, 00015 00140, 00015 00019 0015, 00797 00144, 00810, 00276, 00003, 00014, 00011, 00015 000797 00015, 00315, 00153 00007 00015, 00315, 00153 00007 00015, 00315, 00153 00007 00015, 00315, 00153 00440 00079 00015, 00315, 00153 00440	TV86 Unitak Unitet Unive V2 Viewn Vision Vortet Zenitt Zentet ADC Adcoon Aiwa Akai Audic Audic BSR Burm Califo Carre Carve Classis Crown DAK DBX Denoi DKK DMX Dyna Emer Fisher Garra GE Gemi Gene GoldS GPX Harm Hitac Inkel Integ IVC Kenw
mericast intronix rcher rcher relecor ell & Howell elell South able Star abletenna ableview entury itizen learmaster learMax ololour Voice comtronics contec coolmax baceryung bigi pirector pumont astern merson werquest ocus unai carrard ocus icarrard ocu	00013, 00011, 00017 00315, 00153 00899 00207, 00022 00096 000014 00899 00002 00002 00015 000153 00315, 00153 00315, 00153 00883 00883 00883 00025, 00031 00040 0019 00883 01877, 00877, 00477, 00008 00637 00040, 00015 00406 00637 00019 0019 0019 0019 0019 0019 0019 00	TV86 Unitak Unitet Unive V2 Viewn Vision Vortet Zenitt ADC Adcoor Aiwa Akai Audic Audic BSR Burm Califo Carre Carve Classis Crown DAK DBX Deno DKK MDX Dyna Emer Fisher Garra GE Gemi Gene GoldS GPX Harm Hitacl Inkel Integ InvC Kenw KLH Kodal Korsus KSS Krell
mericast Intronix Ircher Ircher Ielcor Iell & Howell Iell South Ie	00013, 00011, 00017 00315, 00153 00899 00207, 00022 000056 000014 00899 000056 000022 00153 00315, 00153 00315, 00153 00315, 00153 00883 00883 000883 000883 00019 00040 00019 00883 01877, 00877, 00477, 00008 00637 00406 00019 00089 000797 00040, 00015 00400 00019 0019 0	TV86 Unita Unite Unive V2 Viewi Visior Vorte: Zenitil Zente Set ADC Adcor Adcor Aiwa Audic

	000 (2 001 5 (
	00063,00156		
	00019,00007		
mus	00021 01877,00237		
asonic	00000,00008,00107,00040,00021		
her	00637		
gon	00000		
ips	00317,00027,00025,00153,00013,		
eer	00031,01305 01877,00877,00144,00533,01021		
ılar Mechani			-
ar	00000		
sar	00000		
ioShack	00015, 00883, 00797, 00315		
	00021		
istic oton	00207 00400	······	
al	00279, 00273, 00259, 00020		
ency	00002		
brandt	00011		
CO .	00000		
sung	00000, 00144, 00040		
ntific Atlanta n	01877, 00877, 00477, 00008, 00017 00510	······································	-
al	00040,00015		
ature	00011		
larx	00040	•••••••••••	
7	01006		
ıcer	00021		
com	00003,00014,00015		
gate quest	00015,00797,00040 00015		
ercable	00276		
ermax	00883		
ania	00001		
ły	00258		
view	00040		
can	00001 00310		
eless	00040		
om	00012,00013		
	00003		
iiba	00000		
is PX	00276,00153,00315		
ar	00883		
	00003 00015		
6	00063		
ca	00207, 00153, 00022		
ed Artists	00007		
ersal	00153,00056,00207,00022,00191		
	00883		
vmaster	00883 00883		
vmaster vstar	00883 00883 00063,00027,00258		
vmaster	00883 00883		;
vmaster vstar on ex View th	00883 00883 00063,00027,00258 00883 00883 00000,00525,00899		;
vmaster vstar on ex View th	00883 00883 00063,00027,00258 00883 00000,00525,00899 00400		
vmaster vstar on ex View th	00883 00883 00063,00027,00258 00883 00883 00000,00525,00899		
vmaster vstar on ex View tth ek tup Cod	00883 00883 00063,00027,00258 00883 00883 00800,00525,00899 004400 es for CD Players 30018		
wmaster wstar on ex View th ek tup Cod	00883 00883 00063,00027,00258 00883 00883 00000,00525,00899 00400 es for CD Players 30018 30155,30234		
vmaster vstar on ex View th ek tup Cod	00883 00883 00063,00027,00258 00883 00883 00000,00525,00899 00400 es for CD Players 30018 30155,30234 30157,30124,30012		
wmaster wstar on ex View tth eek tup Cod	00883 00883 00063,00027,00258 00883 00883 00000,00525,00899 00400 es for CD Players 30018 30155, 30234 30157, 30124,30012 30156		
wmaster wstar on ex View th ek tup Cod	00883 00883 00063,00027,00258 00883 00883 00000,00525,00899 00400 es for CD Players 30018 30155,30234 30157,30124,30012		
wmaster wstar on ex View tth ek tup Cod o o o o o o o o o o o o o o o o o o	00883 00883 00063,00027,00258 00883 00883 00000,00525,00899 00400 cor CD Players 30018 30155,30234 30157,30124,30012 30156 30194 30170 30245,30194		
wmaster wstar on ex View th ek tup Cod i io Alchemy io-Technica	00883 00883 00863,00027,00258 00883 00883 00800,00525,00899 00400 es for CD Players 30018 30155,30234 30157,30124,30012 30156 30194 30170 30245,30194 30420		
wmaster wstar on ex View tth ek tup Cod i io Alchemy io-Technica mester fornia Audio	00883 00883 00883 00883 00063,00027,00258 000883 00883 00000,00525,00899 00400 es for CD Players 30018 30155, 30234 30157, 30124, 30012 30156 30194 30170 30245, 30194 30420 Labs 30029, 30303		
wmaster vistar on ex View th ek tup Cod o i i io Alchemy io-Technica mester fornia Audio era	00883 00883 00883 00063,00027,00258 00883 00883 00000,00525,00899 00400 ex for CD Players 30018 30155, 30234 30157, 30124, 30012 30156 30194 30170 30245, 30194 30420 30420 30428 30194 30194 30109 30194 30109 30194		
wmaster wstar on ex View tth ek tup Cod i io Alchemy io-Technica mester fornia Audio	00883 00883 00883 00883 00063,00027,00258 000883 00883 00000,00525,00899 00400 es for CD Players 30018 30155, 30234 30157, 30124, 30012 30156 30194 30170 30245, 30194 30420 Labs 30029, 30303		
wmaster vistar on ex View th tup Code i i io Alchemy io-Technica mester fornia Audio era	00883 00883 00883 00883 00883 00883 00800,00525,00899 00400 es for CD Players 30018 30155, 30234 30157, 30124, 30012 30156 30194 30420 Labs 30029, 30303 30194 30157, 30437, 30179		
vmaster vnstar on ex View th ek tup Cod i io Alchemy io-Technica mester fornia Audio erer sic	00883 00883 00883 00883 00883 00883 00880 00880 00880 00880 00800 00400 ex for CD Players 30018 30155, 30234 30157, 30124, 30012 30156 30194 30170 30245, 30194 30170 30245, 30194 30150 30194 30170 30245, 30194 30170 30245		
vmaster vstar on ex View tth ek tup Cod i io Alchemy io-Technica mester fornia Audio era era era	00883 00883 00883 00883 00883 00883 00883 00800,00525,00899 00400 es for CD Players 30018 30157,30124,30012 30156 30194 30170 30245,30194 30420 Labs 30029,30303 30194 30157,30437,30179 31297 30122 30245 30244		
ymaster ynstar yn ymaster yn yn ymaster yn yn ym	00883 00883 00883 00883 00883 00883 00883 00883 00800,00525,00899 00400 es for CD Players 30018 30155, 30234 30157, 30124, 30012 30156 30194 30170 30245, 30194 30420 Labs 30029, 30303 30194 30157, 30437, 30179 31297 30122 30254 30254 30873, 30003		
wmaster vistar on ex View th ek tup Cod i i io Alchemy io-Technica mester fornia Audio era ere er sic vin	00883 00883 00883 00883 00883 00880 00880 00880 00000,00525,00899 00400 es for CD Players 30018 30155, 30234 30157, 30124, 30012 30156 30194 30170 30245, 30194 30420 Labs 30029, 30303 30194 30157, 30437, 30179 311297 30122 30245 30254 30873, 30003 30000		
ymaster ynstar yn ymaster yn yn ymaster yn yn ym	00883 00883 00883 00883 00883 00880 00880 00880 00000,00525,00899 00400 es for CD Players 30018 30155, 30234 30157, 30124, 30012 30156 30194 30170 30245, 30194 30420 Labs 30029, 30303 30194 30157, 30437, 30179 311297 30122 30245 30254 30873, 30003 30000		
wmaster vistar on ex View th eke tup Cod i io Alchemy io-Technica mester fornia Audio era era er er sic on K X Electronics	00883 00883 00883 00883 00883 00883 00880 00800,00525,00899 00400 es for CD Players 30018 30155, 30234 30157, 30124, 30012 30156 30194 30420 Labs 30029, 30303 30194 30157, 30437, 30179 31297 30245 30245 30254 30254 30254 30254 30254 30254 30000 30157		
wmaster wstar on ex View th ek tup Cod i io Alchemy io-Technica mester fornia Audio era ere er K Electronics amic Bass erson er	00883 00883 00883 00883 00883 00883 00800,00525,00899 00400 es for CD Players 30018 30155, 30234 30157, 30124, 30012 30156 30194 30170 30245, 30194 30420 Labs 30029, 30303 30194 30157, 30437, 30179 311297 30122 30245 30254 30873, 30003 30000 30157 30179 30305, 30164, 30155, 30469 30179, 30174, 31325, 30088, 30342		
ymaster ynstar yn ymaster yn yn ymaster yn yn ym	00883 00883 00883 00883 00883 00883 00880 00000,00525,00899 00400 es for CD Players 30018 30157, 30124, 30012 30156 30194 30170 30245, 30194 30420 Labs 30029, 30303 30194 30157, 30437, 30179 31297 30122 30254 30873, 30434 30254 30254 30254 30254 30273 30179 30179 30179 30179 30179 30179 30179 30179 30179 30179 30179 30179 30179 30179 30179 30179, 30174, 31325, 30088, 30342 30179, 30174, 31325, 30088, 30342		
vmaster vnstar on ex View th ek tup Cod i io Alchemy io-Technica mester fornia Audio era era sic X K Electronics amic Bass rsson er arad	00883 00883 00883 00883 00883 00883 00883 00883 00890 0000,00525,00899 00400 es for CD Players 30018 30157, 30124, 30012 30156 30194 30170 30245, 30194 30420 Labs 30029, 30303 30194 30157, 30437, 30179 31297 30122 30254 30254 30873, 30003 30000 30157 30179 30305, 30164, 30155, 30469 30179, 30174, 31325, 30088, 30342 30245, 30420, 30393, 30280, 30425 30099		
ymaster ynstar yn ymaster yn ym ymaster yn ym ymaster ym ym ymaster ym	00883 00883 00883 00883 00883 00063,00027,00258 00883 00883 00000,00525,00899 00400 es for CD Players 30018 30155, 30234 30157, 30124, 30012 30156 30194 30170 30245, 30194 30420 Labs 30029, 30303 30194 30157, 30437, 30179 31297 30122 30245 30245 30254 30873, 3003 30000 30157 30179 30305, 30164, 30155, 30469 30179, 30174, 31325, 30088, 30342 30245, 30420, 30393, 30280, 30425 30245, 30420, 30393, 30280, 30425 30245, 30420, 30393, 30280, 30425		
vmaster vnstar on ex View th ek tup Cod i io Alchemy io-Technica mester fornia Audio era era sic X K Electronics amic Bass rsson er arad	00883 00883 00883 00883 00883 00883 00883 00883 00890 0000,00525,00899 00400 es for CD Players 30018 30157, 30124, 30012 30156 30194 30170 30245, 30194 30420 Labs 30029, 30303 30194 30157, 30437, 30179 31297 30122 30254 30254 30873, 30003 30000 30157 30179 30305, 30164, 30155, 30469 30179, 30174, 31325, 30088, 30342 30245, 30420, 30393, 30280, 30425 30099		
ymaster ynstar yn ymaster yn yn ymaster yn yn ym	00883 00883 00883 00883 00883 00883 00883 00883 00880 00880 0080,00525,00899 00400 es for CD Players 30018 30155, 30234 30157, 30124, 30012 30156 30194 30170 30245, 30194 30420 Labs 30029, 30303 30194 30157, 30437, 30179 31297 30122 30254 30873, 30003 30000 30157 30179 30305, 30164, 30155, 30469 30179, 30174, 31325, 30088, 30342 30245, 30420, 30393, 30280, 30425 3009 30625 30032, 30305, 30164 30417 31296		
wmaster wstar on ex View th ek tup Cod i io Alchemy io-Technica mester fornia Audio era ere sic vn K K Electronics amic Bass rsson er ard	00883 00883 00883 00883 00883 00883 00883 00880 00800,00525,00899 00400 es for CD Players 30018 30155, 30234 30157, 30124, 30012 30156 30194 30170 30245, 30194 30420 Labs 30029, 30303 30194 30157, 30437, 30179 31297 30122 30245 30254 30873, 3003 30000 30157 30179 30179, 30174, 31325, 30088, 30342 30245, 30420, 30393, 30280, 30425 30009 30625 30032, 30305, 30164 30417 31296 30157, 30173, 31202, 30426		
vmaster vmstar on ex View th ek tup Cod i io Alchemy io-Technica mester fornia Audio era ere sisc vn c K Electronics amic Bass rsson ere rard inini exxxa LStar man/Kardon chi	00883 00883 00883 00883 00883 00883 00880 00800,00525,00899 00400 es for CD Players 30018 30157, 30124, 30012 30156 30194 30170 30245, 30194 30420 Labs 30029, 30303 30194 30157, 30437, 30179 31297 30122 30245 30245 30245 30245 30245 30245 30245 30245 30245 30194 30157, 30437, 30179 31297 30122 30245 30245 30254 30273 30179 30179 30179 30179 30179 30179, 30174, 31325, 30088, 30342 30245, 30420, 30393, 30280, 30425 30000 30157 30179 30179, 30174, 31325, 30088, 30342 30245 30000 30157, 30173, 31202, 30426 30032, 30355, 30164 30417		
vmaster vnstar on ex View th ek tup Cod i io Alchemy io-Technica mester fornia Audio erer sic X Electronics amic Bass rrson er ard iini exxa [Star eman/Kardon chi]	00883 00883 00883 00883 00883 00883 00883 00800 00000,00525,00899 00400 es for CD Players 30018 30155,30234 30157,30124,30012 30156 30194 30170 30245,30194 30420 Labs 30029,30303 30194 30157,30437,30179 31297 30122 30254 30873,30003 30000 30157,30437,30179 30305,30164,30155,30469 30179,30174,31325,30088,30342 30245,30420,30393,30280,30425 30009 30625 30009 30625 30032,30305,30164 30417 31296 30157,30173,31202,30426 30032,30155 30196,30180,30437		
vmaster vmstar on ex View th ek tup Cod i io Alchemy io-Technica mester fornia Audio era ere sisc vn c K Electronics amic Bass rsson ere rard inini exxxa LStar man/Kardon chi	00883 00883 00883 00883 00883 00883 00883 00883 00880 00800,00525,00899 00400 es for CD Players 30018 30155, 30234 30157, 30124, 30012 30156 30194 30170 30245, 30194 30420 Labs 30029, 30303 30194 30157, 30437, 30179 31297 30122 30245 300254 30873, 30003 30000 30157, 30174, 31325, 30088, 30342 30873, 30079 30179 30305, 30164, 30155, 30469 30179, 30174, 31325, 30088, 30342 30245, 30420, 30393, 30280, 30425 3009 30625 30032, 30305, 30164 30417 31296 30157, 30173, 31202, 30426 30032, 30155, 30173, 31202, 30426 30032, 30155, 30180, 30437 30190		
vmaster vnstar on ex View th ek tup Cod i io Alchemy io-Technica mester fornia Audio erer sic X Electronics amic Bass rrson er ard iini exxa [Star eman/Kardon chi]	00883 00883 00883 00883 00883 00883 00883 00800 00000,00525,00899 00400 es for CD Players 30018 30155,30234 30157,30124,30012 30156 30194 30170 30245,30194 30420 Labs 30029,30303 30194 30157,30437,30179 31297 30122 30254 30873,30003 30000 30157,30437,30179 30305,30164,30155,30469 30179,30174,31325,30088,30342 30245,30420,30393,30280,30425 30009 30625 30009 30625 30032,30305,30164 30417 31296 30157,30173,31202,30426 30032,30155 30196,30180,30437		
wmaster wstar on ex View th ek tup Cod io io Alchemy io-Technica mester fornia Audio era era sic on K K K Electronics amic Bass erson er arard dinini exxxa SIStar man/Kardon chi el gra	00883 00883 00883 00883 00883 00883 00880 00000,00525,00899 000400 8s for CD Players 30018 30157, 30124, 30012 30156 30194 30170 30245, 30194 30420 Labs 30029, 30303 30194 30157, 30437, 30179 31297 30122 30245 30245 30245 30274 30274 30274 30274 30275 30179 30179 30179, 30174, 31325, 30088, 30342 30245, 30420, 30393, 30280, 30425 30000 30157 30179 30179, 30174, 31325, 30088, 30342 30245, 30420, 30393, 30280, 30425 30009 30625 30032, 30305, 30164 30417 31296 30032, 30355 30196, 30180, 30437 30101 30072, 31294, 30655		
wmaster wstar on ex View th ek tup Cod i io Alchemy io-Technica mester fornia Audio era wn K K Electronics amic Bass rsson er rard inini exxxa IStar iman/Kardon chi i gra wood	00883 00883 00883 00883 00883 00065,00027,00258 00883 00883 00000,00525,00899 00400 es for CD Players 30018 30155, 30234 30157, 30124, 30012 30156 30194 30170 30245, 30194 30420 Labs 30029, 30303 30194 30157, 30437, 30179 31297 30122 30245 300254 30873, 3003 30000 30157, 30164, 30155, 30469 30179, 30174, 31325, 30088, 30342 30245, 30420, 30393, 30280, 30425 30032, 30305, 30164 30179 30179, 30174, 31325, 30088, 30342 30245, 30420, 30393, 30280, 30425 30032, 30305, 30164 30417 31296 30157, 30173, 31202, 30426 30032, 30157 30101 30072, 31294, 30655 30681, 30826, 30028, 30037, 30036, 30190 31318		
vmaster vstar on ex View th th ek tup Cod i io Alchemy io-Technica mester fornia Audio era era k K Electronics amic Bass rson er ard iiiiii er aman/Kardon chi er gra wwood ii ak	00883 00883 00883 00883 00883 00883 00883 00883 00883 00890 00000,00525,00899 000400 es for CD Players 30018 30157, 30124, 30012 30156 30194 30170 30245, 30194 30420 Labs 30029, 30303 30194 30157, 30437, 30179 31297 30122 30245 30254 30873, 30033 30000 30157 30179 30305, 30164, 30155, 30469 30179, 30174, 31325, 30088, 30342 30245, 30420, 30393, 30280, 30425 30000 30157 30179 30305, 30164, 30155, 30469 30179, 30174, 31325, 30088, 30342 30245, 30420, 30393, 30280, 30425 30009 30625 30009 3063030, 30305, 30164 30417 31296 300157, 30173, 31202, 30426 30032, 30155 30196, 30180, 30437 30101 30077, 31294, 30655 30681, 30826, 30626, 30028, 30037, 30036, 30190 31318 30287		
wmaster wstar on ex View th ek tup Cod i io Alchemy io-Technica mester fornia Audio era wn K K Electronics amic Bass rsson er rard inini exxxa IStar iman/Kardon chi i gra wood	00883 00883 00883 00883 00883 00883 00883 00890 00000,00525,00899 00400 es for CD Players 30018 30155,30234 30157,30124,30012 30156 30194 30420 Labs 30029,30303 30194 30157,30437,30179 31297 30122 30254 30873,30003 30000 30157,30437,30179 30305,30164,30155,30469 30179,30174,31325,30088,30342 30245 30245 30245 30179 30305,30164,30155,30469 30179,30174,31325,30088,30342 30245 30032,30305,30164 30417 31296 30157,30173,31202,30426 30032,30155 30196,30180,30437 30101 30072,31294,30655 300681,30826,30626,30028,30037,30036,30190 31318 300287 31484		
wmaster wstar on ex View th ek tup Cod io io Alchemy io-Technica mester fornia Audio era era sic wn t t t t t t t t t t t t t t t t t t	00883 00883 00883 00883 00883 00883 00883 00883 00800,00525,00899 00400 es for CD Players 30018 30155, 30234 30157, 30124, 30012 30156 30194 30170 30245, 30194 30420 Labs 30029, 30303 30194 30157, 30437, 30179 31297 30122 30254 30873, 30033 30000 30157, 30174, 31325, 30088, 30342 30245, 3040, 30393, 30280, 30425 30032, 3035, 30164, 30155, 30469 30179, 30174, 31325, 30088, 30342 30245, 30420, 30393, 30280, 30425 3009 30625 30032, 30305, 30164 30417 31296 30157, 30173, 31202, 30426 30032, 30157 30101 30072, 31294, 30655 30081, 30826, 30626, 30028, 30037, 30086, 30190 31318 30287 31484 31317		
wmaster wstar on ex View th ek tup Cod i io Alchemy io-Technica mester fornia Audio era vier sic wn c K Electronics srson er erard inini exxxa IStar iman/Kardon chi el gra wwood I ak k un i i i i i i i i i i i i i i i i i i	00883 00883 00883 00883 00883 00883 00883 00890 00000,00525,00899 00400 es for CD Players 30018 30155,30234 30157,30124,30012 30156 30194 30420 Labs 30029,30303 30194 30157,30437,30179 31297 30122 30254 30873,30003 30000 30157,30437,30179 30305,30164,30155,30469 30179,30174,31325,30088,30342 30245 30245 30245 30179 30305,30164,30155,30469 30179,30174,31325,30088,30342 30245 30032,30305,30164 30417 31296 30157,30173,31202,30426 30032,30155 30196,30180,30437 30101 30072,31294,30655 300681,30826,30626,30028,30037,30036,30190 31318 300287 31484		
wmaster wstar on ex View th ek tup Cod io io Alchemy io-Technica mester fornia Audio era era sic wn t t t t t t t t t t t t t t t t t t	00883 00883 00883 00883 00883 00883 00880 00000,00525,00899 000400 es for CD Players 30018 30157, 30124, 30012 30156 30194 30157, 30124, 30012 30156 30194 30157, 30134 30420 Labs 30029, 30303 30194 30157, 30437, 30179 31297 31297 31297 31297 30174, 31325, 30084 30157, 30437, 30179 31297 30174, 31325, 30088, 30342 30245 30254 30873, 3003 30000 30157 30179, 30174, 31325, 30088, 30342 30245, 30420, 30393, 30280, 30425 30009 30157 30179, 30174, 31325, 30088, 30342 30245, 30420, 30393, 30280, 30425 30009 30157, 30173, 31202, 30426 30032, 3035, 30164 30417 31296 30032, 3035, 30164 30417 31296 30032, 3035, 30164 30417 31296 30032, 3035, 30164 30417 31296 30032, 3035, 30164 30417 31296 30032, 3035, 30164 30417 31296 30032, 3035, 30164 30417 31296 30032, 3035, 30164 30417 31296 30032, 3035, 30164 30417 31296 30032, 3035, 30164 30417 31296 30032, 3035, 30164 30417 31296 30032, 3035, 30164 30417 31296 30032, 30155 30196, 30180, 30437 30101 30072, 31294, 30655 30681, 30826, 30626, 30028, 30037, 30036, 30190 31318 30287 31484 31317 30157		

Luxman	30093
LXI	30305
Magnavox	30157,30305
Marantz Mark Lavinson	30626, 30029, 30157, 30180
Mark Levinson McIntosh	31484 30287
MCS	30029, 30043
Miro	30000
Mission	30157
MTC	30420, 30625
Nakamichi	30147
NEC	30043, 30234
Nikko	30174, 30170, 30164, 30625
NSM	30157
Onkyo	30868, 30101
Optimus	31063, 30000, 30032, 30037, 30342,
	30437, 31075, 30145, 30194, 30305,
	30426, 30087, 30179, 30280, 30420,
D:	30468, 30175, 30196
Panasonic	30029, 30752, 30303 30420, 30194
Parasound Philips	30626, 30157, 30287
	31063, 31062, 30032, 30305, 30468, 31087
Pioneer Polk Audio	30157
Proton	30157
QED	30157
Quad	30157
Ouasar	30029
RadioShack	31075
RCA	31062, 30032, 30305, 30764, 30179,
	30468, 30009, 30155, 30420, 30053
Realistic	30164, 30180, 30155, 30179, 30175, 30420
Rotel	30157, 30420
SAE	30157
Sansui	30157, 30305, 30202
Sanyo	30179, 30087
SAST	30157
Scott	30305, 30164, 30155
Sears	30305
Sharp	30861, 30037, 30180
Sherwood	31067, 30196, 30180, 30426
Shure Silsonic	30043
Sonic Frontiers	30888,30036 30157
	30490, 30000, 31364, 30185, 30605,
Sony	30100, 30604
Soundesign	30425,30145
STS	30018
Symphonic	30305
TAG McLaren	30157
Tascam	30420
TDK	31208
Teac	30393, 30180, 30174, 30420
Technics	30029, 30207, 30303
Tivoli Audio	31553
Vector Research	30194, 30417
Victor	30072
Wards	30157, 30053
Yamaha	30888, 30036, 30187, 30170, 31292
YBA	30625
Yorx	30461
Zonda	30157
Setup Cod	es for DVD Players
Adcom	21094
Advent	21016
Aiwa	20641,21912
Akai	20899, 20770, 21975, 21089
Allegro	20869
	Wl 22016 22001
Amphion Media	WOFKS 22010, 22001

21094
21016
20641, 21912
20899, 20770, 21975, 21089
20869
Works 22016, 22001
20872, 22016, 22001, 21176
21913
20672, 20717, 20797, 21020, 21100, 20796, 21004, 21061, 21937, 20794,
20830, 21056, 21915, 20755
21168
20736
21071, 21122, 21041, 21121, 21072
21071,21072
20662, 20655
n 21571
20717
20571
20868, 20695
dworks 21916

20627, 2106 20876, 20869

20778, 21107, 21086, 21923, 20852, 21165 21023, 21129, 20816, 21117, 21024 CyberHome 20784, 20869, 20833, 21918, 21172, 20705 20490, 20634 21085, 21068 DVD2000 20591, 20675, 20821 20670, 21919

21077, 21073, 21158

20522, 20815, 20717

Go Video 20744, 20869, 21099, 21970, 20715,	Chaparral 00216	Changfeng	10817, 10264	JBL	10054	Pilot	10030, 10019, 10039	Tongguang	10264	GoldStar	20037, 20209, 20038, 20226, 20225, 21237		21014
20833, 21075, 21730, 20783, 21044, 21144	Crossdigital 01109	Changhai	10817	JCB	10000	Pioneer	10166, 10038, 10866, 10679	Toshiba	10154, 11256, 10156, 10060, 10145, 11918,	Gradiente	20000	Samtron	20643
GPX 20699, 20769 Greenhill 20717	DirecTV 00392, 00566, 00639, 01639, 01142, 00247, 00749, 01749, 00724, 00819, 01856, 01076,	Changhong	10156, 10765, 10817, 10264, 10783, 10767, 11910	Jean	10156, 10051, 10236, 10092, 10179, 10003, 10474	Portland Prima	10092, 10039, 10019 10761, 10815, 10783, 11933, 10817		11945, 10381, 10832, 10036, 11704, 11936, 10264, 10650, 11150, 11656, 11935, 10161,	Haojie Harlev Davids	20240 Ison 20000	Sanky Sansui	20048, 20039 20000, 20067, 20209, 20041, 20479, 20271,
Harman/Kardon 20582, 20702	01109, 00099, 01444, 01108, 01392, 01443, 01640, 01442, 01414	0	10817	Jensen	10761, 10815, 11933, 10817	Princeton	10717, 10700	Toconic	10509, 10845, 11356 10185		don 20081, 20038		21479
Hitachi 20573, 20664, 21919 Hiteker 20672	Dish Network System 01005, 00775, 01775, 01505, 01170		10003, 10474, 10179, 10092 10000, 10180, 10161, 10474, 11150, 10092,	Jiahua Jialicai	10051 10264	Prism	10051	Tosonic Totevision	10039	Harwood	20072, 20068	Sanyo	20047, 20240, 20104, 20046, 20159, 20369, 20368
Initial 20717, 21931	Dishpro 01005, 00775, 01505, 01775		10843, 10003, 10179, 10700	Jinfeng	10051,10817	Proscan Proton	11447, 10047, 11347, 11922 10030, 10178, 10001, 10039, 10466, 10003,	Trical	10157	Hauppauge Headquarter	21992 20046	Scott	20184, 20045, 20121, 20043, 20210, 20212
Integra 20627, 21924	Echostar 01005, 00775, 01170, 01775, 01505 Expressvu 00775, 01775		10264 10180, 10053, 11150, 10036, 10474	Jinhai	11910		10052, 10474	Tuntex TVS	10030, 10474, 10092 10463	Hewlett Packa	ard 21972	Sears	20035, 20037, 20047, 20000, 20042, 20104, 20046, 20066, 21237, 20054, 20105
Jamo 22003 Jaton 21078	Funai 00338	***************************************	10180, 10053, 11150, 10036, 10474	Jinque Jinta	10817, 10264 10264, 11910	Pulsar Qingdao	10017, 10019 10051, 10817, 10264	Ultra	10391	HI-Q Hitachi	20047 20037, 20000, 20042, 20041, 20166, 20105,	Sharp	20048, 20209, 20363, 20848, 20807, 20062,
JBL 21926, 20702	GE 00566 General Instrument 00869	Cinema	10672	Jinxing	10054, 10156, 10145, 10264, 10037, 10817	Quasar	10250, 10051, 11924, 10165, 11919, 10055,	Universal V Inc	10027		20089	Shinco	20738, 21048 20000
Jensen 21016 IVC 20558, 20623, 21940, 21901, 20867	General Instrument 00869 GOI 00775, 01775		10060, 10030, 10039, 10280, 10056, 10186, 10046, 10092, 11928	Juhua IVC	10817, 10264 10053, 10160, 11923, 11253, 10036, 10653	RadioShack	10650 10047, 10154, 10180, 10030, 10178, 10032,	V Inc. Vector Research	11756, 10885, 10864 h 10030	Howard Comp	puters 21972 21972	Shinco	20072
jWin 21051, 21049	Goodmans 01246	Clairtone	10185	JVC Kaige	10053, 10160, 11923, 11253, 10036, 10653 10264, 10817		10056, 11920, 10165, 11904, 10019, 10039	Victor	10250, 10053, 10160, 10650, 10376, 10036,	HTS	21972 21944	Shogun	20240
Kenwood 20490, 20534, 21063, 20682	Hisense 01535 Hitachi 00819,01250,00214,00491,00489,00201	Clarion Colt	10180 11906	Kangchong	11910	RCA	11447, 10047, 11454, 10000, 10030, 10178, 10679, 11247, 11917, 10090, 11948, 11147,	Vidikron	10653	Q	ork Systems 20042, 21949, 20739	Singer Sonic Blue	20072 20614,20616
KLH 20717, 21939, 21149, 21020 Konka 20720, 20719, 20711, 20721	HTS 00775,01775	Concerto	10056	Kangli Kangyi	10001, 10817, 10391, 10264 10264		10019, 11907, 11922, 10135, 11958,	Vidtech	10178, 10019, 10036	Hyundai iBUYPOWER	וכעוב 21972	Sony	20035, 20032, 20033, 20000, 20253, 20639,
Koss 20651	Hughes Network Systems 01142, 00749, 01749, 01443, 01442,	Conrowa	10156, 10145, 10264	Kaypani	10052		11047,11347, 10018, 11547, 10038, 11919, 10092, 11953	Viewsonic Viking	10857,11755,10885,10864 10046	Jensen	20041		21232, 21972, 20636, 21032, 21957, 20034, 20586, 20640, 21956
Landel 20826 Lasonic 20798, 21173			10180, 10157, 10185 10180, 10161	KEC Kenwood	10180 10030, 10019	Realistic	10154, 10180, 10030, 10178, 10056, 10019,	Viking Wards	10046 10054, 10030, 10178, 10020, 10080, 10165,	JVC	20045, 20067, 20041, 21945, 20008, 21944, 20384, 20366	STS	20042
Lasonic 20798, 21173 Lenoxx 21938	JVC 00775,01170,00492,01775	Crosley	10054	KLH	10030, 10019 10765, 10767	Rhapsody	10039, 10165, 10032 10185		10866, 10019, 10027, 10056, 10111, 10179, 10016, 10021, 10096	KEC	20037, 20278	Sunpak Sylvania	20253 20035, 20081, 20000, 20043, 20110, 21781,
LG 20801,20101	LG 01414,01226 Magnavox 00724,00722		10180, 10039 10047, 10054, 10154, 10451, 10093, 10060,	KLL	10037	Rowa	10748, 10037, 10817	Warumaia	10391	Kenwood KLH	20067, 20041, 20038, 20384 20072		21593, 20593
Liquid Video 21980 Lite-On 21158, 21058	Matsushita 00340,00214,00500		10702, 10030, 10145, 10166, 10466, 11347,	Kloss Kolin	10046, 10024 10180, 10053, 11150, 10036, 10474	Runco Ruyi	10017, 10030, 10603, 10497 10817	Waycon Westinghouse	10156	KLH Kodak	20072 20035, 20037	Symphonic Systemax	20000, 21593, 20593 21972
Loewe 20511	Memorex 00724 Mitsubishi 00749,00491		10039, 10056, 11147, 10016, 11919 10180	Kongque	10264, 10817	Saige	10817	Westinghouse White Westingho	10889 house 10463, 10186, 11909, 10623	Kolin	20043, 20041	Tagar Systems	21972
Magnavox 20503, 20675, 21976, 21914, 20821 Malata 21159, 20782	Motorola 00869	Daewoo	10154, 10451, 10180, 10030, 10178, 11661,	- Konka	10632, 10707, 11940, 10628, 10703, 11939, 10638, 10817	Sampo	10154, 10093, 10030, 10178, 10171, 10032, 10052, 10474, 11755, 10039, 10700, 10036,	Xiahua	10817, 10264	ГР	20037, 20045, 20042, 20209, 20038, 22010, 21037, 20040	Tashiko	20037
Marantz 20539	NEC 00496,01270		10474, 10003, 10628, 10032, 11150, 10092, 11928, 10627, 10700, 10056, 11909, 10170,	KTV	10180, 10030, 10185, 10039, 10280		10092, 10650	Xiangyang Xihu	10264 10817, 10264	Lloyd's	20000, 20208	Tatung Teac	20045, 20067, 20041, 20366, 20008 20000, 20041
Memorex 20695	Next Level 00869 Panasonic 00247, 00701, 00214, 00500, 00340		10391, 10623, 10019, 10672, 10039	Kuaile Kunlun	10264 10051, 10817, 10264	Samsung	10154, 10156, 10060, 10812, 10702, 10030, 10178, 10019, 10056, 11060, 10092, 10474,	Xinghai	10264	Logik LXI	20072 20037	Technics	20035, 20162
Mintek 20839, 20717	Paysat 00724	Daytron Dayu	10019 10391	LG	10060, 10030, 10178, 10056, 10442, 10856,		10774, 10032, 10817, 10090, 11903, 10264,	Xinrisong	11910 11910	Magnasonic	21278, 20593	Teco Teknika	20035, 20037, 20048, 20041, 20038, 20040 20035, 20037, 20000, 20052
Mitsubishi 21521,20521	Philips 01142,00749,01749,00724,01076,00722, 00099,01442	Dell	11080	-	10001, 10038, 10700, 10019, 10037, 10474, 11178, 10003, 10032, 10006	Samsux	10766, 10814, 11150, 10179 10039	Xuelian Yamaha	10030, 10838, 10019, 10833, 10769, 10839	Magnavox	20035, 20039, 20081, 20000, 20593, 20563, 20110, 21781	Thomas	20000
Momitsu 21082 NEC 20785	Proscan 00392, 00566		10145, 10511 10017, 10019	- Lihua	10817	Sanjian	10264	Yapshe	10250	Magnin	20240	Tivo TMK	20739, 21957, 20636, 21956, 20618, 21503
Nesa 20717	Proton 01535 RadioShack 00869	Durabrand	10463, 10180, 10178, 10171, 11034, 10003	Lloyd's	11904 10136	Sansui Sanyo	10463, 11904, 11929, 11911 10154, 10156, 10180, 10145, 10376, 10474,	Yongbao Youlanasi	11910 10817	Marantz Marta	20035, 20081, 21381 20037	TMK Toshiba	20240, 20208, 20036 20045, 20067, 20043, 20041, 20210, 20384,
Next Base 20826 Nim 22024	RCA 00392, 00566, 00855, 00143, 01392	Dwin	10774, 10720	Loewe Logik	10016	Junyo	10036, 10893, 11907, 10159, 10280, 10424,	Yousida	11910	Marta Matsushita	20037 20035, 20162, 20226, 21162, 20367, 20227		21008, 21972, 20366, 20845, 21503, 20066,
Niro 22024 Norcent 21003, 20872, 21923, 21107	Samsung 01276, 01109, 01108		10037 10000, 10185	Longjiang	10264, 10817		10799, 11154, 10157, 10264, 10381, 10798, 10088, 11150	Zenith	10017, 10463, 10178, 11911, 10016, 11909, 10092, 11904, 11929	Media Center	r PC 21972	Totevision	20212, 20828, 21145, 20008 20037, 20240
Onkyo 20503, 20627, 21924, 20792, 21985	Sanyo 00493,01219 Sharp 00494	Electrohome	10381	Luxman LXI	10056 10047, 10054, 10154, 10156, 10178	Sanyuan	10093, 10817	Zonda	10092, 11904, 11929	MEI Memorex	20035 20035, 20162, 20037, 20048, 20039, 20047,	Touch	21972
Oritron 20651,21980 Panasonic 20490,21462,21907,21910,21990,21362,	SKY 00856		10017, 11661 10154, 10236, 10463, 10180, 10178, 10171,	Magnasonic	11928, 11913	Scimitsu Scotch	10019 10178		des for VCRs	OFCX	20240, 20000, 20104, 20209, 21237, 20046,	UltimateTV Unitech	21989 20240
21762, 21909, 21986, 20632, 21490, 21908,	Sony 00639, 01639, 00294, 01640, 00163 Star Choice 00869		10280, 10623, 10038, 11911, 11944, 10179,	Magnavox	11454, 10054, 10030, 10706, 11904, 10020, 11944, 10036, 10179, 10386, 11931, 10096,	Scott	10236, 10180, 10178, 10179, 10019	ABS	21972		20479, 21162, 20348, 21048, 21262, 20307, 21037	Vector	20045
21925, 22017 Philco 22000	Tivo 01142, 01444, 01443, 01442		10019, 11909, 11929, 10185, 10282, 11905, 10039, 11928, 10177		10187, 11254, 11913, 10024, 10186	Sears	10047, 10054, 10154, 10156, 10178, 10171, 11926, 11904, 10056, 10159, 10179	Admiral	20048, 20209	MGA MCN Tochnol	20240, 20043, 20061	Vector Research Victor	
Philips 20503, 20539, 20646, 20885, 20854, 21914	Toshiba 00749, 01749, 00790, 00486, 01285	Envision	10030, 10813	Magnin Maiestic	11907 10016	Shancha	10817, 10264	Adventura Aiko	20000 20278	MGN Technol Microsoft	ology 20240 21972	Video Concepts	s 20045, 20040, 20061
Pioneer 20525, 20571, 20638, 20632, 20631, 21902 Polaroid 21086, 21061, 21998, 21200	UltimateTV 01392, 01640 Uniden 00724, 00722		10833, 10840 10030, 10161, 10003	Majestic Marantz	10054, 10030, 10854, 10704, 11154, 10855	Shanghai	10264, 11910, 10817	Aiwa	20037, 20000, 20307, 20468, 20124, 20406,	Mind	21972	Videomagic	20037
Polk Audio 20539	US Digital 01535	. Feilu	10817	Maruman	10627, 10391	Shaofeng Sharp	10145, 10817 10093, 10030, 10157, 10386, 10650, 10720,	Akai	20348, 20479 20041, 20061, 20175, 20106	Minolta	20042, 20105	Videosonic Viewsonic	20240 21972
Portland 20770	USDTV 01535	. Feiyan	10264	Matsushita	10250, 10650, 10161	P			, =0 , =0100	Mitsubishi	20067, 20043, 20041, 20061, 20807, 20173		20000
Prima 21016	Victor 00492		10817	Weasson	10700		10032, 10851, 10256, 10491, 10689, 10818, 10039, 10165, 10474, 10688, 10787, 10036	Alienware	21972	Motorola	20035, 20048	Villain	
Princeton 20674	Voom 00869	/	10817 10236	Megapower Megatron	10700 10178, 10145, 10003		10039, 10165, 10474, 10688, 10787, 10036, 11917	America Action	21972 n 20278	MTC	20240, 20000	Villain Wards	20060, 20035, 20048, 20047, 20081, 20240, 20000, 20042, 20072, 20062, 20212, 20760
Proscan 20522		Firstar Fisher	10236 10154, 10159	Megatron MEI	10700 10178, 10145, 10003 10185	Sharper Image	10039, 10165, 10474, 10688, 10787, 10036, 11917 ge 11950		21972 n 20278			Wards White Westingh	20060, 20035, 20048, 20047, 20081, 20240, 20000, 20042, 20072, 20062, 20212, 20760 couse 20209, 20072, 20637
Proscan 20522 ProVision 20778	Voom 00869	Firstar Fisher Fortress	10236 10154, 10159 10093	Megatron	10700 10178, 10145, 10003 10185 10264, 11910, 10817 10154, 10463, 10150, 10178, 10179, 11920,	Sharper Image Shen Ying Shencai	10039, 10165, 10474, 10688, 10787, 10036, 11917	America Action American High Amoisonic Anam	21972 n 20278 h 20035 20479 20162, 20037, 20240, 20278, 20226, 21037	MTC Multitech NAD National	20240, 20000 20000, 20072 20058 20226	Wards White Westingh XR-1000	20060, 20035, 20048, 20047, 20081, 20240, 20000, 20042, 20072, 20062, 20212, 20760 20082, 20209, 20072, 20637 20035, 20000, 20072
Proscan 20522 ProVision 20778 Qwestar 20651 RCA 20522, 20571, 20717, 20822, 21193, 21974,	Voom 00869 Zenith 00856, 01856 Setup Codes for TVs 888 10264	Firstar Fisher Fortress Fujitsu Funai	10236 10154, 10159 10093 10186, 10853, 10179, 10809, 10683 10180, 10171, 10264, 11904, 10179, 10342	Megatron MEI Meile Memorex	10700 10178, 10145, 10003 10185 10264, 11910, 10817 10154, 10463, 10150, 10178, 10179, 11920, 11927, 10016, 11911, 11926, 11924	Shen Ying Shencai Sheng Chia	10039, 10165, 10474, 10688, 10787, 10036, 11917 ge 11950 10092, 10003, 10474, 10179 10145, 10264 10093, 10236, 10179, 11150, 10474	America Action American High Amoisonic	21972 n 20278 h 20035 20479 20162, 20037, 20240, 20278, 20226, 21037	MTC Multitech NAD	20240, 20000 20000, 20072 20058	Wards White Westingh	20060, 20035, 20048, 20047, 20081, 20240, 20000, 20042, 20072, 20062, 20212, 20760 20035, 20000, 20072, 20637 20035, 20000, 20072 20041, 20038 20039, 20033, 20000, 20209, 20034, 20479,
Proscan 20522 ProVision 20778 Qwestar 20651 RCA 20522, 20571, 20717, 20822, 21193, 21974, 21132, 21965, 21022, 21913	Voom 00869 Zenith 00856,01856 Setup Codes for TVs 888 10264 A-Mark 10003	Firstar Fisher Fortress Fujitsu Funai Furi	10236 10154,10159 10093 10186,10853,10179,10809,10683 10180,10171,10264,11904,10179,10342 10145,10817,10264	Megatron MEI Meile	10700 10178, 10145, 10003 10185 10264, 11910, 10817 10154, 10463, 10150, 10178, 10179, 11920,	Shen Ying Shencai Sheng Chia Shenyang	10039, 10165, 10474, 10688, 10787, 10036, 11917 ge 11950 10092, 10003, 10474, 10179 10145, 10264	America Action American High Amoisonic Anam Anam National Asha Audiovox	21972 n 20278 h 20035 20479 20162, 20037, 20240, 20278, 20226, 21037 1 20162, 20226 20240 20037, 20278	MTC Multitech NAD National NEC	20240, 20000 20000, 20072 20058 20226 20035, 20037, 20048, 20104, 20067, 20041, 20038, 20040, 20008, 20370 20037	Wards White Westingh XR-1000 Yamaha Zenith	20060, 20035, 20048, 20047, 20081, 20240, 20000, 20042, 200772, 20062, 20212, 20760 20035, 20000, 20072, 20637 20035, 20000, 20072 20041, 20038 20039, 20039, 20039, 20039, 20039, 20039, 20039, 20039, 20039, 20039, 20039
Proscan 20522 ProVision 20778 Qwestar 20651 RCA 20522, 20571, 20717, 20822, 21193, 21974,	Voom 00869 Zenith 00856, 01856 Setup Codes for TVs 888 10264	Firstar Fisher Fortress Fujitsu Funai Furi	10236 10154, 10159 10093 10186, 10853, 10179, 10809, 10683 10180, 10171, 10264, 11904, 10179, 10342	Megatron MEI Meile Memorex Mermaid MGA Midland	10700 10178, 10145, 10003 10185 10264, 11910, 10817 10154, 10463, 10150, 10178, 10179, 11920, 11927, 10016, 11911, 11926, 11924 10037 10150, 10030, 10178, 11907, 10019 10047, 10017, 10051, 10039, 10135, 10032	Shen Ying Shencai Sheng Chia	10039, 10165, 10474, 10688, 10787, 10036, 11917 ge 11950 10092, 10003, 10474, 10179 10145, 10264 10093, 10236, 10179, 11150, 10474 10817, 10264 10019 10016	America Action American High Amoisonic Anam Anam National Asha Audiovox Beaumark	21972 n 20278 h 200278 c 20479 20162, 20037, 20240, 20278, 20226, 21037 n 20162, 20226 20240 20240 20037, 20278 20240	MTC Multitech NAD National NEC	20240, 20000 20000, 20072 20058 20226 20035, 20037, 20048, 20104, 20067, 20041, 20038, 20040, 20008, 20370 20037	Wards White Westingh XR-1000 Yamaha Zenith ZT Group	20060, 20035, 20048, 20047, 20081, 20240, 20000, 20042, 20072, 20062, 20212, 20760 100use 20209, 20072, 20637 20035, 20000, 20072 20041, 20038 20039, 20033, 20000, 20209, 20034, 20479, 21139, 20637 21972
Proscan 20522 ProVision 20778 Qwestar 20651 RCA 20522, 20571, 20717, 20822, 21193, 21974, 21132, 21965, 21022, 21913 Regent 21338 Rio 20869 Rotel 20623	Voom 00869 Zenith 00856,01856 Setup Codes for TVs 888 10264 A-Mark 10003 Abex 10032 Addison 11150,10653,10092 Admiral 10093,10463	Firstar Fisher Fortress Fujitsu Funai Furi Futuretech Ganxin Gateway	10236 10154, 10159 10093 10186, 10853, 10179, 10809, 10683 10180, 10171, 10264, 11904, 10179, 10342 10145, 10817, 10264 10180 10817 11756, 11755	Megatron MEI Meile Memorex Mermaid MGA	10700 10178, 10145, 10003 10185 10264, 11910, 10817 10154, 10463, 10150, 10178, 10179, 11920, 11927, 10016, 11911, 11926, 11924 10037 10150, 10030, 10178, 11907, 10019	Shen Ying Shencai Sheng Chia Shenyang Shogun Signature Simpson	10039, 10165, 10474, 10688, 10787, 10036, 11917 ge 11950 10092, 10003, 10474, 10179 10145, 10264 10093, 10236, 10179, 11150, 10474 10817, 10264 10019 10016 10187, 10186	America Action American High Amoisonic Anam Anam National Asha Audiovox	21972 n 20278 h 20035 20479 20162, 20037, 20240, 20278, 20226, 21037 nl 20162, 20226 20240 20037, 20278 20240 20104 20226	MTC Multitech NAD National NEC	20240, 20000 20000, 20072 20058 20226 20035, 20037, 20048, 20104, 20067, 20041, 20038, 20040, 20008, 20370 20037	Wards White Westingh XR-1000 Yamaha Zenith ZT Group Setup Cod	20060, 20035, 20048, 20047, 20081, 20240, 20000, 20042, 200772, 20062, 20212, 20760 20035, 20000, 20072 20041, 20035, 20000, 20072 20041, 20038 20039, 20033, 20000, 20209, 20034, 20479, 21479, 21139, 20637 21972 2008 2008 2008 2008 2008 2008 2008 20
Proscan 20522 ProVision 20778 Qwestar 20651 RCA 20522, 20571, 20717, 20822, 21193, 21974, 21132, 21965, 21022, 21913 Regent 2138 Rio 20869	Voom 00869 Zenith 00856,01856 Setup Codes for TVs 888 10264 A-Mark 10003 Abex 10032 Addison 11150, 10653, 10092	Firstar Fisher Fortress Fujitsu Funai Furi Futuretech Ganxin Gateway GE	10236 10154, 10159 10093 10186, 10853, 10179, 10809, 10683 10180, 10171, 10264, 11904, 10179, 10342 10145, 10817, 10264 10180 10817 11756, 11755 11447, 10047, 11454, 10051, 10451, 10180, 10030, 10178, 10092, 11147, 11919, 10055,	Megatron MEI Meile Memorex Mermaid MGA Midland Minutz	10700 10178, 10145, 10003 10185 10264, 11910, 10817 10154, 10463, 10150, 10178, 10179, 11920, 11927, 10016, 11911, 11926, 11924 10037 10150, 10030, 10178, 11907, 10019 10047, 10017, 10051, 10039, 10135, 10032 10021 10154, 10250, 10093, 10236, 10180, 11250, 10150, 10030, 10178, 10381, 10836, 10036,	Shen Ying Shencai Sheng Chia Shenyang Shogun Signature	10039, 10165, 10474, 10688, 10787, 10036, 11917 ge 11950 10092, 10003, 10474, 10179 10145, 10264 10093, 10236, 10179, 11150, 10474 10817, 10264 10019 10016	America Action American High Amoisonic Anam Anam National Asha Audiovox Beaumark Bell & Howell	21972 n 20278 h 200278 b 200479 20162, 20037, 20240, 20278, 20226, 21037 ll 20162, 20226 20240 20037, 20278 20240 20104 20104 20126 20184, 20121, 20209, 20002, 20348, 20295,	MTC Multitech NAD National NEC Newave Nikko Nikko Nikon Noblex Northgate	20240, 20000 20000, 20072 20058 20256 2025, 20037, 20048, 20104, 20067, 20041, 20038, 20040, 20008, 20370 20037 20253, 20034 20240 21972	Wards White Westingh XR-1000 Yamaha Zenith ZT Group	20060, 20035, 20048, 20047, 20081, 20240, 20000, 20042, 20072, 20062, 20212, 20760 20035, 20000, 20072, 20637 20035, 20000, 20072 20041, 20038 20039, 20033, 20000, 20209, 20034, 20479, 21139, 20637 21972
Proscan 20522 ProVision 20778 Questar 20651 RCA 20522, 20571, 20717, 20822, 21193, 21974, 21132, 21965, 21022, 21913 Regent 21938 Rio 20869 Rotel 20623 Rowa 20823 Saba 21977 Sampo 20752, 20698	Voom 00869 Zenith 00856, 01856 Setup Codes for TVs 888 10264 A-Mark 10003 Abex 10032 Addison 11150, 10653, 10092 Admiral 10093, 10463 Advent 10761, 10817, 10815, 11933, 10783, 10842 Adventura 10046 Aiko 10092	Firstar Fisher Fortress Fujitsu Funai Furi Futuretech Ganxin Gateway GE	10236 10154, 10159 10093 10186, 10853, 10179, 10809, 10683 10180, 10171, 10264, 11904, 10179, 10342 10145, 10817, 10264 10180 10817 11756, 11755 11447, 10047, 11454, 10051, 10451, 10180, 10030, 10178, 10092, 11147, 11919, 10055, 10027, 11917, 10135, 10282, 11347, 10021,	Megatron MEI Meile Memorex Mermaid MGA Midland Minutz	10700 10178, 10145, 10003 10185 10264, 11910, 10817 10154, 10463, 10150, 10178, 10179, 11920, 11927, 10016, 11911, 11926, 11924 10037 10150, 10030, 10178, 11907, 10019 10047, 10017, 10051, 10039, 10135, 10032 10021 10154, 10250, 10093, 10236, 10180, 11250,	Shen Ying Shencai Sheng Chia Shenyang Shogun Signature Simpson Skygiant	10039, 10165, 10474, 10688, 10787, 10036, 11917 ge 11950 10092, 10003, 10474, 10179 10145, 10264 10093, 10236, 10179, 11150, 10474 10817, 10264 10019 10016 10187, 10186 10180 10748, 10264, 10037, 10817 11100, 10000, 10036, 10650, 11300, 10111,	America Action American High Amoisonic Anam Anam National Asha Audiovox Beaumark Bell & Howell Blaupunkt	21972 n 20278 h 20035 20479 20162, 20037, 20240, 20278, 20226, 21037 nl 20162, 20226 20240 20037, 20278 20240 20104 20104 20226 20184, 20121, 20209, 20002, 20348, 20295, 21479, 20479 20037	MTC Multitech NAD National NEC Newave Nikko Nikon Noblex	20240, 20000 20000, 20072 20058 20226 20035, 20037, 20048, 20104, 20067, 20041, 20038, 20040, 20008, 20370 20037 20037 20253, 20034 20240	Wards White Westingh XR-1000 Yamaha Zenith ZT Group Setup Cod ABS Alienware CyberPower	20060, 20035, 20048, 20047, 20081, 20240, 20000, 20042, 200772, 20062, 20212, 20760 rouse 20209, 20072, 20637 20035, 20000, 20072 20041, 20038 20039, 20033, 20000, 20209, 20034, 20479, 21479, 21139, 20637 21972 des for Video Accessories 01272 01272 01272
Proscan 20522 ProVision 20778 Qwestar 20651 RCA 20522, 20571, 20717, 20822, 21193, 21974, 21132, 21965, 21022, 21913 Regent 21938 Rio 20869 Rotel 20623 Rowa 20823 Saba 21977	Voom 00869 Zenith 00856,01856 Setup Codes for TVs 888 10264 A-Mark 10003 Abex 10032 Addison 11150, 10653, 10092 Admiral 10093, 10463 Advent 10761, 10817, 10815, 11933, 10783, 10842 Adventura 10046 Aiko 10092 Aiwa 11914, 11910	Firstar Fisher Fortress Fujitsu Funai Furi Futuretech Ganxin Gateway GE	10236 10154, 10159 10093 10186, 10853, 10179, 10809, 10683 10180, 10171, 10264, 11904, 10179, 10342 10145, 10817, 10264 10180 10817 11756, 11755 11447, 10047, 11454, 10051, 10451, 10180, 10030, 10178, 10092, 11147, 11919, 10055,	Megatron MEI Meile Memorex Mermaid MGA Midland Minutz Mitsubishi	10700 10178, 10145, 10003 10185 10264, 11910, 10817 10154, 10463, 10150, 10178, 10179, 11920, 11927, 10016, 11911, 11926, 11924 10037 10150, 10030, 10178, 11907, 10019 10047, 10017, 10051, 10039, 10135, 10032 10021 10154, 10250, 10093, 10236, 10180, 11250, 10150, 10030, 10178, 10381, 10836, 10036, 10179, 10817, 11150, 10474, 10019, 10868, 10056, 11917 10843, 10700	Shen Ying Shencai Sheng Chia Shenyang Shogun Signature Simpson Skygiant Skyworth	10039, 10165, 10474, 10688, 10787, 10036, 11917 2e 11950	America Action American High Amoisonic Anam Anam National Asha Audiovox Beaumark Bell & Howell Blaupunkt Broksonic Calix Canon	21972 n 20278 h 200278 b 200479 20162, 20037, 20240, 20278, 20226, 21037 ll 20162, 20226 20240 20037, 20278 20240 20104 20104 20126 20184, 20121, 20209, 20002, 20348, 20295, 21479, 20479 20037 20035, 21174, 20167	MTC Multitech NAD National NEC Newave Nikko Nikoo Noblex Northgate Olympus	20240, 20000 20000, 20072 20058 20256 20035, 20037, 20048, 20104, 20067, 20041, 20038, 20040, 20008, 20370 20037 20037 20253, 20034 20240 21972 20035, 20226, 21046 20222 21062, 20162, 20037, 20048, 20104, 21048,	Wards White Westingh XR-1000 Yamaha Zenith ZT Group Setup Cod ABS Alienware CyberPower Gateway	20060, 20035, 20048, 20047, 20081, 20240, 20000, 20042, 20072, 20062, 20212, 20760 20005, 2009, 20072, 20637 20035, 20000, 20072 20041, 20038 20039, 20033, 20000, 20209, 20034, 20479, 21479, 21139, 20637 21972 20090, 20
Proscan 20522 ProVision 20778 Qwestar 20651 RCA 20522, 20571, 20717, 20822, 21193, 21974, 21132, 21965, 21022, 21913 Regent 21938 Rio 20869 Rotel 20623 Rowa 20823 Saba 21977 Sampo 20752, 20698 Sansung 20490, 20573, 20820, 21932, 21075, 20899, 21979 Sansui 20695	Voom 00869 Zenith 00856, 01856 Setup Codes for TVs 888 10264 A-Mark 10003 Abex 10032 Addison 11150, 10653, 10092 Admiral 10093, 10463 Advent 10761, 10817, 10815, 11933, 10783, 10842 Adventura 10046 Aiko 10092	Firstar Fisher Fortress Fujitsu Funai Furi Futuretech Ganxin Gateway GE	10236 10154, 10159 10093 10186, 10853, 10179, 10809, 10683 10180, 10171, 10264, 11904, 10179, 10342 10145, 10817, 10264 10180 10817 11756, 11755 11447, 10047, 11454, 10051, 10451, 10180, 10030, 10178, 10092, 11147, 11919, 10055, 10027, 11917, 10135, 10282, 11347, 10021, 11907, 11922 10186 10017, 10030, 10019	Megatron MEI Meile Memorex Mermaid MGA Midland Minutz Mitsubishi	10700 10178, 10145, 10003 10185 10264, 11910, 10817 10154, 10463, 10150, 10178, 10179, 11920, 11927, 10016, 11911, 11926, 11924 10037 10150, 10030, 10178, 11907, 10019 10047, 10017, 10051, 10039, 10135, 10032 10021 10154, 10250, 10093, 10236, 10180, 11250, 10150, 10030, 10178, 10381, 10386, 10036, 10179, 10817, 11150, 10474, 10019, 10868, 10056, 11917	Shen Ying Shencai Sheng Chia Shenyang Shogun Signature Simpson Skygiant Skyworth Sony	10039, 10165, 10474, 10688, 10787, 10036, 11917 2e 11950 10092, 10003, 10474, 10179 10145, 10264 10093, 10236, 10179, 11150, 10474 10817, 10264 10019 10016 10187, 10186 10180 10748, 10264, 10037, 10817 11100, 10000, 10036, 10650, 11300, 10111, 11925, 10080, 10834, 11904 10180, 10178, 10179, 10186 10156, 10071, 10166	America Action American High Amoisonic Anam Anam National Asha Audiovox Beaumark Bell & Howell Blaupunkt Broksonic	21972 n 20278 h 20035 20479 20162, 20037, 20240, 20278, 20226, 21037 nl 20162, 20226 20240 20037, 20278 20240 20104 20104 20226 20184, 20121, 20209, 20002, 20348, 20295, 21479, 20479 20037	MTC Multitech NAD National NEC Newave Nikko Nikoo Noblex Northgate Olympus Onkyo Optimus	20240, 20000 20000, 20072 20058 20226 20035, 20037, 20048, 20104, 20067, 20041, 20038, 20040, 20008, 20370 20037 20037 20253, 20034 20240 21972 20035, 20226, 21046 20222	Wards White Westingh XR-1000 Yamaha Zenith ZT Group Setup Cod ABS Alienware CyberPower Gateway Hewlett Packard Howard Compu	20060, 20035, 20048, 20047, 20081, 20240, 20000, 20042, 20072, 20062, 20212, 20760 100use 20209, 20072, 20637 20035, 20000, 20072 20041, 20038 20039, 20033, 20000, 20209, 20034, 20479, 21479, 21139, 20637 21972 1les for Video Accessories 01272
Proscan 20522 ProVision 20778 Qwestar 20651 RCA 20522, 20571, 20717, 20822, 21193, 21974, 21132, 21965, 21022, 21913 Regent 21938 Rio 20869 Rotel 20623 Rowa 20823 Saba 21977 Sampo 20752, 20698 Samsung 20490, 20573, 20820, 21932, 21075, 20899, 21979 Sansui 20695 Sanyo 20695, 20670, 21967, 20873	Voom 00869 Zenith 00856,01856 Setup Codes for TVs 888 10264 A-Mark 10003 Abex 10032 Addison 11150,10653,10092 Admiral 10093,10463 Advent 10761,10817, 10815, 11933,10783, 10842 Adventura 10046 Aiko 10092 Aiwa 11914,11910 Akai 10812, 10702, 10030, 10672, 11903, 10264 Allaron 10179 Albatron 10843, 10700	Firstar Fisher Fortress Fujitsu Funai Furi Futuretech Ganxin Gateway GE	10236 10154, 10159 10093 10186, 10853, 10179, 10809, 10683 10180, 10171, 10264, 11904, 10179, 10342 10145, 10817, 10264 10180 10817 11756, 11755 11447, 10047, 11454, 10051, 10451, 10180, 10030, 10178, 10092, 11147, 11919, 10055, 10027, 11917, 10135, 10282, 11347, 10021, 11907, 11902	Megatron MEI Meile Memorex Mermaid MGA Midland Minutz Mitsubishi Monivision Motorola MTC Mudan	10700 10178, 10145, 10003 10185 10264, 11910, 10817 10154, 10463, 10150, 10178, 10179, 11920, 11927, 10016, 11911, 11926, 11924 10037 10150, 10030, 10178, 11907, 10019 10047, 10017, 10051, 10039, 10135, 10032 10021 10154, 10250, 10093, 10236, 10180, 11250, 10150, 10030, 10178, 10381, 10336, 10036, 10179, 10817, 11150, 10474, 10019, 10868, 10056, 11917 10843, 10700 10093, 10055 10060, 10030, 10185, 10019, 10056 10051, 10817, 10264	Shen Ying Shencai Sheng Chia Shenyang Shogun Signature Simpson Skygiant Skyworth Sony	10039, 10165, 10474, 10688, 10787, 10036, 11917 2e 11950 10092, 10003, 10474, 10179 10145, 10264 10093, 10236, 10179, 11150, 10474 10817, 10264 10019 10016 10187, 10186 10180 10748, 10264, 10037, 10817 11100, 10000, 10036, 10650, 11300, 10111, 11925, 10080, 10834, 11904 10180, 10178, 10179, 10186	America Action American High Amoisonic Anam Anam National Asha Audiovox Beaumark Bell & Howell Blaupunkt Broksonic Calix Canon Carver CCE Changhong	21972 n 20278 h 200278 h 20035 20479 20162, 20037, 20240, 20278, 20226, 21037 l 20162, 20226 20240 20037, 20278 20240 20104 20026 20184, 20121, 20209, 20002, 20348, 20295, 21479, 20479 20037 20035, 21174, 20167 20081 20072, 20278 20048, 20081	MTC Multitech NAD National NEC Newave Nikko Nikon Noblex Northgate Olympus Onkyo Optimus Optonica Orion	20240, 20000 20000, 20072 20058 20226 20035, 20037, 20048, 20104, 20067, 20041, 20038, 20040, 20008, 20370 20037 20037 20253, 20034 20240 21972 20035, 20226, 21046 20222 21062, 20162, 20037, 20048, 20104, 21048, 21262, 20593, 21162, 20058, 20432 20062 20184, 20209, 20002, 20479, 20295, 21479	Wards White Westingh XR-1000 Yamaha Zenith ZT Group Setup Cod ABS Alienware CyberPower Gateway Hewlett Packare Howard Compu	20060, 20035, 20048, 20047, 20081, 20240, 20000, 20042, 200772, 20062, 20212, 20760 nouse 20209, 20072, 20637 20035, 20000, 20072 20041, 20038 20039, 20033, 20000, 20209, 20034, 20479, 21479, 21139, 20637 21972 des for Video Accessories 01272 01272 01272 01272 d
Proscan 20522 ProVision 20778 Qwestar 20651 RCA 20522, 20571, 20717, 20822, 21193, 21974, 21132, 21965, 21022, 21913 Regent 21938 Rio 20869 Rotel 20623 Rowa 20823 Saba 21977 Sampo 20752, 20698 Samsung 20490, 20573, 20820, 21932, 21075, 20899, 21979 Sansui 20695 Sanyo 20695, 20670, 21967, 20873 Sharp 20630, 20752 Sharper Image 21995, 21117	Voom 00869 Zenith 00856, 01856 Setup Codes for TVs 888 10264 A-Mark 10003 Abex 10032 Addison 11150, 10653, 10092 Admiral 10093, 10463 Advent 10761, 10817, 10815, 11933, 10783, 10842 Adventura 10046 Aiko 10092 Aiwa 11914, 11910 Akai 10812, 10702, 10030, 10672, 11903, 10264 Alaron 10179	Firstar Fisher Fortress Fujitsu Funai Furi Furi Ganxin Gateway GE General Gibralter Gintai Go Video GoldStar	10236 10154, 10159 10093 10186, 10853, 10179, 10809, 10683 10180, 10171, 10264, 11904, 10179, 10342 10145, 10817, 10264 10180 10817 11756, 11755 11447, 10047, 11454, 10051, 10451, 10180, 10030, 10178, 10092, 11147, 11919, 10055, 10027, 11917, 10135, 10282, 11347, 10021, 11907, 11922 10186 10017, 10030, 10019 11150, 10474 10886 10154, 10030, 10178, 11926, 10019, 10037,	Megatron MEI Meile Memorex Mermaid MGA Midland Minutz Mitsubishi Monivision Motorola MTC	10700 10178, 10145, 10003 10185 10264, 11910, 10817 10154, 10463, 10150, 10178, 10179, 11920, 11927, 10016, 11911, 11926, 11924 10037 10150, 10030, 10178, 11907, 10019 10047, 10017, 10051, 10039, 10135, 10032 10021 10154, 10250, 10093, 10236, 10180, 11250, 10150, 10030, 10178, 10381, 10836, 10036, 10179, 10817, 11150, 10474, 10019, 10868, 10056, 11917 10843, 10700 10039, 10055 10060, 10030, 10185, 10019, 10056	Shen Ying Shencai Sheng Chia Shenyang Shogun Signature Simpson Skygiant Skyworth Sony Soundesign Sowa Spectricon Squareview	10039, 10165, 10474, 10688, 10787, 10036, 11917 3e 11950	America Action American High Amoisonic Anam Anam National Asha Audiovox Beaumark Bell & Howell Blaupunkt Broksonic Calix Canon Carver CCE Changhong Citizen	21972 n 20278 h 200278 h 20035 20479 20162, 20037, 20240, 20278, 20226, 21037 nl 20162, 20226 20240 20104 20226 20184, 20121, 20209, 20002, 20348, 20295, 21479, 20479 20037 20035, 21174, 20167 20081 20072, 20278	MTC Multitech NAD National NEC Newave Nikko Nikon Noblex Northgate Olympus Onkyo Optimus Optonica Orion Panarex	20240, 20000 20000, 20072 20058 20256 20035, 20037, 20048, 20104, 20067, 20041, 20038, 20040, 20008, 20370 20037 20037 20253, 20034 20240 21972 20035, 20226, 21046 20222 21062, 20162, 20037, 20048, 20104, 21048, 21262, 20593, 21162, 20058, 20432 20062 20184, 20209, 20002, 20479, 20295, 21479 21950	Wards White Westingh XR-1000 Yamaha Zenith ZT Group Setup Cod ABS Alienware CyberPower Gateway Hewlett Packard Howard Compu	20060, 20035, 20048, 20047, 20081, 20240, 20000, 20042, 200772, 20062, 20212, 20760 nouse 20209, 20072, 20637 20035, 20000, 20072 20041, 20038 20039, 20033, 20000, 20209, 20034, 20479, 21479, 21139, 20637 21972 des for Video Accessories 01272 01272 01272 01272 d
Proscan 20522 ProVision 20778 Qwestar 20651 RCA 20522, 20571, 20717, 20822, 21193, 21974, 21132, 21965, 21022, 21913 Regent 21388 Rio 20869 Rotel 20623 Rowa 20823 Saba 21977 Sampo 20752, 20698 Samsung 20490, 20573, 20820, 21932, 21075, 20899, 21979 Sansui 20695 Sanyo 20695, 20670, 21967, 20873 Sharp 20630, 20752 Sharper Image 21995, 21117 Sherwood 21043, 20770, 20633, 21077	Voom 00869 Zenith 00856, 01856 Setup Codes for TVs 888 10264 A-Mark 10003 Abex 10032 Addison 11150, 10653, 10092 Admiral 10093, 10463 Adventu 10761, 10817, 10815, 11933, 10783, 10842 Adventura 10046 Aiko 10092 Aiwa 11914, 11910 Akai 10812, 10702, 10030, 10672, 11903, 10264 Allaron 10179 Albatron 10843, 10700 Ambassador 10177 America Action 10180 Ampro 10751	Firstar Fisher Fortress Fujitsu Funai Furi Futuretech Ganxin Gateway GE General Gibralter Gintai Go Video GoldStar	10236 10154, 10159 10093 10186, 10853, 10179, 10809, 10683 10180, 10171, 10264, 11904, 10179, 10342 10145, 10817, 10264 10180 10817 11756, 11755 11447, 10047, 11454, 10051, 10451, 10180, 10030, 10178, 10092, 11147, 11919, 10055, 10027, 11917, 10135, 10282, 11347, 10021, 11907, 11922 10186 10017, 10030, 10019 11150, 10474 10886	Megatron MEI Meile Memorex MGA Midland Minutz Mitsubishi Monivision Motorola MTC Mudan Multitech NAD Nanbao	10700 10178, 10145, 10003 10185 10264, 11910, 10817 10154, 10463, 10150, 10178, 10179, 11920, 11927, 10016, 11911, 11926, 11924 10037 10150, 10030, 10178, 11907, 10019 10047, 10017, 10051, 10039, 10135, 10032 10021 10154, 10250, 10093, 10236, 10180, 11250, 10150, 10030, 10178, 10381, 10386, 10036, 10179, 10817, 11150, 10474, 10019, 10868, 10056, 11917 10843, 10700 10093, 10055 10060, 10030, 10185, 10019, 10056 10051, 10817, 10264 10180 10156, 10178, 10866 11910, 10264	Shen Ying Shencai Sheng Chia Shenyang Shogun Signature Simpson Skygiant Skyworth Sony Soundesign Sowa Spectricon	10039, 10165, 10474, 10688, 10787, 10036, 11917 2e 11950 10092, 10003, 10474, 10179 10145, 10264 10093, 10236, 10179, 11150, 10474 10817, 10264 10019 10016 10187, 10186 10180 10748, 10264, 10037, 10817 11100, 10000, 10036, 10650, 11300, 10111, 11925, 10080, 10834, 11904 10180, 10178, 10179, 10186 10156, 10051, 10060, 10178, 10036, 10092, 10474, 11150 10003	America Action American High Amoisonic Anam Anam National Asha Audiovox Beaumark Bell & Howell Blaupunkt Broksonic Calix Canon Carver CCE Changhong Citizen Colt Craig	21972 n 20278 h 20278 h 20278 h 20035 20479 20162, 20037, 20240, 20278, 20226, 21037 nl 20162, 20226 20240 20104 20226 20184, 20121, 20209, 20002, 20348, 20295, 21479, 20479 20037 20035, 21174, 20167 20081 20072, 20278 20048, 20081 20037, 20278, 21278 20049, 20047, 20240, 20072, 20271	MTC Multitech NAD National NEC Newave Nikko Nikon Noblex Northgate Olympus Onkyo Optimus Optonica Orion Panarex Panasonic	20240, 20000 20000, 20072 20058 20226 20035, 20037, 20048, 20104, 20067, 20041, 20038, 20040, 20008, 20370 20037 20037 20253, 20034 20240 21972 20035, 20226, 21046 20222 21062, 20162, 20037, 20048, 20104, 21048, 21262, 20593, 21162, 20058, 20432 20062 20184, 20209, 20002, 20479, 20295, 21479 21950 21062, 20035, 20162, 20077, 20226, 20616, 21162, 20225, 20367, 20227, 21035, 21262	Wards White Westingh XR-1000 Yamaha Zenith ZT Group Setup Cod ABS Alienware CyberPower Gateway Hewlett Packard Howard Compu HP iBUYPOWER InterVideo Jensen	20060, 20035, 20048, 20047, 20081, 20240, 20000, 20042, 20072, 20062, 20212, 20760 nouse 20209, 20072, 20637 20035, 20000, 20072 20041, 20038 20039, 20033, 20000, 20209, 20034, 20479, 21479, 21139, 20637 21972 les for Video Accessories 01272 01273 01274 01275 01275 01276 01277 01277 01277 01279 01393 01165
Proscan 20522 ProVision 20778 Qwestar 20651 RCA 20522, 20571, 20717, 20822, 21193, 21974, 21132, 21965, 21022, 21913 Regent 21938 Rio 20869 Rotel 20623 Rowa 20823 Saba 21977 Sampo 20752, 20698 Samsung 20490, 20573, 20820, 21932, 21075, 20899, 21979 Sansui 20695 Sanyo 20695, 20670, 21967, 20873 Sharp 20630, 20752 Sharper Image 21995, 21117	Voom 00869 Zenith 00856, 01856 Setup Codes for TVs 888 10264 A-Mark 10003 Abex 10032 Addison 11150, 10653, 10092 Admiral 10093, 10463 Advent 10761, 10817, 10815, 11933, 10783, 10842 Adventura 10046 Aiko 10092 Aiwa 11914, 11910 Akai 10812, 10702, 10030, 10672, 11903, 10264 Alaron 10179 Albatron 10843, 10700 Ambassador 10177 America Action 10180 Ampro 10751 Anam 10250, 10180, 10003, 10700, 10161, 10628	Firstar Fisher Fortress Fujitsu Funai Furi Futuretech Ganxin Gateway GE General Gibralter Gintai Go Video GoldStar Goodmans Grunpy	10236 10154, 10159 10093 10186, 10853, 10179, 10809, 10683 10180, 10171, 10264, 11904, 10179, 10342 10145, 10817, 10264 10180 10817 11756, 11755 11447, 10047, 11454, 10051, 10451, 10180, 10030, 10178, 10092, 11147, 11919, 10055, 10027, 11917, 10135, 10282, 11347, 10021, 11907, 11922 10186 10017, 10030, 10019 11150, 10474 10886 10154, 10030, 10178, 11926, 10019, 10037, 11910, 10001, 10032, 10056, 11150, 10039 10360 10180, 10179	Megatron MEI Meile Memorex Mermaid MGA Midland Minutz Mitsubishi Monivision Motorola MTC Mudan Multitech NAD Nanbao Nansheng	10700 10178, 10145, 10003 10185 10264, 11910, 10817 10154, 10463, 10150, 10178, 10179, 11920, 11927, 10016, 11911, 11926, 11924 10037 10150, 10030, 10178, 11907, 10019 10047, 10017, 10051, 10039, 10135, 10032 10021 10154, 10250, 10093, 10236, 10180, 11250, 10150, 10030, 10178, 10381, 10384, 10036, 10179, 10817, 11150, 10474, 10019, 10868, 100956, 11917 10843, 10700 10093, 10055 10060, 10030, 10185, 10019, 10056 10051, 10817, 10264 10180 10156, 10178, 10866 11910, 10264	Shen Ying Shencai Sheng Chia Shenyang Shogun Signature Simpson Skygiant Skyworth Sony Soundesign Sowa Spectricon Squareview SSS Starlite Studio Experie	10039, 10165, 10474, 10688, 10787, 10036, 11917 2e 11950 10092, 10003, 10474, 10179 10145, 10264 10093, 10236, 10179, 11150, 10474 10817, 10264 10019 10016 10187, 10186 10180 10748, 10264, 10037, 10817 11100, 10000, 10036, 10650, 11300, 10111, 11925, 10080, 10834, 11904 10180, 10178, 10179, 10186 10156, 10051, 10060, 10178, 10036, 10092, 10474, 11150 10003 10171 10180, 10019 10180 ience 10843	America Action American High Amoisonic Anam Anam National Asha Audiovox Beaumark Bell & Howell Blaupunkt Broksonic Calix Canon Carver CCE Changhong Citizen Colt Craig Curtis Mathes	21972 n 20278 h 200278 h 20035 20479 20162, 20037, 20240, 20278, 20226, 21037 ll 20162, 20226 20240 20037, 20278 20240 20104 20226 20184, 20121, 20209, 20002, 20348, 20295, 21479, 20479 20035, 21174, 20167 20081 20072, 20278 20048, 20081 20037, 20278, 21278 20072 20037, 20278, 21278 20072 20035, 20047, 20240, 20072, 20271 20060, 20035, 20162, 20041, 20760, 21035	MTC Multitech NAD National NEC Newave Nikko Nikon Noblex Northgate Olympus Onkyo Optimus Optonica Orion Panarex Panasonic Pansat	20240, 20000 20000, 20072 20058 20256 20035, 20037, 20048, 20104, 20067, 20041, 20038, 20040, 20008, 20370 20037 20037 20253, 20034 20240 21972 20035, 20226, 21046 20222 21062, 20162, 20037, 20048, 20104, 21048, 21262, 20593, 21162, 20058, 20432 20062 20184, 20209, 20002, 20479, 20295, 21479 21950 21062, 20035, 20162, 20077, 20226, 20616, 21162, 20225, 20367, 20227, 21035, 21262 21950	Wards White Westingh XR-1000 Yamaha Zenith ZT Group Setup Cod ABS Alienware CyberPower Gateway Hewlett Packare Howard Compu HP iBUYPOWER InterVideo Jensen JVC	20060, 20035, 20048, 20047, 20081, 20240, 20000, 20042, 20072, 20062, 20212, 20760 100use 20209, 20072, 20637 20035, 20000, 20072 20041, 20038 20039, 20033, 20000, 20209, 20034, 20479, 21479, 21139, 20637 21972 1les for Video Accessories 01272 01393
Proscan 20522 ProVision 20778 Qwestar 20651 RCA 20522, 20571, 20717, 20822, 21193, 21974, 21132, 21965, 21022, 21913 Regent 21938 Rio 20869 Rotel 20623 Rowa 20823 Saba 21977 Sampo 20752, 20698 Samsung 20490, 20573, 20820, 21932, 21075, 20899, 21979 Sansui 20695 Sanyo 20695, 20670, 21967, 20873 Sharper Image 21995, 21117 Sherwood 21043, 20770, 20633, 21077 Shinsonic 20533, 20839, 21931 Sigma Designs 20674	Voom	Firstar Fisher Fortress Fujitsu Funai Futri Futuretech Ganxin Gateway GE General Gibralter Gintai Go Video GoldStar Goodmans Grunpy Haier	10236 10154, 10159 10093 10186, 10853, 10179, 10809, 10683 10180, 10171, 10264, 11904, 10179, 10342 10145, 10817, 10264 10180 10817 11756, 11755 11447, 10047, 11454, 10051, 10451, 10180, 10030, 10178, 10092, 11147, 11919, 10055, 10027, 11917, 10135, 10282, 11347, 10021, 11907, 11922 10186 10017, 10030, 10019 11150, 10474 10886 100154, 10030, 10178, 11926, 10019, 10037, 11910, 10001, 10032, 10056, 11150, 10039 10360 10180, 10179 11034, 10768	Megatron MEI Meile Memorex MGA Midland Minutz Mitsubishi Monivision Motorola MTC Mudan Multitech NAD Nanbao	10700 10178, 10145, 10003 10185 10264, 11910, 10817 10154, 10463, 10150, 10178, 10179, 11920, 11927, 10016, 11911, 11926, 11924 10037 10150, 10030, 10178, 11907, 10019 10047, 10017, 10051, 10039, 10135, 10032 10021 10154, 10250, 10093, 10236, 10180, 11250, 10150, 10030, 10178, 10381, 10386, 10036, 10179, 10817, 11150, 10474, 10019, 10868, 10056, 11917 10843, 10700 10093, 10055 10060, 10030, 10185, 10019, 10056 10051, 10817, 10264 10180 10156, 10178, 10866 11910, 10264 10817, 10264 10817, 10264 10817, 10264 10817, 10264 10051	Shen Ying Shencai Shencai Sheng Chia Shenyang Shogun Signature Simpson Skygiant Skyworth Sony Soundesign Sowa Spectricon Squareview SSS Starlite Studio Experies Supre-Macy	10039, 10165, 10474, 10688, 10787, 10036, 11917 3e 11950 10092, 10003, 10474, 10179 10145, 10264 10093, 10236, 10179, 11150, 10474 10817, 10264 10019 10016 10187, 10186 10180 10748, 10264, 10037, 10817 11100, 10000, 10036, 10650, 11300, 10111, 11925, 10080, 10834, 11904 10180, 10178, 10178, 10186 10156, 10051, 10060, 10178, 10036, 10092, 10474, 11150 10003 10171 10180, 10019 10180 ience 10843 10046	America Action American High Amoisonic Anam Anam National Asha Audiovox Beaumark Bell & Howell Blaupunkt Broksonic Calix Canon Carver CCE Changhong Citizen Colt Craig	21972 n 20278 h 20278 h 20278 h 20035 20479 20162, 20037, 20240, 20278, 20226, 21037 nl 20162, 20226 20240 20104 20226 20184, 20121, 20209, 20002, 20348, 20295, 21479, 20479 20037 20035, 21174, 20167 20081 20072, 20278 20048, 20081 20037, 20278, 21278 20049, 20047, 20240, 20072, 20271	MTC Multitech NAD National NEC Newave Nikko Nikon Noblex Northgate Olympus Onkyo Optimus Optonica Orion Panarex Panasonic	20240, 20000 20000, 20072 20058 20226 20035, 20037, 20048, 20104, 20067, 20041, 20038, 20040, 20008, 20370 20037 20037 20253, 20034 20240 21972 20035, 20226, 21046 20222 21062, 20162, 20037, 20048, 20104, 21048, 21262, 20593, 21162, 20058, 20432 20062 20184, 20209, 20002, 20479, 20295, 21479 21950 21062, 20035, 20162, 20077, 20226, 20616, 21162, 20225, 20367, 20227, 21035, 21262 21950 20035, 20037, 20240, 20042, 20038, 21035, 20040, 20054, 21237	Wards White Westingh XR-1000 Yamaha Zenith ZT Group Setup Cod ABS Alienware CyberPower Gateway Hewlett Packard Howard Compu HP iBUYPOWER InterVideo Jensen JVC Keyspan KWorld	20060, 20035, 20048, 20047, 20081, 20240, 20000, 20042, 20072, 20062, 20212, 20760 100use 20209, 20072, 20637 20035, 20000, 20072 20041, 20038 20039, 20033, 20000, 20209, 20034, 20479, 21479, 21139, 20637 21972 Iles for Video Accessories 01272 01393 01165 01384 01403
Proscan 20522 ProVision 20778 Qwestar 20651 RCA 20522, 20571, 20717, 20822, 21193, 21974, 21132, 21965, 21022, 21913 Regent 21938 Rio 20869 Rotel 20623 Rowa 20823 Saba 21977 Sampo 20752, 20698 Samsung 20490, 20573, 20820, 21932, 21075, 20899, 21979 Sansui 20695 Sanyo 20695, 20670, 21967, 20873 Sharp 20630, 20752 Sharper Image 21995, 21117 Sherwood 21043, 20770, 20633, 21077 Shinco 20717 Shinsonic 20533, 20839, 21931 Sigma Designs 20674 Sonic Blue 20869, 21970, 21099	Voom 00869 Zenith 00856,01856 Setup Codes for TVs 888 10264 A-Mark 10003 Abex 10032 Addison 11150, 10653, 10092 Admiral 10093, 10463 Advent 10761, 10817, 10815, 11933, 10783, 10842 Adventura 10094 Aiko 10092 Aiwa 11914, 11910 Akai 10812, 10702, 10030, 10672, 11903, 10264 Alaron 10179 Albatron 10843, 10700 Ambassador 10177 America Action 10180 Ampro 10751 Anam 10250, 10180, 10003, 10700, 10161, 10628 Anam National 10250, 10161, 10055, 10650 Anhua 10051 AOC 10451, 10093, 10180, 10060, 10030, 10060, 10030, 10178,	Firstar Fisher Fortress Fujitsu Funai Furi Futuretech Ganxin Gateway GE General Gibralter Gintai Go Video GoldStar Goodmans Grunpy Haier Haiyan	10236 10154, 10159 10093 10186, 10853, 10179, 10809, 10683 10180, 10171, 10264, 11904, 10179, 10342 10145, 10817, 10264 10180 10817 11756, 11755 11447, 10047, 11454, 10051, 10451, 10180, 10030, 10178, 10092, 11147, 11919, 10055, 10027, 11917, 10135, 10282, 11347, 10021, 11907, 11922 10186 10017, 10030, 10019 11150, 10474 10886 10154, 10030, 10178, 11926, 10019, 10037, 11910, 10001, 10032, 10056, 11150, 10039 10360 10180, 10179	Megatron MEI Meile Memorex Mermaid MGA Midland Minutz Mitsubishi Monivision Motorola MTC Mudan Multiech NAD Nanbao Nansheng National	10700 10178, 10145, 10003 10185 10264, 11910, 10817 10154, 10463, 10150, 10178, 10179, 11920, 11927, 10016, 11911, 11926, 11924 10037 10150, 10030, 10178, 11907, 10019 10047, 10017, 10051, 10039, 10135, 10032 10021 10154, 10250, 10093, 10236, 10180, 11250, 10150, 10030, 10178, 10381, 10836, 10036, 10179, 10817, 11150, 10474, 10019, 10868, 10095, 11917 10843, 10700 10093, 10055 10060, 10030, 10185, 10019, 10056 10051, 10817, 10264 10180 10156, 10178, 10866 11910, 10264 10817, 10264 10051 10154, 10156, 10051, 10053, 10030, 10178, 10064, 11150, 10056, 10165, 10178, 10866, 10051	Shen Ying Shencai Sheng Chia Shenyang Shogun Signature Simpson Skygiant Skyworth Sony Soundesign Sowa Spectricon Squareview SSS Starlite Studio Experie	10039, 10165, 10474, 10688, 10787, 10036, 11917 2e 11950 10092, 10003, 10474, 10179 10145, 10264 10093, 10236, 10179, 11150, 10474 10817, 10264 10019 10016 10187, 10186 10180 10748, 10264, 10037, 10817 11100, 10000, 10036, 10650, 11300, 10111, 11925, 10080, 10834, 11904 10180, 10178, 10179, 10186 10156, 10051, 10060, 10178, 10036, 10092, 10474, 11150 10003 10171 10180, 10019 10180 ience 10843	America Action American High Amoisonic Anam Anam National Asha Audiovox Beaumark Bell & Howell Blaupunkt Broksonic Calix Canon Carver CCE Changhong Citizen Colt Craig Curtis Mathes Cybernex	21972 n 20278 h 200278 b 200479 20162, 20037, 20240, 20278, 20226, 21037 ll 20162, 20226 20240 20037, 20278 20240 20104 20226 20184, 20121, 20209, 20002, 20348, 20295, 21479, 20479 20035, 21174, 20167 20081 20072, 20278 20048, 20081 20037, 20278, 21278 20072 20037, 20278, 21278 20072 20037, 20278, 20210, 20368, 21278, 21972 20045, 20104, 20278, 20210, 20368, 21278,	MTC Multitech NAD National NEC Newave Nikko Nikon Noblex Northgate Olympus Onkyo Optimus Optonica Orion Panarex Panasonic Pansat Penney Pentax	20240, 20000 20000, 20072 20058 20256 20035, 20037, 20048, 20104, 20067, 20041, 20038, 20040, 20008, 20370 20037 20037 20253, 20034 20240 21972 20035, 20226, 21046 20222 21062, 20162, 20037, 20048, 20104, 21048, 21262, 20593, 21162, 20058, 20432 20062 20184, 20209, 20002, 20479, 20295, 21479 21950 21062, 20035, 20162, 20077, 20226, 20616, 21162, 20225, 20367, 20227, 21035, 21262 21950 20035, 20037, 20240, 20042, 20038, 21035, 200402, 20054, 21237 20042, 20054, 21237	Wards White Westingh XR-1000 Yamaha Zenith ZT Group Setup Cod ABS Alienware CyberPower Gateway Hewlett Packare Howard Compu HP iBUYPOWER InterVideo Jensen JVC Keyspan KWorld LG	20060, 20035, 20048, 20047, 20081, 20240, 20000, 20042, 200772, 20062, 20212, 20760
Proscan 20522 ProVision 20778 Qwestar 20651 RCA 20522, 20571, 20717, 20822, 21193, 21974, 21132, 21965, 21022, 21913 Regent 21938 Rio 20869 Rotel 20623 Rowa 20823 Saba 21977 Sampo 20752, 20698 Samsung 20490, 20573, 20820, 21932, 21075, 20899, 21979 Sansui 20695 Sanyo 20695, 20670, 21967, 20873 Sharp 20630, 20752 Sharper Image 21995, 21117 Sherwood 21043, 20770, 20633, 21077 Shinconic 20533, 20839, 21931 Sigma Designs 20674 Sonic Blue 20869, 21970, 21099 Sony 20533, 21533, 20864, 21033, 21904, 22020, 21903, 21981, 20772, 21934	Voom 00869 Zenith 00856, 01856 Setup Codes for TVs 888 10264 A-Mark 10003 Abex 10032 Addison 11150, 10653, 10092 Admiral 10093, 10463 Advent 10761, 10817, 10815, 11933, 10783, 10842 Adventura 10046 Aiko 10092 Aiwa 11914, 11910 Akai 10812, 10702, 10030, 10672, 11903, 10264 Alaron 10179 Albatron 10843, 10700 Ambassador 10177 America Action 10180 Ampro 10751 Anam 10250, 10180, 10003, 10700, 10161, 10628 Anam National 10250, 10180, 10005, 10650 Anhua 10051 AOC 10451, 10093, 10180, 10008, 10030, 10030, 10178, 100019, 10185, 11150, 10018, 10052, 10474, 10003, 10092, 10179	Firstar Fisher Fortress Fujitsu Funai Furi Futuretech Ganxin Gateway GE General Gibralter Gintai Go Video GoldStar Goodmans Grunpy Haier Haiyan Hallmark Hankook	10236 10154, 10159 10093 10180, 10853, 10179, 10809, 10683 10180, 10171, 10264, 11904, 10179, 10342 10145, 10817, 10264 10180 10817 11756, 11755 11447, 10047, 11454, 10051, 10451, 10180, 10030, 10178, 10092, 11147, 11919, 10055, 10027, 11917, 10135, 10282, 11347, 10021, 11907, 11922 10180 10017, 10030, 10019 11150, 10474 10886 10154, 10030, 10178, 11926, 10019, 10037, 11910, 10001, 10032, 10056, 11150, 10039 10360 10180, 10179 11034, 10768 10264, 10817 10178	Megatron MEI Meile Memorex Mermaid MGA Midland Minutz Mitsubishi Monivision Motorola MTC Mudan Multiech NAD Nanbao Nansheng National	10700 10178, 10145, 10003 10185 10264, 11910, 10817 10154, 10463, 10150, 10178, 10179, 11920, 11927, 10016, 11911, 11926, 11924 10037 10150, 10030, 10178, 11907, 10019 10047, 10017, 10051, 10039, 10135, 10032 10021 10154, 10250, 10093, 10236, 10180, 11250, 10150, 10030, 10178, 10381, 10386, 10036, 10179, 10817, 11150, 10474, 10019, 10868, 10056, 11917 10843, 10700 10093, 10055 10060, 10030, 10185, 10019, 10056 10051, 10817, 10264 10180 10156, 10178, 10866 11910, 10264 10817, 10381, 10817, 11704, 10170, 10264, 11019, 110474, 10036, 10882, 10381, 10817, 11704, 10170, 10264, 11019, 10497	Shen Ying Shencai Shencai Sheng Chia Shenyang Shogun Signature Simpson Skygiant Skyworth Sony Soundesign Sowa Spectricon Squareview SSS Starlite Studio Experie- Supre-Macy Supreme SVA	10039, 10165, 10474, 10688, 10787, 10036, 11917 3e 11950 10092, 10003, 10474, 10179 10145, 10264 10093, 10236, 10179, 11150, 10474 10817, 10264 10019 10016 10187, 10186 10180 10748, 10264, 10037, 10817 11100, 10000, 10036, 10650, 11300, 10111, 11925, 10080, 10834, 11904 10180, 10178, 10179, 10186 10156, 10051, 10060, 10178, 10036, 10092, 10474, 11150 101003 10171 10180, 10019 10180 ience 10843 10046 10000 10748, 10587, 10865, 10872, 10768, 10871, 10870	America Action American High Amoisonic Anam Anam National Asha Audiovox Beaumark Bell & Howell Blaupunkt Broksonic Calix Canon Carver CCE Changhong Citizen Colt Craig Curtis Mathes Cybernex CyberPower	21972 n 20278 h 20278 h 20278 h 20035 20479 20162, 20037, 20240, 20278, 20226, 21037 il 20162, 20226 20240 20037, 20278 20226 20184, 20121, 20209, 20002, 20348, 20295, 21479, 20479 20037 20035, 21174, 20167 20081 20072, 20278 20048, 20081 20072, 20278 20037, 20278, 21278 20037 20037, 20278, 21278 20072 20037, 20378, 20279, 20271 20060, 20035, 20162, 20041, 20760, 21035 20240 21972	MTC Multitech NAD National NEC Newave Nikko Nikko Nikon Noblex Northgate Olympus Onkyo Optimus Optonica Orion Panarex Panasonic Pansat Penney	20240, 20000 20000, 20072 20058 20226 20035, 20037, 20048, 20104, 20067, 20041, 20038, 20040, 20008, 20370 20037 20037 20253, 20034 20240 21972 20035, 20226, 21046 20222 21062, 20162, 20037, 20048, 20104, 21048, 21262, 20593, 21162, 20058, 20432 20062 20184, 20209, 20002, 20479, 20295, 21479 21950 21062, 20035, 20162, 20077, 20226, 20616, 21162, 20225, 20367, 20227, 21035, 21262 21950 20035, 20037, 20240, 20042, 20038, 21035, 20040, 20054, 21237	Wards White Westingh XR-1000 Yamaha Zenith ZT Group Setup Cod ABS Alienware CyberPower Gateway Hewlett Packard Howard Compu HP iBUYPOWER InterVideo Jensen JVC Keyspan KWorld	20060, 20035, 20048, 20047, 20081, 20240, 20000, 20042, 20072, 20062, 20212, 20760 rouse 20209, 20072, 20637 20035, 20000, 20072 20041, 20038 20039, 20033, 20000, 20209, 20034, 20479, 21479, 21139, 20637 21479, 21139, 20637 21972 des for Video Accessories 01272 01272 01272 01272 01272 01272 01272 01272 01272 01272 01272 01272 01393 01165 01384 01344 01403 01415 01415 01365
Proscan 20522 ProVision 20778 Qwestar 20651 RCA 20522, 20571, 20717, 20822, 21193, 21974, 21132, 21965, 21022, 21913 Regent 21938 Rio 20869 Rotel 20623 Rowa 20823 Sampo 20752, 20698 Samsung 20490, 20573, 20820, 21932, 21075, 20899, 21979 Sansui 20695 Sanyo 20695, 20670, 21967, 20873 Sharp 20630, 20752 Sharper Image 21995, 21117 Sherwood 21043, 20770, 20633, 21077 Shinco 20717 Shinsonic 20533, 20839, 21931 Sigma Designs 20674 Sonic Blue 20869, 21970, 21009 Sony 20533, 21981, 20772, 21934 Sungale 21074	Voom 00869 Zenith 00856, 01856 Setup Codes for TVs 888 10264 A-Mark 10003 Abex 10032 Addison 11150, 10653, 10092 Admiral 10093, 10463 Advent 10761, 10817, 10815, 11933, 10783, 10842 Adventura 10046 Aiko 10092 Aiwa 11914, 11910 Akai 10812, 10702, 10030, 10672, 11903, 10264 Alaron 10179 Albatron 10843, 10700 Ambassador 10177 America Action 10180 Ampro 10751 Anam 10250, 10180, 10003, 10700, 10161, 10628 Anam National 10250, 10180, 10003, 10700, 10161, 10628 Annam National 10251, 10018, 10055, 10650 Anhua 10051 AOC 10451, 10093, 10180, 10006, 10030, 10178, 10018, 10052, 10474, 10003, 10092, 10179 Aolinpike 10264	Firstar Fisher Fortress Fujitsu Funai Furi Futuretech Ganxin Gateway GE General Gibralter Gintai Go Video GoldStar Goodmans Grunpy Haier Haiyan Hallmark	10236 10154, 10159 10093 10180, 10853, 10179, 10809, 10683 10180, 10171, 10264, 11904, 10179, 10342 10145, 10817, 10264 10180 10817 11756, 11755 11447, 10047, 11454, 10051, 10451, 10180, 10030, 10178, 10092, 11147, 11919, 10055, 10027, 11917, 10135, 10282, 11347, 10021, 11907, 11922 10186 10017, 10030, 10019 11150, 10474 10886 10154, 10030, 10178, 11926, 10019, 10037, 11910, 10001, 10032, 10056, 11150, 10039 10360 10160, 10179 11034, 10768 10264, 10817 10178	Megatron MEI Meile Memorex Mermaid MGA Midland Minutz Mitsubishi Monivision Motorola MTC Mudan Multitech NAD Nanbao Nansheng National NEC	10700 10178, 10145, 10003 10185 10264, 11910, 10817 10154, 10463, 10150, 10178, 10179, 11920, 11927, 10016, 11911, 11926, 11924 10037 10150, 10030, 10178, 11907, 10019 10047, 10017, 10051, 10039, 10135, 10032 10021 10154, 10250, 10093, 10236, 10180, 11250, 10150, 10030, 10178, 10381, 10836, 10036, 10179, 10817, 11150, 10474, 10019, 10868, 10096, 11917 10843, 10700 10093, 10055 10060, 10030, 10185, 10019, 10056 10051, 10817, 10264 10180 10156, 10178, 10866 11910, 10264 10817, 10264 10051 10154, 10156, 10051, 10053, 10030, 10178, 10066, 1150, 10078, 10085, 10086, 110974, 10186, 10178, 10866 11910, 10264 10817, 10264 10051 10154, 10156, 10051, 10053, 10030, 10178, 10066, 11150, 100756, 10186, 10174, 10036, 10882, 10381, 10817, 11704, 10170, 10264, 10019, 10479 10093, 10178, 11150, 10092, 10161	Shen Ying Shencai Sheng Chia Sheng Chia Shenyang Shogun Signature Simpson Skygiant Skyworth Sony Soundesign Sowa Spectricon Squareview SSS Starlite Studio Experie Supre-Macy Supreme	10039, 10165, 10474, 10688, 10787, 10036, 11917 2e 11950 10092, 10003, 10474, 10179 10145, 10264 10093, 10236, 10179, 11150, 10474 10817, 10264 10019 10016 10187, 10186 10180 10748, 10264, 10037, 10817 11100, 10000, 10036, 10650, 11300, 10111, 11925, 10080, 10834, 11904 10180, 10178, 10179, 10186 10156, 10051, 10060, 10178, 10036, 10092, 10474, 11150 10003 10171 10180, 10019 10180 ience 10843 10046 10000 10748, 10587, 10865, 10872, 10768, 10871,	America Action American High Amoisonic Anam Anam National Asha Audiovox Beaumark Bell & Howell Blaupunkt Broksonic Calix Canon Carver CCE Changhong Citizen Colt Craig Curtis Mathes CyberPower Daewoo Dell Denon	21972 n 20278 h 20278 h 20035 20479 20162, 20037, 20240, 20278, 20226, 21037 nl 20162, 20226 20240 20037, 20278 20240 20104 20226 20184, 20121, 20209, 20002, 20348, 20295, 21479, 20479 20037 20035, 21174, 20167 20081 20072, 20278 20048, 20081 20072, 20278 20048, 20081 20037, 20278, 21278 20072 20037, 20278, 21278 20072 20037, 20278, 20209, 20002, 20271 20060, 20035, 20162, 20041, 20760, 21035 20240 21972 20045, 20104, 20278, 20210, 20368, 21278, 20637, 20046, 20212, 20561 21972 20042	MTC Multitech NAD National NEC Newave Nikko Nikon Noblex Northgate Olympus Onkyo Optimus Optonica Orion Panarex Panasonic Pansat Penney Pentax Philco	20240, 20000 20000, 20072 20058 20256 20035, 20037, 20048, 20104, 20067, 20041, 20038, 20040, 20008, 20370 20037 20037 20253, 20034 20240 21972 20035, 20226, 21046 20222 21662, 20162, 20037, 20048, 20104, 21048, 21262, 20593, 21162, 20058, 20432 20062 20184, 20209, 20002, 20479, 20295, 21479 21950 21062, 20035, 20162, 20077, 20226, 20616, 21162, 20225, 20367, 20227, 21035, 21262 21950 20035, 20037, 20240, 20042, 20038, 21035, 20040, 20054, 21237 20042, 20105 20035, 20000, 20226, 20479 20035, 20001, 20001, 20079, 21381, 20110, 20618, 21181, 20563, 21081, 21949,	Wards White Westingh XR-1000 Yamaha Zenith ZT Group Setup Cod ABS Alienware CyberPower Gateway Hewlett Packard Howard Compu HP iBUYPOWER InterVideo Jensen JVC Keyspan KWorld LG Linksys Macro Image Te Media Center Pe	20060, 20035, 20048, 20047, 20081, 20240, 20000, 20042, 200772, 20062, 20212, 20760
Proscan 20522 ProVision 20778 Qwestar 20651 RCA 20522, 20571, 20717, 20822, 21193, 21974, 21132, 21965, 21022, 21913 Regent 21938 Rio 20869 Rotel 20623 Rowa 20823 Saba 21977 Sampon 20752, 20698 Samsung 20490, 20573, 20820, 21932, 21075, 20899, 21979 Sansui 20695 Sanyo 20695, 20670, 21967, 20873 Sharp 20630, 20752 Sharper Image 21995, 21117 Sherwood 21043, 20770, 20633, 21077 Shinsonic 20533, 20839, 21931 Sigma Designs 20674 Sonic Blue 20869, 21970, 21099 Sony 20533, 21533, 20864, 21033, 21904, 22020, 21903, 21981, 20772, 21934	Voom 00869 Zenith 00856, 01856 Setup Codes for TVs 888 10264 A-Mark 10003 Abex 10032 Addison 11150, 10653, 10092 Admiral 10093, 10463 Advent 10761, 10817, 10815, 11933, 10783, 10842 Adventura 10046 Aiko 10092 Aiwa 11914, 11910 Akai 10812, 10702, 10030, 10672, 11903, 10264 Alaron 10179 Albatron 10843, 10700 Ambassador 10177 America Action 10180 Ampro 10751 Anam 10250, 10180, 10003, 10700, 10161, 10628 Anam National 10250, 10180, 10005, 10650 Anhua 10051 AOC 10451, 10093, 10180, 10008, 10030, 10030, 10178, 100019, 10185, 11150, 10018, 10052, 10474, 10003, 10092, 10179	Firstar Fisher Fortress Fujitsu Funai Furi Futuretech Ganxin Gateway GE General Gibralter Gibralter Giotalter Goodfatar Goodmans Gruppy Haier Haiyan Hallmark Hankook Harrhan/Kardon Harrhan/Kardon Harvard	10236 10154,10159 10093 10180,10853,10179,10809,10683 10180,10171,10264,11904,10179,10342 10145,10817,10264 10180 10817 11756,11755 11447,10047,11454,10051,10451,10180,10030,10178,10092,11147,11919,10055,10027,11917,10135,10282,11347,10021,11907,11902,11907,11902 10186 10017,10030,10019 11150,10474 10886 10154,10030,10178,11926,10019,10037,11910,10001,10032,10056,11150,10039 10360 10180,10179 11034,10768 10264,10817 10178 10180,10030,10178,11019,10056,10628 11904,10179 11080,10030,10178,10019,10056,10628 11904,10179	Megatron MEI Meile Memorex Mermaid MGA Midland Minutz Mitsubishi Monivision Motorola MTC Mudan Multitech NAD Nanbao Nansheng National NEC	10700 10178, 10145, 10003 10185 10264, 11910, 10817 10154, 10463, 10150, 10178, 10179, 11920, 11927, 10016, 11911, 11926, 11924 10037 10150, 10030, 10178, 11907, 10019 10047, 10017, 10051, 10039, 10135, 10032 10021 10154, 10250, 10093, 10236, 10180, 11250, 10150, 10030, 10178, 10381, 10386, 10036, 10179, 10817, 11150, 10474, 10019, 10868, 10056, 11917 10843, 10700 10093, 10055 10060, 10030, 10185, 10019, 10056 10051, 10817, 10264 10180 10156, 10178, 10866 11910, 10264 10817, 10381, 10817, 11704, 10170, 10264, 11019, 110474, 10036, 10882, 10381, 10817, 11704, 10170, 10264, 11019, 10497	Shen Ying Shencai Shencai Sheng Chia Shenyang Shogun Signature Simpson Skygiant Skyworth Sony Soundesign Sowa Spectricon Squareview SSS Starlite Studio Experie Supre-Macy Supreme SVA Sylvania Symphonic	10039, 10165, 10474, 10688, 10787, 10036, 11917 2e 11950 10092, 10003, 10474, 10179 10145, 10264 10093, 10236, 10179, 11150, 10474 10817, 10264 10019 10016 10187, 10186 10180 10748, 10264, 10037, 10817 11100, 10000, 10036, 10650, 11300, 10111, 11925, 10080, 10834, 11904 10180, 10178, 10179, 10186 10156, 10051, 10060, 10178, 10036, 10092, 10474, 11150 101003 10171 10180, 10019 10180 ience 10843 10046 10000 10748, 10587, 10865, 10872, 10768, 10871, 10870 1054, 10030, 10171, 11913, 11934, 10381, 11944, 10020, 10096 10180, 10171, 11913, 11934, 10381, 11944, 10020, 10096	America Action American High Amoisonic Anam Anam National Asha Audiovox Beaumark Bell & Howell Blaupunkt Broksonic Calix Canon Carver CCE Changhong Citizen Colt Craig Curtis Mathes Cybernex CyberPower Daewoo Dell Denon DirecTV	21972 n 20278 h 200278 h 20035 20479 20162, 20037, 20240, 20278, 20226, 21037 ll 20162, 20226 20240 20037, 20278 20240 20104 20226 20184, 20121, 20209, 20002, 20348, 20295, 21479, 20479 20035, 21174, 20167 20081 20072, 20278 20048, 20081 20072, 20278, 21278 20072 20035, 21474, 20167, 2026, 20271 20060, 20035, 20162, 20041, 20760, 21035 20240 21972 20045, 20104, 20278, 20210, 20368, 21278, 20637, 20046, 20212, 20561 21972 20042 20739, 21989, 21954, 21949	MTC Multitech NAD National NEC Newave Nikko Nikon Noblex Northgate Olympus Onkyo Optimus Optonica Orion Panarex Panasonic Pansat Penney Pentax Philco	20240, 20000 20000, 20072 20058 20226 20035, 20037, 20048, 20104, 20067, 20041, 20038, 20040, 20008, 20370 20037 20037 20037 20253, 20034 20240 21972 20035, 20226, 21046 20222 21062, 20162, 20037, 20048, 20104, 21048, 21262, 20593, 21162, 20058, 20432 20062 20184, 20209, 20002, 20479, 20295, 21479 21950 21062, 20035, 20162, 20077, 20226, 20616, 21162, 20225, 2035, 2035, 2035, 2035, 20042, 20195 20035, 20037, 20240, 20042, 20038, 21035, 20040, 20054, 21237 20042, 20105 2035, 20000, 20226, 20479 20035, 20081, 20000, 20226, 20479 20035, 20081, 20000, 20226, 20479 20035, 20081, 20000, 20226, 20739, 21381,	Wards White Westingh XR-1000 Yamaha Zenith ZT Group Setup Cod ABS Alienware CyberPower Gateway Hewlett Packare Howard Compu HP IBUYPOWER InterVideo Jensen JVC Keyspan KWorld LG Linksys Macro Image Te	20060, 20035, 20048, 20047, 20081, 20240, 20000, 20042, 20072, 20062, 20212, 20760 100use 20209, 20072, 20637 20035, 20000, 20072 20041, 20038 20039, 20033, 20000, 20209, 20034, 20479, 21479, 21139, 20637 21972 1les for Video Accessories 01272 01272 01272 01272 01272 01272 01272 01272 01272 01272 01272 01272 01272 01393 01165 01384 01344 01403 01415 01365 6chnology 01383
Proscan 20522 ProVision 20778 Qwestar 20651 RCA 20522, 20571, 20717, 20822, 21193, 21974, 21132, 21965, 21022, 21913 Regent 21338 Rio 20869 Rotel 20623 Rowa 20823 Sampo 20752, 20698 Samsung 20490, 20573, 20820, 21932, 21075, 20899, 21979 Sansui 20695 Sanyo 20695, 20670, 21967, 20873 Sharp 20630, 20752 Sharper Image 21995, 21117 Sherwood 21043, 20770, 20633, 21077 Shinco 20717 Shinsonic 20533, 20839, 21931 Sigma Designs 20674 Sonic Blue 20869, 21970, 21099 Sony 20533, 21533, 20864, 21033, 21904, 22020, 21903, 21981, 20772, 21934 Sungale 21074 Superscan 20821 SVA 20717, 20860, 21105 Sylvania 20821, 20675	Voom	Firstar Fisher Fortress Fujitsu Funai Furi Furi Ganxin Gateway GE General Gibralter Gintai Go Video GoldStar Goodmans Grunpy Haier Haiyan Hallmark Hankook Harley Davidson Harman/Kardon Harward Havermy	10236 10154, 10159 10093 10180, 10853, 10179, 10809, 10683 10180, 10171, 10264, 11904, 10179, 10342 10145, 10817, 10264 10180 10817 11756, 11755 11447, 10047, 11454, 10051, 10451, 10180, 10030, 10178, 10092, 11147, 11919, 10055, 10027, 11917, 10135, 10282, 11347, 10021, 11907, 11922 10186 10017, 10030, 10019 11150, 10474 10886 10154, 10030, 10178, 11926, 10019, 10037, 11910, 10001, 10032, 10056, 11150, 10039 10360 10179 11034, 10768 10264, 10817 10178 10180, 10030, 10178, 10019, 10056, 10628 11904, 10179 11034, 10768 10264, 10817 10180, 10030, 10178, 10019, 10056, 10628 11904, 10179 11036	Megatron MEI Meile Memorex Mermaid MGA Midland Minutz Mitsubishi Monivision Motorola MTC Mudan Multitech NAD Nanbao Nansheng National NEC Newave Nikko Nikoo Norcent	10700 10178, 10145, 10003 10185 10264, 11910, 10817 10154, 10463, 10150, 10178, 10179, 11920, 11927, 10016, 11911, 11926, 11924 10037 10150, 10030, 10178, 11907, 10019 10047, 10017, 10051, 10039, 10135, 10032 10021 10154, 10250, 10093, 10236, 10180, 11250, 10150, 10030, 10178, 10381, 10836, 10036, 10179, 10817, 11150, 10474, 10019, 10868, 10056, 11917 10843, 10700 10093, 10055 10060, 10030, 10185, 10019, 10056 10051, 10817, 10264 10180 10156, 10178, 10866 11910, 10264 10817, 10264 100151 10154, 10156, 10051, 10053, 10030, 10178, 10046, 11150, 10056, 10165, 10188, 10046, 11190, 10264 10051 10154, 10156, 10051, 10053, 10030, 10178, 10046, 11150, 10056, 10165, 10186, 10474, 10036, 10882, 10381, 10817, 11704, 10170, 10264, 10019, 10497 10093, 10178, 11150, 10092, 10161 10030, 10178, 10092	Shen Ying Shencai Sheng Chia Shenyang Shogun Signature Simpson Skygiant Skyworth Sony Soundesign Sowa Spectricon Squareview SSS Starlite Studio Experie Supre-Macy Supreme SVA Sylvania	10039, 10165, 10474, 10688, 10787, 10036, 11917 3e 11950 10092, 10003, 10474, 10179 10145, 10264 10093, 10236, 10179, 11150, 10474 10019 10016 10187, 10186 10180 10748, 10264, 10037, 10817 11100, 10000, 10036, 10650, 11300, 10111, 11925, 10080, 10834, 11904 10180, 10178, 10179, 10186 10156, 10051, 10060, 10178, 10036, 10092, 10474, 11150 10003 10171 10180, 10019 10180 ience 10843 10046 10000 10748, 10587, 10865, 10872, 10768, 10871, 10870 10054, 10030, 10171, 11931, 10381, 11944, 10020, 10096	America Action American High Amoisonic Anam Anam National Asha Audiovox Beaumark Bell & Howell Blaupunkt Broksonic Calix Canon Carver CCE Changhong Citizen Colt Craig Curtis Mathes Cybernex CyberPower Daewoo Dell Denon DirecTV	21972 n 20278 h 20278 h 20035 20479 20162, 20037, 20240, 20278, 20226, 21037 nl 20162, 20226 20240 20037, 20278 20240 20104 20226 20184, 20121, 20209, 20002, 20348, 20295, 21479, 20479 20037 20035, 21174, 20167 20081 20072, 20278 20048, 20081 20072, 20278 20048, 20081 20037, 20278, 21278 20072 20037, 20278, 21278 20072 20037, 20278, 20209, 20002, 20271 20060, 20035, 20162, 20041, 20760, 21035 20240 21972 20045, 20104, 20278, 20210, 20368, 21278, 20637, 20046, 20212, 20561 21972 20042	MTC Multitech NAD National NEC Newave Nikko Nikko Nikon Noblex Northgate Olympus Onkyo Optimus Optonica Orion Panarex Panasanic Pansat Penney Pentax Philco Philips	20240, 20000 20000, 20072 20058 20226 20035, 20037, 20048, 20104, 20067, 20041, 20038, 20040, 20008, 20370 20037 20037 20253, 20034 20240 21972 20035, 20226, 21046 20222 21062, 20162, 20037, 20048, 20104, 21048, 21262, 20593, 21162, 20058, 20432 20062 20184, 20209, 20002, 20479, 20295, 21479 21950 21062, 20035, 20162, 20077, 20226, 20616, 21162, 20025, 2035,	Wards White Westingh XR-1000 Yamaha Zenith ZT Group Setup Cod ABS Alienware CyberPower Gateway Hewlett Packare Howard Compu HP IBUYPOWER InterVideo Jensen JVC Keyspan KWorld LG Linksys Macro Image Te Media Center Po Microsoft Mind Motorola	20060, 20035, 20048, 20047, 20081, 20240, 20000, 20042, 20072, 20062, 20212, 20760 100use 20209, 20072, 20637 20035, 20000, 20072 20041, 20038 20039, 20033, 20000, 20209, 20034, 20479, 21479, 21139, 20637 21972 1les for Video Accessories 01272 01272 01272 01272 01272 01272 01272 01272 01272 01393 01165 01384 01384 01403 01415 01365 10365 10365 10360 10372 10272 10272 10272 10272 10272 10272 10272 10272 10272 10272 10393 10465 10584 10585 10586 10686 10797 10
Proscan 20522 ProVision 20778 Qwestar 20651 RCA 20522, 20571, 20717, 20822, 21193, 21974, 21132, 21965, 21022, 21913 Regent 21938 Rio 20869 Rotel 20623 Rowa 20823 Saba 21977 Sampo 20752, 20698 Samsung 20490, 20573, 20820, 21932, 21075, 20899, 21979 Sansui 20695 Sanyo 20695, 20670, 21967, 20873 Sharp 20630, 20752 Sharper Image 21995, 21117 Sherwood 21043, 20770, 20633, 21077 Shinsonic 20533, 20839, 21931 Sigma Designs 20674 Sonic Blue 20869, 21970, 21099 Sony 20533, 21533, 20864, 21033, 21904, 22020, 21903, 21981, 20772, 21934 Sungale 21074 SVA 20717, 20860, 21105	Voom	Firstar Fisher Fortress Fujitsu Funai Furi Futuretech Ganxin Gateway GE General Gibralter Gintai Go Video GoldStar Goodmans Grunpy Haier Haiyan Hallmark Hankook Harley Davidson Harvard Havermy Hello Kitty	10236 10154,10159 10093 10180,10853,10179,10809,10683 10180,10171,10264,11904,10179,10342 10145,10817,10264 10180 10817 11756,11755 11447,10047,11454,10051,10451,10180,10030,10178,10092,11147,11919,10055,10027,11917,10135,10282,11347,10021,11907,11902,11907,11902 10186 10017,10030,10019 11150,10474 10886 10154,10030,10178,11926,10019,10037,11910,10001,10032,10056,11150,10039 10360 10180,10179 11034,10768 10264,10817 10178 10180,10030,10178,11019,10056,10628 11904,10179 11080,10030,10178,10019,10056,10628 11904,10179	Megatron MEI Meile Memorex Mermaid MGA Midland Minutz Mitsubishi Monivision Motorola MTC Mudan Multiech NAD Nanbao Nansheng National NEC	10700 10178, 10145, 10003 10185 10264, 11910, 10817 10154, 10463, 10150, 10178, 10179, 11920, 11927, 10016, 11911, 11926, 11924 10037 10150, 10030, 10178, 11907, 10019 10047, 10017, 10051, 10039, 10135, 10032 10021 10154, 10250, 10093, 10236, 10180, 11250, 10150, 10030, 10178, 10381, 10836, 10036, 10179, 10817, 11150, 10474, 10019, 10868, 10056, 11917 10843, 10700 10093, 10055 10060, 10030, 10185, 10019, 10056 10051, 10817, 10264 10180 10156, 10178, 10866 11910, 10264 10817, 10882, 10381, 10817, 11704, 10170, 10264, 10019, 10497 10093, 10178, 11150, 10092, 10161 10030, 10178, 110902	Shen Ying Shencai Shencai Sheng Chia Shenyang Shogun Signature Simpson Skygiant Skyworth Sony Soundesign Sowa Spectricon Squareview SSS Starlite Studio Experie Supre-Macy Supreme SVA Sylvania Symphonic Synco Tacico	10039, 10165, 10474, 10688, 10787, 10036, 11917 3e 11950 10092, 10003, 10474, 10179 10145, 10264 10093, 10236, 10179, 11150, 10474 100817, 10264 10019 10016 10187, 10186 10180 10748, 10264, 10037, 10817 11100, 10000, 10036, 10650, 11300, 10111, 11925, 10080, 10834, 11904 10180, 10178, 10179, 10186 10156, 10051, 10060, 10178, 10036, 10092, 10474, 11150 10003 10171 10180, 10019 10180 ience 10843 10046 10000 10748, 10587, 10865, 10872, 10768, 10871, 10870 10748, 10587, 10865, 10872, 10768, 10871, 10870 10754, 10030, 10171, 11931, 10381, 11944, 10020, 10096 10180, 10171, 11913, 11904 10000, 10451, 10093, 10060, 10178, 10092, 1036, 10474 10178, 10179, 11150, 10092, 10474	America Action American High Amoisonic Anam Anam National Asha Audiovox Beaumark Bell & Howell Blaupunkt Broksonic Calix Canon Carver CCE Changhong Citizen Colt Craig Curtis Mathes CyberPower Daewoo Dell Denon DirecTV Dish Network St Dishpro Durabrand	21972 n 20278 h 200278 h 20035 20479 20162, 20037, 20240, 20278, 20226, 21037 ll 20162, 20226 20240 20037, 20278 20240 20104 20226 20184, 20121, 20209, 20002, 20348, 20295, 21479, 20479 20035, 21174, 20167 20081 20072, 20278 20048, 20081 20037, 20278, 21278 20072 20037, 20278, 21278 20072 20037, 20278, 21278 20072 20037, 20278, 21278 20072 20037, 2047, 20240, 20072, 20271 20060, 20035, 20162, 20041, 20760, 21035 20240 21972 20045, 20104, 20278, 20210, 20368, 21278, 20637, 20046, 20212, 20561 21972 20042 20739, 21989, 21954, 21949 System 21943, 21946, 21945, 21944 21944, 21943 20039, 20038	MTC Multitech NAD National NEC Newave Nikko Nikon Noblex Northgate Olympus Onkyo Optimus Optonica Orion Panarex Panasonic Pansat Penney Pentax Philco Philips Pilot Pioneer Polk Audio	20240, 20000 20000, 20072 20058 20026 20035, 20037, 20048, 20104, 20067, 20041, 20038, 20040, 20008, 20370 20037 20037 20253, 20034 20240 21972 20035, 20226, 21046 20222 21062, 20162, 20037, 20048, 20104, 21048, 21262, 20593, 21162, 20058, 20432 20062 20184, 20209, 20002, 20479, 20295, 21479 21950 21062, 20035, 20162, 20077, 20226, 20616, 21162, 20225, 20367, 20227, 21035, 21262 21950 2035, 20037, 20240, 20042, 20038, 21035, 20042, 20105 20035, 20037, 20240, 20042, 20038, 21035, 20042, 20105 20355, 20000, 20226, 20479 20355, 20081, 20000, 20226, 20739, 21381, 20110, 20618, 21181, 20563, 21081, 21949, 20062 20037	Wards White Westingh XR-1000 Yamaha Zenith ZT Group Setup Cod ABS Alienware CyberPower Gateway Hewlett Packard Howard Compu HP iBUYPOWER InterVideo Jensen JVC Keyspan KWorld LG Linksys Macro Image Te Media Center Po Microsoft Mind Motorola MyHD	20060, 20035, 20048, 20047, 20081, 20240, 20000, 20042, 200772, 20062, 20212, 20760 rouse 20209, 20072, 20637 20035, 20000, 20072 20041, 20038 20039, 20033, 20000, 20209, 20034, 20479, 21479, 21139, 20637 21972 les for Video Accessories 01272 01272 01272 01272 01272 01272 01272 01272 01272 01272 01393 01165 01384 01403 01415 01365 echnology 01383 C 01272 01272 01272 01272 01272 01272 01272 01393 01165 01384 01403 01415 01365 echnology 01383 C 01272 01272 01272 01272 01272 01272 01272 01272 01272 01272 01272 01273 01274 01275 01275 01276 01277 01277 01277 01277 01277 01277 01277 01277 01277 01363 01383
Proscan 20522 ProVision 20778 Qwestar 20651 RCA 20522, 20571, 20717, 20822, 21193, 21974, 21132, 21965, 21022, 21913 Regent 21938 Rio 20869 Rotel 20623 Rowa 20823 Saba 21977 Sampo 20752, 20698 Samsung 20490, 20573, 20820, 21932, 21075, 20899, 21979 21979 20695 Sanyo 20695, 20670, 21967, 20873 Sharp 20630, 20752 Sharper Image 21995, 21117 Sherwood 21043, 20770, 20633, 21077 Shinsonic 20533, 20839, 21931 Sigma Designs 20674 Sonic Blue 20869, 21970, 21099 Sony 20533, 21533, 20864, 21033, 21904, 22020, 21903, 21981, 20772, 21934 Sungale 21074 Superscan 20821 SVA 20717, 20860, 21105 Symphonic 20675 Symphonic 20675 Steac 21984, 20809 Technics<	Voom	Firstar Fisher Fortress Fujitsu Funai Furi Furi Futuretech Ganxin Gateway GE General Gibralter Gintai Go Video GoldStar Goodmans Grunpy Haier Haiyan Hallmark Hankook Harley Davidson Harrand/Kardon Harvard Havermy Hello Kitty Himitsu Hisense	10236 10154,10159 10093 10180,10853,10179,10809,10683 10180,10171,10264,11904,10179,10342 10145,10817,10264 10180 10817 11756,11755 11447,10047,11454,10051,10451,10180,10030,10178,10092,11147,11919,10055,10027,11917,10135,10282,11347,10021,11907,11922 10186 10017,10030,10019 11150,10474 10886 10154,10030,10178,11926,10019,10037,11910,10001,10032,10056,11150,10039 10360 10180,10179 11034,10768 10264,10817 10178 10180,10030,10178,11019,10056,10628 11904,10179 10054 10180,10030,10178,10019,10056,10628 11904,10179 10054 10180,10030,10178,10019,10056,10628 11909,10179 10054 10180,10030,10178,10019,10056,10628 11909,10179	Megatron MEI Meile Memorex Memorex Mermaid MGA Midland Minutz Mitsubishi Monivision Motorola MTC Mudan Multitech NAD Nanbao Nansheng National NEC	10700 10178, 10145, 10003 10185 10264, 11910, 10817 10154, 10463, 10150, 10178, 10179, 11920, 11927, 10016, 11911, 11926, 11924 10037 10150, 10030, 10178, 11907, 10019 10047, 10017, 10051, 10039, 10135, 10032 10021 10154, 10250, 10093, 10236, 10180, 11250, 10150, 10030, 10178, 10381, 10386, 10036, 10179, 10817, 11150, 10474, 10019, 10868, 10056, 11917 10843, 10700 10093, 10055 10060, 10030, 10185, 10019, 10056 10051, 10817, 10264 10180 10156, 10178, 10866 11910, 10264 10817, 10156, 10051, 10053, 10030, 10178, 10046, 11150, 10056, 10165, 10186, 10474, 10036, 10882, 10381, 10817, 11704, 10170, 10264, 10019, 10497 10093, 10178, 11150, 10092, 10161 10030, 10178, 10092 10280	Shen Ying Shencai Shencai Sheng Chia Shenyang Shogun Signature Simpson Skygiant Skyworth Sony Soundesign Sowa Spectricon Squareview SSS Starlite Studio Experie Supre-Macy Supre-Macy Supreme SVA Sylvania Symphonic Synco	10039, 10165, 10474, 10688, 10787, 10036, 11917 3e 11950 10092, 10003, 10474, 10179 10145, 10264 10093, 10236, 10179, 11150, 10474 10817, 10264 10019 10016 10187, 10186 10180 10748, 10264, 10037, 10817 11100, 10000, 1036, 10650, 11300, 10111, 11925, 10080, 10834, 11904 10180, 10178, 10179, 10186 10156, 10051, 10060, 10178, 10036, 10092, 10474, 11150 10003 10171 10180, 10019 10180 10748, 10587, 10865, 10872, 10768, 10871, 10870 10748, 10380, 10171, 11931, 10381, 11944, 10020, 10096 10180, 10171, 11931, 11904 10000, 10074, 10151, 10093, 10060, 10178, 10092, 10006, 10171, 11931, 11904	America Action American High Amoisonic Anam Anam National Asha Audiovox Beaumark Bell & Howell Blaupunkt Broksonic Calix Canon Carver CCE Changhong Citizen Colt Craig Curris Mathes Cybernex CyberPower Daewoo Dell Denon DirecTV Dish Network S Dishpro	21972 n 20278 h 20278 h 20278 h 20035 20479 20162, 20037, 20240, 20278, 20226, 21037 il 20162, 20226 20240 20037, 20278 20240 20104 20226 20184, 20121, 20209, 20002, 20348, 20295, 21479, 20479 20037 20035, 21174, 20167 20081 20072, 20278 20048, 20081 20072, 20278 20049, 20079, 20079, 20079, 20071 20037, 20079, 21278 20072 20037, 20078, 21278 20072 20037, 20047, 20240, 20072, 20271 20060, 20035, 20162, 20041, 20760, 21035 20240 21972 20045, 20104, 20278, 20210, 20368, 21278, 20637, 20046, 20212, 20561 21972 20042 20739, 21989, 21954, 21949 System 21943, 21946, 21945, 21944 21944, 21943, 21946, 21945, 21944	MTC Multitech NAD National NEC Newave Nikko Nikko Nikon Noblex Northgate Olympus Onkyo Optimus Optonica Orion Panarex Panasonic Pansat Penney Pentax Philco Philips Pilot Pioneer Polk Audio Profitronic Proscan	20240, 20000 20000, 20072 20058 20226 20035, 20037, 20048, 20104, 20067, 20041, 20038, 20040, 20008, 20370 20037 20037 20253, 20034 20240 21972 20035, 20226, 21046 20222 21062, 20162, 20037, 20048, 20104, 21048, 21262, 20593, 21162, 20058, 20432 20062 20184, 20209, 20002, 20479, 20295, 21479 21950 21062, 20035, 20162, 20037, 20048, 20104, 21048, 21162, 20258, 20432 20062 20184, 20209, 20002, 20479, 20226, 20616, 21162, 20035, 20037, 20240, 20042, 20038, 21035, 20040, 20054, 21237 20042, 20105 20035, 20037, 20240, 20042, 20038, 21035, 20042, 20105 20035, 20081, 20000, 20226, 20479 20037 20042, 20067, 20058 20081 20040 20060, 20760, 21954, 20202, 21060, 20761	Wards White Westingh XR-1000 Yamaha Zenith ZT Group Setup Cod ABS Alienware CyberPower Gateway Hewlett Packare Howard Compu HP IBUYPOWER InterVideo Jensen JVC Keyspan KWorld LG Linksys Macro Image Te Media Center Po Microsoft Mind Motorola	20060, 20035, 20048, 20047, 20081, 20240, 20000, 20042, 20072, 20062, 20212, 20760 100use 20209, 20072, 20637 20035, 20000, 20072 20041, 20038 20039, 20033, 20000, 20209, 20034, 20479, 21479, 21139, 20637 21972 101272 01272 01272 01272 01272 01272 01272 01272 01272 01393 01165 01384 011344 01403 01415 01365 10365 10365 10360 10372 10272 10272 10272 10272 10272 10272 10272 10272 10272 10272 10272 10272 10272 10272 10393 10465 10584 10585 10586 10686 10797
Proscan 20522 ProVision 20778 Qwestar 20651 RCA 20522, 20571, 20717, 20822, 21193, 21974, 21132, 21965, 21022, 21913 Regent 21938 Rio 20869 Rotel 20623 Rowa 20823 Sampo 20752, 20698 Samsung 20490, 20573, 20820, 21932, 21075, 20899, 21979 Sansui 20695 Sanyo 20695, 20670, 21967, 20873 Sharp 20630, 20752 Sharper Image 21995, 21117 Sherwood 21043, 20770, 20633, 21077 Shinco 20717 Shinco 20717 Shinsonic 2053, 20839, 21931 Sigma Designs 20674 Sonic Blue 20869, 21970, 21099 Sony 20533, 21833, 20864, 21033, 21904, 22020, 21932, 21934 Sungale 21074 Superscan 2081 SVA 20717, 20860, 21105 Sylvania 20821, 20675 Symphonic 20675 Teac	Voom 00869 Zenith 00856, 01856 Setup Codes for TVs 888 10264 A-Mark 10003 Abex 10032 Addison 11150, 10653, 10092 Admiral 10093, 10463 Advent 10046 Aiko 10092 Aiwa 11914, 11910 Akai 10812, 10702, 10030, 10672, 11903, 10264 Allaron 10179 Albatron 10843, 10700 Ambassador 10177 America Action 10180 Ampro 10751 Anam 10250, 10180, 10003, 10700, 10161, 10628 Anam National 10250, 10161, 10055, 10650 Anhua 10051 AOC 10451, 10093, 10180, 10006, 10030, 10178, 10018, 10052, 10474, 10003, 10092, 10179 Aolinpike 10264 Apex Digital 10748, 10765, 10767, 11943, 10879 Archer 10003 Audiovox 10451, 10180, 10875, 11952, 10802, 11951, 10092, 10623, 11937, 10003 Baile 10264	Firstar Fisher Fortress Fujitsu Funai Furi Furi Futuretech Ganxin Gateway GE General Gibralter Gibralter Gintai Go Video GoldStar Goodmans Gruppy Haier Haiyan Hallmark Hankook Harley Davidson Harman/Kardon Harvard Havermy Hello Kitty Himitsu Hisense Hitachi	10236 10154,10159 10093 10180,10853,10179,10809,10683 10180,10171,10264,11904,10179,10342 10145,10817,10264 10180 10817 11756,11755 11447,10047,11454,10051,10451,10180,10030,10178,10092,11147,11919,10055,10027,11917,10135,10282,11347,10021,11907,11912,10135,10282,11347,10021,11907,11902,11917,10030,10019 11150,10474 10886 10154,10030,10178,11926,10019,10037,11910,10001,10032,10056,11150,10039 10360 10180,10179 11034,10768 101264,10817 10178 10180,10030,10178,11019,10056,10628 11904,10179 11034,10768 10054 10180 10093 10451 10180,10030,10178,10019,10056,10628 11904,10179 10180 10093	Megatron MEI Meile Memorex Mermaid MGA Midland Minutz Mitsubishi Monivision Motorola MTC Mudan Multitech NAD Nanbao Nansheng National NEC Newave Nikko Nikon Norcent Noshi NTC Onking Onwa	10700 10178, 10145, 10003 10185 10264, 11910, 10817 10154, 10463, 10150, 10178, 10179, 11920, 11927, 10016, 11911, 11926, 11924 10037 10150, 10030, 10178, 11907, 10019 10047, 10017, 10051, 10039, 10135, 10032 10021 10154, 10250, 10093, 10236, 10180, 11250, 10150, 10030, 10178, 10381, 10836, 10036, 10179, 10817, 11150, 10474, 10019, 10868, 10056, 11917 10843, 10700 10093, 10055 10060, 10030, 10185, 10019, 10056 10051, 10817, 10264 10180 10156, 10178, 10866 11910, 10264 10817, 10264 10817, 10264 10051 10154, 10156, 10051, 10053, 10030, 10178, 10046, 11150, 10056, 10165, 10186, 10474, 10036, 10882, 10381, 10817, 11704, 10170, 10264, 10019, 10079 10093, 10178, 11150, 10092, 10161 10030, 10178, 101909 11910 10748, 10824 10018 10092 10280 10180	Shen Ying Shencai Shencai Sheng Chia Shenyang Shogun Signature Simpson Skygiant Skyworth Sony Soundesign Sowa Spectricon Squareview SSS Starlite Studio Experie Supre-Macy Supreme SVA Sylvania Symphonic Synco Tacico Tai Yi Taishan Tandy	10039, 10165, 10474, 10688, 10787, 10036, 11917 3e 11950 10092, 10003, 10474, 10179 10145, 10264 10093, 10236, 10179, 11150, 10474 10817, 10264 10019 10016 10187, 10186 10180 10748, 10264, 10037, 10817 11100, 10000, 10036, 10650, 11300, 10111, 11925, 10080, 10834, 11904 10180, 10178, 10179, 10186 10156, 10051, 10060, 10178, 10036, 10092, 10474, 11150 10003 10171 10180, 10019 10180 ience 10843 10046 10000 10748, 10587, 10865, 10872, 10768, 10871, 10870 10054, 10030, 10171, 11931, 10381, 11944, 10020, 10096 10180, 10171, 11913, 11904 10000, 10451, 10093, 10060, 10178, 10092, 1036, 10474 10178, 10179, 11150, 10092, 10474 11150 10081, 10199 10180 10181, 10199, 11150, 10092, 10474 10178, 10179, 11150, 10092, 10474 10178, 10179, 11150, 10092, 10474 10181, 10391	America Action American High Amoisonic Anam Anam National Asha Audiovox Beaumark Bell & Howell Blaupunkt Broksonic Calix Canon Carver CCE Changhong Citizen Colt Craig Curtis Mathes Cybernex CyberPower Daewoo Dell Denon DirecTV Dish Network Sy Dishpro Durabrand Dynatech Echostar Electrohome	21972 n 20278 h 200278 h 20035 20479 20162, 20037, 20240, 20278, 20226, 21037 il 20162, 20226 20240 20037, 20278 20240 20104 20126 20184, 20121, 20209, 20002, 20348, 20295, 21479, 20479 20037 20035, 21174, 20167 20081 20072, 20278 20048, 20081 20072, 20278 20048, 20081 20037, 20078, 21278 20072 20037, 20078, 21278 20072 20037, 20047, 20240, 20072, 20271 20060, 20035, 20162, 20041, 20760, 21035 20240 21972 20045, 20104, 20278, 20210, 20368, 21278, 20637, 20046, 20212, 20561 21972 20042 20739, 21989, 21954, 21949 System 21943, 21946, 21945, 21944 21944, 21943, 21946, 21945, 21944 20037	MTC Multitech NAD National NEC Newave Nikko Nikon Noblex Northgate Olympus Onkyo Optimus Optonica Orion Panarex Panasonic Pansat Penney Pentax Philco Philips Pilot Pioneer Polk Audio Profitronic Proscan Protec	20240, 20000 20000, 20072 20058 20256 20035, 20037, 20048, 20104, 20067, 20041, 20038, 20040, 20008, 20370 20037 20037 20253, 20034 20240 21972 20035, 20226, 21046 20222 21062, 20162, 20037, 20048, 20104, 21048, 21262, 20593, 21162, 20058, 20432 20062 20184, 20209, 20002, 20479, 20295, 21479 21950 21062, 20035, 20162, 20077, 20226, 20616, 21162, 20252, 20367, 20227, 21035, 21262 21950 20035, 20037, 20240, 20042, 20038, 21035, 20040, 20054, 21237 20042, 20105 20035, 20081, 20000, 20226, 20739, 21381, 20110, 20618, 21181, 20563, 21081, 21949, 20062 20037 20042, 20067, 20058 20081 20040 20060, 20760, 21954, 20202, 21060, 20761 20072	Wards White Westingh XR-1000 Yamaha Zenith ZT Group Setup Cod ABS Alienware CyberPower Gateway Hewlett Packare Howard Compu HP iBUYPOWER InterVideo Jensen JVC Keyspan KWorld LG Linksys Macro Image Te Media Center Po Microsoft Mind Motorola MyHD Northgate Panasonic Pinnacle System	20060, 20035, 20048, 20047, 20081, 20240, 20000, 20042, 200772, 20062, 20212, 20760 100use 20209, 20072, 20637 20035, 20000, 20072 20041, 20038 20039, 20033, 20000, 20209, 20034, 20479, 21479, 21139, 20637 21972 101272 101272 101272 101272 101272 101272 101272 101272 101272 101272 101272 101393 10165 10384 101344 101403 101415 101365 101272 10170 10170
Proscan 20522 Provision 20778 Qwestar 20651 RCA 20522, 20571, 20717, 20822, 21193, 21974, 21132, 21965, 21022, 21913 Regent 21938 Rio 20869 Rotel 20623 Rowa 20823 Saba 21977 Sampo 20752, 20698 Samsung 20490, 20573, 20820, 21932, 21075, 20899, 21979 Sansu 20695 Sanyo 20695, 20670, 21967, 20873 Sharp 20630, 20752 Sharper Image 21995, 21117 Sherwood 21043, 20770, 20633, 21077 Shinco 20717 Shinco<	Voom 00869 Zenith 00856, 01856 Setup Codes for TVs 888 10264 A-Mark 10003 Addison 11150, 10653, 10092 Admiral 10093, 10463 Advent 10761, 10817, 10815, 11933, 10783, 10842 Adventura 10046 Aiko 10092 Aiwa 11914, 11910 Akai 10812, 10702, 10030, 10672, 11903, 10264 Alaron 10179 Albatron 10843, 10700 Ampro 10751 Anam 10250, 10180, 10003, 10700, 10161, 10628 Anam National 10250, 10161, 10055, 10650 Anhua 10051 AOC 10451, 10093, 10180, 10008, 10030, 10178, 10018, 10052, 10474, 10009, 10185, 11150, 10018, 10052, 10474, 10009, 10185, 11150, 10018, 10052, 10474, 10009, 1064 Apex Digital 10748, 10765, 10767, 11943, 10879 Archer 10003 Audiovox 10451, 10180, 10875, 11952, 10802, 11951, 10092, 10623, 11937, 10003 Axion 11937 Baihe 100001, 10391 Baosheng	Firstar Fisher Fortress Fujitsu Funai Furi Furi Furi Ganxin Gateway GE General Gibralter Gintai Go Video GoldStar Goodmans Grunpy Haier Haiyan Hallmark Hankook Harley Davidson Harrand/Kardon Harrvard Havermy Hello Kitty Himitsu Hisense Hitachi	10236 10154, 10159 10093 10186, 10853, 10179, 10809, 10683 10180, 10171, 10264, 11904, 10179, 10342 10145, 10817, 10264 10180 10817 11756, 11755 11447, 10047, 11454, 10051, 10451, 10180, 10030, 10178, 10092, 11147, 11919, 10055, 10027, 11917, 10135, 10282, 11347, 10021, 11907, 11922 10186 10017, 10030, 10019 11150, 10474 10886 10154, 10030, 10178, 11926, 10019, 10037, 11910, 10001, 10032, 10056, 11150, 10039 10360 10180, 10179 11034, 10768 10264, 10817 10178 10180, 10030, 10178, 11092, 10056, 10628 11904, 10179 10054 10180, 10030, 10178, 10019, 10056, 10628 11904, 10179 10054 10180, 10030, 10178, 11019, 10056, 10628 11904, 10179 10054 10180, 10030, 10178, 10019, 10056, 10628 11904, 10179 10054 10180, 10030, 10178, 10019, 10056, 10628 11904, 10179 10054 10180, 10628 10156, 10748, 10145 11256, 10156, 10030, 10178, 11145, 10145, 10038, 11245, 10092, 10027, 10381, 10036, 11150, 10056, 110019, 100151, 10165, 10019,	Megatron MEI Meile Memorex Mermaid MGA Midland Minutz Mitsubishi Monivision Motorola MTC Mudan Multitech NAD Nanbao Nansheng National NEC Newave Nikko Nikon Norcent Norcent North Onking Onwa Optimus	10700 10178, 10145, 10003 10185 10264, 11910, 10817 10154, 10463, 10150, 10178, 10179, 11920, 11927, 10016, 11911, 11926, 11924 10037 10150, 10030, 10178, 11907, 10019 10047, 10017, 10051, 10039, 10135, 10032 10021 10154, 10250, 10093, 10236, 10180, 11250, 10150, 10030, 10178, 10381, 10386, 10036, 10179, 10381, 10180, 10199, 10868, 10056, 11917 10843, 10700 10093, 10055 10060, 10030, 10185, 10019, 10056 10051, 10817, 11250, 10474, 10019, 10866 11910, 10264 10180 10156, 10178, 10866 11910, 10264 10817, 10264 1081, 1082, 10818, 10817, 11704, 10170, 10264, 10019, 10497 10093, 10178, 11150, 10092, 10161 10030, 10178, 10824 10018 10092 10280 10180 10154, 10250, 10166, 11924, 11913, 10650, 11927	Shen Ying Shencai Shencai Shencai Shencai Sheng Chia Shenyang Shogun Signature Simpson Skygiant Skyworth Sony Soundesign Sowa Spectricon Squareview SSS Starlite Studio Experie Supre-Macy Supreme SVA Sylvania Symphonic Synco Tacico Tai Yi Taishan Tandy Tashiko	10039, 10165, 10474, 10688, 10787, 10036, 11917 2e 11950 10092, 10003, 10474, 10179 10145, 10264 10093, 10236, 10179, 11150, 10474 10817, 10264 10019 10016 10187, 10186 10180 10748, 10264, 10037, 10817 11100, 10000, 10036, 10650, 11300, 10111, 11925, 10080, 10834, 11904 10180, 10178, 10179, 10186 10156, 10051, 10060, 10178, 10036, 10092, 10474, 11150 10003 10171 10180, 10019 10180 ience 10843 10046 10000 10748, 10587, 10865, 10872, 10768, 10871, 10870 10054, 10030, 10171, 11931, 10381, 11944, 10020, 10096 10180, 10171, 11913, 11904 10000, 10451, 10093, 10060, 10178, 10092, 1036, 10474 10178, 10179, 11150, 10092, 10474 11150 10817, 10391 10093 11150, 10650, 10092	America Action American High Amoisonic Anam Anam National Asha Audiovox Beaumark Bell & Howell Blaupunkt Broksonic Calix Canon Carver CCE Changhong Citizen Colt Craig Curtis Mathes CyberPower Daewoo Dell Denon DirecTV Dish Network Sy Dishpro Durabrand Dynatech Echostar Electrohome Electrophonic	21972 n 20278 h 200278 h 20035 20479 20162, 20037, 20240, 20278, 20226, 21037 ll 20162, 20226 20240 20037, 20278 20240 20104 20226 20184, 20121, 20209, 20002, 20348, 20295, 21479, 20479 20035, 21174, 20167 20081 20072, 20278 20048, 20081 20037, 20278, 21278 20072 20035, 20174, 20240, 20072, 20271 20060, 20035, 20162, 20041, 20760, 21035 20240 21972 20045, 20104, 20278, 20210, 20368, 21278, 20637, 20047, 20278 20072 20045, 20104, 20278, 20210, 20368, 21278, 20637, 20047, 20279, 20210, 20368, 21278, 20637, 20048, 201972 20042 20739, 21989, 21954, 21949 System 21943, 21946, 21945, 21944 21944, 21943 20037, 20038 20000 21943, 21946, 21945, 21944 20037	MTC Multitech NAD National NEC Newave Nikko Nikko Nikon Noblex Northgate Olympus Onkyo Optimus Optonica Orion Panarex Panasonic Pansat Penney Pentax Philco Philips Pilot Pioneer Polk Audio Profitronic Proscan	20240, 20000 20000, 20072 20058 20226 20035, 20037, 20048, 20104, 20067, 20041, 20038, 20040, 20008, 20370 20037 20037 20253, 20034 20240 21972 20035, 20226, 21046 20222 21062, 20162, 20037, 20048, 20104, 21048, 21262, 20593, 21162, 20058, 20432 20062 20184, 20209, 20002, 20479, 20295, 21479 21950 21062, 20035, 20162, 20037, 20048, 20104, 21048, 21162, 20258, 20432 20062 20184, 20209, 20002, 20479, 20226, 20616, 21162, 20035, 20037, 20240, 20042, 20038, 21035, 20040, 20054, 21237 20042, 20105 20035, 20037, 20240, 20042, 20038, 21035, 20042, 20105 20035, 20081, 20000, 20226, 20479 20037 20042, 20067, 20058 20081 20040 20060, 20760, 21954, 20202, 21060, 20761	Wards White Westingh XR-1000 Yamaha Zenith ZT Group Setup Cod ABS Alienware CyberPower Gateway Hewlett Packare Howard Compu HP iBUYPOWER InterVideo Jensen JVC Keyspan KWorld LG Linksys Macro Image Te Media Center Pe Microsoft Mind Motorola MyHD Northgate Panasonic	20060, 20035, 20048, 20047, 20081, 20240, 20000, 20042, 20072, 20062, 20212, 20760 100use 20209, 20072, 20637 20035, 20000, 20072 20041, 20038 20039, 20033, 20000, 20209, 20034, 20479, 21479, 21139, 20637 21972 101272 101272 101272 101272 101272 101272 101272 101272 101272 101272 101272 101393 10165 101384 101344 101403 101415 101365 101365 101365 101365 101365 101365 101365 101365 101365 101365 101365 101365 101365 101365 101365 101365 101365 101365 101363 101363 101363 101383 101272 10120
Proscan 20522 Provision 20778 Qwestar 20651 RCA 20522, 20571, 20717, 20822, 21193, 21974, 21132, 21965, 21022, 21913 Regent 21938 Rio 20869 Rotel 20623 Rowa 20823 Sampo 20752, 20698 Samsung 20490, 20573, 20820, 21932, 21075, 20899, 21979 Sanyo 20695, 20670, 21967, 20873 Sharp 20630, 20752 Sharper Image 21995, 21117 Sherwood 21043, 20770, 20633, 21077 Shinsonc 20717 Shinsonc 20573 Sonic Blue 20869, 21970, 21099 Sony 20533, 21537, 21099 Sony 20533, 21537, 21099 Sony 20533, 21537, 21099 Sony 20533, 21539, 21099 Sony 20533, 21530, 21094, 21015 <th< td=""><td>Voom 00869 Zenith 00856, 01856 Setup Codes for TVs 888 10264 A-Mark 10003 Abex 10032 Addison 11150, 10653, 10092 Admiral 10093, 10463 Adventu 10046 Aiko 10092 Aiwa 11914, 11910 Akai 10812, 10702, 10030, 10672, 11903, 10264 Alaron 10179 Albatron 10843, 10700 Ambassador 10177 America Action 10180 Ampro 10751 Anam 10250, 10180, 10003, 10700, 10161, 10628 Anam National 10051 Ano 10451, 10093, 10180, 10003, 10700, 10161, 10628 Anhua 10051 AOC 10451, 10093, 10180, 10060, 10030, 10178, 10018, 10052, 10474, 10033, 10092, 10179 Achipike 10264 Apex Digital 10748, 10765, 10767, 11943, 10879 Archer 10003 Audiovox 10451, 10180, 10875, 11952, 10802, 11951, 10092, 10624, 10317, 10003</td><td>Firstar Fisher Fortress Fujitsu Funai Furi Futuretech Ganxin Gateway GE General Gibralter Gintai Go Video GoldStar Goodmans Grunpy Haier Haiyan Hallmark Hankook Harley Davidson Harrard Havermy Hello Kitty Himitsu Hisense Hitachi</td><td>10236 10154,10159 10093 10180,10853,10179,10809,10683 10180,10171,10264,11904,10179,10342 10145,10817,10264 10180 10817 11756,11755 11447,10047,11454,10051,10451,10180,10030,10178,10092,11147,11919,10055,10027,11917,10135,10282,11347,10021,11907,11907,11902 10186 10017,10030,10019 11150,10474 10886 10154,10030,10178,11926,10019,10037,11910,10001,10032,10056,11150,10039 10360 10180,10179 11034,10768 101264,10817 10178 10180,10030,10178,11019,10056,10628 11904,10179 11034,10768 101904,10179 10180,10030,10178,10019,10056,10628 11904,10179 10180 10093 10451 10180,10628 10156,10748,10145 11256,10156,10030,10178,11145,10145,10038,11245,10092,10027,10381,10036,11150,10036,11150,10036,11150,10036,11150,10036,11150,10036,11150,10036,11150,10036,11150,10036,11150,10036,11150,10036,11150,10036,11150,10036,11150,10036,11036,10032,10039,10157,10016,10179,10474</td><td>Megatron MEI Meile Memorex Mermaid MGA Midland Minutz Mitsubishi Monivision Motorola MTC Mudan Multitech NAD Nanbao Nansheng National NEC Newave Nikko Nikon Norcent Noshi NTC Onking Onwa Optimus Optoma</td><td>10700 10178, 10145, 10003 10185 10264, 11910, 10817 10154, 10463, 10150, 10178, 10179, 11920, 11927, 10016, 11911, 11926, 11924 10037 10150, 10030, 10178, 11907, 10019 10047, 10017, 10051, 10039, 10135, 10032 10021 10154, 10250, 10093, 10236, 10180, 11250, 10150, 10030, 10178, 10381, 10836, 10036, 10179, 10817, 11150, 10474, 10019, 10868, 10056, 11917 10843, 10700 10093, 10055 10060, 10030, 10185, 10019, 10056 10051, 10817, 10264 10180 10156, 10178, 10866 11910, 10264 10817, 10264 10817, 10264 10051 10154, 10156, 10051, 10053, 10030, 10178, 10046, 11150, 10056, 10165, 10186, 10474, 10036, 1082, 10381, 10817, 11704, 10170, 10264, 10019, 10479 10093, 10178, 11150, 10051, 10170, 10264, 10019, 10479 10093, 10178, 11150, 10051, 10170, 10264, 10019, 10479 10093, 10178, 11150, 10092, 10161 10030, 10178, 10092 11910 10748, 10824 10018 10092 10280 10180 101587</td><td>Shen Ying Shencai Shencai Sheng Chia Shenyang Shogun Signature Simpson Skygiant Skyworth Sony Soundesign Sowa Spectricon Squareview SSS Starlite Studio Experie: Supre-Macy Supreme SVA Sylvania Symphonic Synco Tacico Tai Yi Taishan Tandy Tashiko Tatung</td><td>10039, 10165, 10474, 10688, 10787, 10036, 11917 ge 11950 10092, 10003, 10474, 10179 10145, 10264 10093, 10236, 10179, 11150, 10474 10817, 10264 10019 10016 10187, 10186 10180 10748, 10264, 10037, 10817 11100, 10000, 10036, 10650, 11300, 10111, 11925, 10080, 10834, 11904 10180, 10178, 10179, 10186 10156, 10051, 10060, 10178, 10036, 10092, 10474, 11150 10003 10171 10180, 10019 10180 10748, 10587, 10865, 10872, 10768, 10871, 10870 10748, 1030, 10171, 11931, 10381, 11944, 10020, 10096 10748, 10587, 10865, 10872, 10768, 10871, 10870 10180, 10171, 11913, 11904 10000, 10451, 10093, 10060, 10178, 10092, 1036, 10474 10178, 10179, 11150, 10092, 10474 11150 10003 11150, 10650, 10092 10054, 10154, 10156, 10051, 10060, 11150, 10474, 10156, 10055, 11756, 10003</td><td>America Action American High Amoisonic Anam Anam National Asha Audiovox Beaumark Bell & Howell Blaupunkt Broksonic Calix Canon Carver CCE Changhong Citizen Colt Craig Curtis Mathes Cybernex CyberPower Daewoo Dell Denon DirecTV Dish Network Sy Dishpro Durabrand Dynatech Echostar Electrohome</td><td>21972 n 20278 h 200278 h 20035 20479 20162, 20037, 20240, 20278, 20226, 21037 ll 20162, 20226 20240 20037, 20278 20240 20104 20226 20184, 20121, 20209, 20002, 20348, 20295, 21479, 20479 20037 20035, 21174, 20167 20081 20072, 20278 20048, 20081 20072, 20278 20048, 20081 20037, 20078, 21278 20072 20037, 20079, 21278 20072 20037, 20047, 20240, 20072, 20271 20060, 20035, 20162, 20041, 20760, 21035 20240 21972 20045, 20104, 20278, 20210, 20368, 21278, 20637, 20046, 20212, 20561 21972 20049 20739, 21989, 21954, 21949 System 21943, 21946, 21945, 21944 21944, 21943 20039, 20038 20000 21943, 21946, 21945, 21944 20037 20037 20037 20037 20037 20032 20035, 20037, 20184, 20240, 20045, 20000,</td><td>MTC Multitech NAD National NEC Newave Nikko Nikko Nikon Noblex Northgate Olympus Onkyo Optimus Optonica Orion Panarex Panasonic Pansat Penney Pentax Philco Philips Pilot Pioneer Polk Audio Profitronic Proscan Protec Pulsar Qisheng Quarter</td><td>20240, 20000 20000, 20072 20058 20226 20035, 20037, 20048, 20104, 20067, 20041, 20038, 20040, 20008, 20370 20037 20037 20037 20253, 20034 20240 21972 20035, 20226, 21046 20222 21062, 20162, 20037, 20048, 20104, 21048, 21262, 20593, 21162, 20058, 20432 20062 20184, 20209, 20002, 20479, 20295, 21479 21950 21062, 20035, 20162, 20077, 20226, 20616, 21162, 20225, 2035,</td><td>Wards White Westingh XR-1000 Yamaha Zenith ZT Group Setup Cod ABS Alienware CyberPower Gateway Hewlett Packare Howard Compu HP IBUYPOWER InterVideo Jensen JVC Keyspan KWorld LG Linksys Macro Image Te Media Center Po Microsoft Mind Motorola MyHD Northgate Panasonic Pinnacle System Pioneer Princeton Rabbit</td><td>20060, 20035, 20048, 20047, 20081, 20240, 20000, 20042, 20072, 20062, 20212, 20760 100use 20209, 20072, 20637 20035, 20000, 20072 20041, 20038 20039, 20033, 20000, 20209, 20034, 20479, 21479, 21139, 20637 21972 1les for Video Accessories 01272 01272 01272 01272 01272 01272 01272 01272 01272 01272 01393 01165 01384 01344 01403 01415 01365 8chnology 01383 CO1272 01272 01272 01272 01363 01383 01363 01383 01383 01288 01010 000113, 00295 00081</td></th<>	Voom 00869 Zenith 00856, 01856 Setup Codes for TVs 888 10264 A-Mark 10003 Abex 10032 Addison 11150, 10653, 10092 Admiral 10093, 10463 Adventu 10046 Aiko 10092 Aiwa 11914, 11910 Akai 10812, 10702, 10030, 10672, 11903, 10264 Alaron 10179 Albatron 10843, 10700 Ambassador 10177 America Action 10180 Ampro 10751 Anam 10250, 10180, 10003, 10700, 10161, 10628 Anam National 10051 Ano 10451, 10093, 10180, 10003, 10700, 10161, 10628 Anhua 10051 AOC 10451, 10093, 10180, 10060, 10030, 10178, 10018, 10052, 10474, 10033, 10092, 10179 Achipike 10264 Apex Digital 10748, 10765, 10767, 11943, 10879 Archer 10003 Audiovox 10451, 10180, 10875, 11952, 10802, 11951, 10092, 10624, 10317, 10003	Firstar Fisher Fortress Fujitsu Funai Furi Futuretech Ganxin Gateway GE General Gibralter Gintai Go Video GoldStar Goodmans Grunpy Haier Haiyan Hallmark Hankook Harley Davidson Harrard Havermy Hello Kitty Himitsu Hisense Hitachi	10236 10154,10159 10093 10180,10853,10179,10809,10683 10180,10171,10264,11904,10179,10342 10145,10817,10264 10180 10817 11756,11755 11447,10047,11454,10051,10451,10180,10030,10178,10092,11147,11919,10055,10027,11917,10135,10282,11347,10021,11907,11907,11902 10186 10017,10030,10019 11150,10474 10886 10154,10030,10178,11926,10019,10037,11910,10001,10032,10056,11150,10039 10360 10180,10179 11034,10768 101264,10817 10178 10180,10030,10178,11019,10056,10628 11904,10179 11034,10768 101904,10179 10180,10030,10178,10019,10056,10628 11904,10179 10180 10093 10451 10180,10628 10156,10748,10145 11256,10156,10030,10178,11145,10145,10038,11245,10092,10027,10381,10036,11150,10036,11150,10036,11150,10036,11150,10036,11150,10036,11150,10036,11150,10036,11150,10036,11150,10036,11150,10036,11150,10036,11150,10036,11150,10036,11036,10032,10039,10157,10016,10179,10474	Megatron MEI Meile Memorex Mermaid MGA Midland Minutz Mitsubishi Monivision Motorola MTC Mudan Multitech NAD Nanbao Nansheng National NEC Newave Nikko Nikon Norcent Noshi NTC Onking Onwa Optimus Optoma	10700 10178, 10145, 10003 10185 10264, 11910, 10817 10154, 10463, 10150, 10178, 10179, 11920, 11927, 10016, 11911, 11926, 11924 10037 10150, 10030, 10178, 11907, 10019 10047, 10017, 10051, 10039, 10135, 10032 10021 10154, 10250, 10093, 10236, 10180, 11250, 10150, 10030, 10178, 10381, 10836, 10036, 10179, 10817, 11150, 10474, 10019, 10868, 10056, 11917 10843, 10700 10093, 10055 10060, 10030, 10185, 10019, 10056 10051, 10817, 10264 10180 10156, 10178, 10866 11910, 10264 10817, 10264 10817, 10264 10051 10154, 10156, 10051, 10053, 10030, 10178, 10046, 11150, 10056, 10165, 10186, 10474, 10036, 1082, 10381, 10817, 11704, 10170, 10264, 10019, 10479 10093, 10178, 11150, 10051, 10170, 10264, 10019, 10479 10093, 10178, 11150, 10051, 10170, 10264, 10019, 10479 10093, 10178, 11150, 10092, 10161 10030, 10178, 10092 11910 10748, 10824 10018 10092 10280 10180 101587	Shen Ying Shencai Shencai Sheng Chia Shenyang Shogun Signature Simpson Skygiant Skyworth Sony Soundesign Sowa Spectricon Squareview SSS Starlite Studio Experie: Supre-Macy Supreme SVA Sylvania Symphonic Synco Tacico Tai Yi Taishan Tandy Tashiko Tatung	10039, 10165, 10474, 10688, 10787, 10036, 11917 ge 11950 10092, 10003, 10474, 10179 10145, 10264 10093, 10236, 10179, 11150, 10474 10817, 10264 10019 10016 10187, 10186 10180 10748, 10264, 10037, 10817 11100, 10000, 10036, 10650, 11300, 10111, 11925, 10080, 10834, 11904 10180, 10178, 10179, 10186 10156, 10051, 10060, 10178, 10036, 10092, 10474, 11150 10003 10171 10180, 10019 10180 10748, 10587, 10865, 10872, 10768, 10871, 10870 10748, 1030, 10171, 11931, 10381, 11944, 10020, 10096 10748, 10587, 10865, 10872, 10768, 10871, 10870 10180, 10171, 11913, 11904 10000, 10451, 10093, 10060, 10178, 10092, 1036, 10474 10178, 10179, 11150, 10092, 10474 11150 10003 11150, 10650, 10092 10054, 10154, 10156, 10051, 10060, 11150, 10474, 10156, 10055, 11756, 10003	America Action American High Amoisonic Anam Anam National Asha Audiovox Beaumark Bell & Howell Blaupunkt Broksonic Calix Canon Carver CCE Changhong Citizen Colt Craig Curtis Mathes Cybernex CyberPower Daewoo Dell Denon DirecTV Dish Network Sy Dishpro Durabrand Dynatech Echostar Electrohome	21972 n 20278 h 200278 h 20035 20479 20162, 20037, 20240, 20278, 20226, 21037 ll 20162, 20226 20240 20037, 20278 20240 20104 20226 20184, 20121, 20209, 20002, 20348, 20295, 21479, 20479 20037 20035, 21174, 20167 20081 20072, 20278 20048, 20081 20072, 20278 20048, 20081 20037, 20078, 21278 20072 20037, 20079, 21278 20072 20037, 20047, 20240, 20072, 20271 20060, 20035, 20162, 20041, 20760, 21035 20240 21972 20045, 20104, 20278, 20210, 20368, 21278, 20637, 20046, 20212, 20561 21972 20049 20739, 21989, 21954, 21949 System 21943, 21946, 21945, 21944 21944, 21943 20039, 20038 20000 21943, 21946, 21945, 21944 20037 20037 20037 20037 20037 20032 20035, 20037, 20184, 20240, 20045, 20000,	MTC Multitech NAD National NEC Newave Nikko Nikko Nikon Noblex Northgate Olympus Onkyo Optimus Optonica Orion Panarex Panasonic Pansat Penney Pentax Philco Philips Pilot Pioneer Polk Audio Profitronic Proscan Protec Pulsar Qisheng Quarter	20240, 20000 20000, 20072 20058 20226 20035, 20037, 20048, 20104, 20067, 20041, 20038, 20040, 20008, 20370 20037 20037 20037 20253, 20034 20240 21972 20035, 20226, 21046 20222 21062, 20162, 20037, 20048, 20104, 21048, 21262, 20593, 21162, 20058, 20432 20062 20184, 20209, 20002, 20479, 20295, 21479 21950 21062, 20035, 20162, 20077, 20226, 20616, 21162, 20225, 2035,	Wards White Westingh XR-1000 Yamaha Zenith ZT Group Setup Cod ABS Alienware CyberPower Gateway Hewlett Packare Howard Compu HP IBUYPOWER InterVideo Jensen JVC Keyspan KWorld LG Linksys Macro Image Te Media Center Po Microsoft Mind Motorola MyHD Northgate Panasonic Pinnacle System Pioneer Princeton Rabbit	20060, 20035, 20048, 20047, 20081, 20240, 20000, 20042, 20072, 20062, 20212, 20760 100use 20209, 20072, 20637 20035, 20000, 20072 20041, 20038 20039, 20033, 20000, 20209, 20034, 20479, 21479, 21139, 20637 21972 1les for Video Accessories 01272 01272 01272 01272 01272 01272 01272 01272 01272 01272 01393 01165 01384 01344 01403 01415 01365 8chnology 01383 CO1272 01272 01272 01272 01363 01383 01363 01383 01383 01288 01010 000113, 00295 00081
Proscan 20522 Provision 20778 Qwestar 20651 RCA 20522, 20571, 20717, 20822, 21193, 21974, 21132, 21965, 21022, 21913 Regent 21938 Rio 20859 Rotel 20623 Rowa 20823 Saba 21977 Sampo 20752, 20698 Samsung 20490, 20573, 20820, 21932, 21075, 20899, 21979 Sansui 20695 Sanyo 20695, 20670, 21967, 20873 Sharp 20630, 20752 Sharper Image 21995, 21117 Sherwood 21043, 20770, 20633, 21077 Shinco 20717 Shinsonic 20533, 20839, 21931 Sigma Designs 20674 Sonic Blue 20869, 21970, 21099 Sony 20533, 21533, 20864, 21033, 21904, 22020, 21903, 21981, 20772, 21934 Sungale 21074 Superscan 20821 SVA 20717, 20860, 21105 Sylvania 20821, 20675 Symphonic 20675 Teac <td>Voom 00869 Zenith 00856, 01856 Setup Codes for TVs 888 10264 A-Mark 10003 Addison 11150, 10653, 10092 Admiral 10093, 10463 Advent 10761, 10817, 10815, 11933, 10783, 10842 Adventura 10046 Aiko 10092 Aiwa 11914, 11910 Akai 10812, 10702, 10030, 10672, 11903, 10264 Alaron 10179 Albatron 10843, 10700 Ampro 10751 Anam 10250, 10180, 10003, 10700, 10161, 10628 Anam National 10250, 10161, 10055, 10650 Anhua 10051 AOC 10451, 10093, 10180, 10008, 10030, 10178, 10018, 10052, 10474, 10009, 10185, 11150, 10018, 10052, 10474, 10009, 10185, 11150, 10018, 10052, 10474, 10009, 1064 Apex Digital 10748, 10765, 10767, 11943, 10879 Archer 10003 Audiovox 10451, 10180, 10875, 11952, 10802, 11951, 10092, 10623, 11937, 10003 Axion 11937 Baihe 100001, 10391 Baosheng</td> <td>Firstar Fisher Fortress Fujitsu Funai Furi Furi Furietch Ganxin Gateway GE General Gibralter Gintai Go Video GoldStar Goodmans Grunpy Haier Haiyan Hallmark Hankook Harley Davidson Harrand/Kardon Harrvard Havermy Hello Kitty Himitsu Hisense Hitachi</td> <td>10236 10154, 10159 10093 10180, 10853, 10179, 10809, 10683 10180, 10171, 10264, 11904, 10179, 10342 10145, 10817, 10264 10180 10817 11756, 11755 11447, 10047, 11454, 10051, 10451, 10180, 10030, 10178, 10092, 11147, 11919, 10055, 10027, 11917, 10135, 10282, 11347, 10021, 11907, 11922 10186 10017, 10030, 10019 11150, 10474 10886 10154, 10030, 10178, 11926, 10019, 10037, 11910, 10001, 10032, 10056, 11150, 10039 10360 10180, 10179 11034, 10768 10264, 10817 10178 10180, 10030, 10178, 11091, 10056, 10628 11904, 10179 10054 10180, 10030, 10178, 11019, 10056, 10628 11904, 10179 10054 10180, 10030, 10178, 11019, 10056, 10628 11904, 10179 10054 10180, 10030, 10178, 11019, 10056, 10628 11904, 10179 10054 10180, 10030, 10178, 11019, 10056, 10628 11904, 10179 10056 11080, 10628 10156, 10748, 10145 11256, 10156, 10030, 10178, 11145, 10145, 10150, 10056, 11094, 10151, 10165, 10019, 10180, 10032, 10039, 10157, 10016, 10179, 10474 10093, 11910, 10817, 10264</td> <td>Megatron MEI Meile Memorex Mermaid MGA Midland Minutz Mitsubishi Monivision Motorola MTC Mudan Multitech NAD Nanbao Nansheng National NEC Newave Nikko Nikon Norcent Norcent North Onking Onwa Optimus</td> <td>10700 10178, 10145, 10003 10185 10264, 11910, 10817 10154, 10463, 10150, 10178, 10179, 11920, 11927, 10016, 11911, 11926, 11924 10037 10150, 10030, 10178, 11907, 10019 10047, 10017, 10051, 10039, 10135, 10032 10021 10154, 10250, 10093, 10236, 10180, 11250, 10150, 10030, 10178, 10381, 10386, 10036, 10179, 10381, 10180, 10199, 10868, 10056, 11917 10843, 10700 10093, 10055 10060, 10030, 10185, 10019, 10056 10051, 10817, 11250, 10474, 10019, 10866 11910, 10264 10180 10156, 10178, 10866 11910, 10264 10817, 10264 1081, 1082, 10818, 10817, 11704, 10170, 10264, 10019, 10497 10093, 10178, 11150, 10092, 10161 10030, 10178, 10824 10018 10092 10280 10180 10154, 10250, 10166, 11924, 11913, 10650, 11927</td> <td>Shen Ying Shencai Shencai Shencai Sheng Chia Shenyang Shogun Signature Simpson Skygiant Skyworth Sony Soundesign Sowa Spectricon Squareview SSS Starlite Studio Experie Supre-Macy Supreme SVA Sylvania Symphonic Synco Tacico Tai Yi Taishan Tandy Tashiko Tatung Technics</td> <td>10039, 10165, 10474, 10688, 10787, 10036, 11917 2e 11950 10092, 10003, 10474, 10179 10145, 10264 10093, 10236, 10179, 11150, 10474 10817, 10264 10019 10016 10187, 10186 10180 10748, 10264, 10037, 10817 11100, 10000, 10036, 10650, 11300, 10111, 11925, 10080, 10834, 11904 10180, 10178, 10179, 10186 10156, 10051, 10060, 10178, 10036, 10092, 10474, 11150 10003 10171 10180, 10019 10180 ience 10843 10046 10000 10748, 10587, 10865, 10872, 10768, 10871, 10870 10748, 1030, 10171, 11931, 10381, 11944, 10020, 10096 10180, 10171, 11913, 11904 10000, 10451, 10093, 10060, 10178, 10092, 1036, 10474 10178, 10179, 11150, 10092, 10474 11150 10817, 10391 10093 11150, 10650, 10092 10054, 10154, 10156, 10051, 10060, 11150, 10474, 10056, 10095 10165, 10093 11150, 10650, 10092 10054, 10154, 10156, 10051, 10060, 11150, 10474, 10056, 10055, 11756, 10003 10250, 10051</td> <td>America Action American High Amoisonic Anam Anam National Asha Audiovox Beaumark Bell & Howell Blaupunkt Broksonic Calix Canon Carver CCE Changhong Citizen Colt Craig Curtis Mathes CyberPower Daewoo Dell Denon DirecTV Dish Network Sy Dishpro Durabrand Dynatech Echostar Electrophonic Emerex</td> <td>21972 n 20278 h 200278 h 20035 20479 20162, 20037, 20240, 20278, 20226, 21037 il 20162, 20226 20240 20037, 20278 20240 20104 20226 20184, 20121, 20209, 20002, 20348, 20295, 21479, 20479 20035, 21174, 20167 20081 20072, 20278 20048, 20081 20072, 20278, 21278 20072 20035, 20174, 20240, 20072, 20271 20060, 20035, 20162, 20041, 20760, 21035 20240 21972 20045, 20104, 20278, 20210, 20368, 21278, 20637, 20047, 20278 20049 21972 20045, 20104, 20278, 20210, 20368, 21278, 20637, 20048, 20121, 20561 21972 20042 20739, 21989, 21954, 21949 System 21943, 21946, 21945, 21944 21944, 21943 20039, 20038 20000 21943, 21946, 21945, 21944 20037 20037 20037 20037 20037 20037 20037 20037 20037, 20043, 20209, 20002, 20278, 20295, 20295, 20278, 20295, 20295, 20278, 20295, 20295, 20278, 20295, 20295, 20278, 20295, 20295, 20278, 20295, 20295, 20278, 20295, 20295, 20278, 20295, 20295, 20278, 20295, 20295, 20278, 20295, 20295, 20278, 20295, 20295, 20278,</td> <td>MTC Multitech NAD National NEC Newave Nikko Nikon Noblex Northgate Olympus Onkyo Optimus Optonica Orion Panarex Panasonic Pansat Penney Pentax Philco Philips Pilot Pioneer Polk Audio Profitronic Proscan Protec Pulsar Qisheng</td> <td>20240, 20000 20000, 20072 20000, 20072 20058 20026 20035, 20037, 20048, 20104, 20067, 20041, 20038, 20040, 20008, 20370 20037 20037 20253, 20034 20240 21972 20035, 20226, 21046 20222 21062, 20162, 20037, 20048, 20104, 21048, 21262, 20162, 20053, 21162, 20058, 20452 20062 20184, 2029, 20002, 20479, 20295, 21479 21950 21062, 20035, 20162, 20077, 20226, 20616, 21162, 20225, 20367, 20227, 21035, 21262 21950 20035, 20037, 20240, 20042, 20038, 21035, 20040, 20054, 21237 20042, 20105 20035, 20000, 20226, 20479 20035, 20081, 20000, 20226, 20739, 21381, 20110, 20618, 21181, 20563, 21081, 21949, 20062 20037 20042, 20067, 20058 20081 20240 20060, 20760, 21954, 20202, 21060, 20761 20072 20039 20060</td> <td>Wards White Westingh XR-1000 Yamaha Zenith ZT Group Setup Cod ABS Alienware CyberPower Gateway Hewlett Packare Howard Compu HP iBUYPOWER InterVideo Jensen JVC Keyspan KWorld LG Linksys Macro Image Te Media Center Pd Microsoft Mind Motorola MyHD Northgate Panasonic Pinnacle System Pioneer Princeton Rabbit Roku</td> <td>20060, 20035, 20048, 20047, 20081, 20240, 20000, 20042, 20072, 20062, 20212, 20760 100use 20209, 20072, 20062, 20212, 20760 100use 20209, 20072, 20063, 20212, 20760 100use 20209, 20072, 20637 100use 20209, 20034, 20479, 20479, 20479, 20479, 20479, 20479, 20479, 20479, 20479, 20479, 20479, 20479, 20479, 20479, 20479, 20479, 20472 101272 101272 101272 101272 101272 101272 101272 101272 101393 10165 101384 101403 101415 101344 10403 10415 1036</td>	Voom 00869 Zenith 00856, 01856 Setup Codes for TVs 888 10264 A-Mark 10003 Addison 11150, 10653, 10092 Admiral 10093, 10463 Advent 10761, 10817, 10815, 11933, 10783, 10842 Adventura 10046 Aiko 10092 Aiwa 11914, 11910 Akai 10812, 10702, 10030, 10672, 11903, 10264 Alaron 10179 Albatron 10843, 10700 Ampro 10751 Anam 10250, 10180, 10003, 10700, 10161, 10628 Anam National 10250, 10161, 10055, 10650 Anhua 10051 AOC 10451, 10093, 10180, 10008, 10030, 10178, 10018, 10052, 10474, 10009, 10185, 11150, 10018, 10052, 10474, 10009, 10185, 11150, 10018, 10052, 10474, 10009, 1064 Apex Digital 10748, 10765, 10767, 11943, 10879 Archer 10003 Audiovox 10451, 10180, 10875, 11952, 10802, 11951, 10092, 10623, 11937, 10003 Axion 11937 Baihe 100001, 10391 Baosheng	Firstar Fisher Fortress Fujitsu Funai Furi Furi Furietch Ganxin Gateway GE General Gibralter Gintai Go Video GoldStar Goodmans Grunpy Haier Haiyan Hallmark Hankook Harley Davidson Harrand/Kardon Harrvard Havermy Hello Kitty Himitsu Hisense Hitachi	10236 10154, 10159 10093 10180, 10853, 10179, 10809, 10683 10180, 10171, 10264, 11904, 10179, 10342 10145, 10817, 10264 10180 10817 11756, 11755 11447, 10047, 11454, 10051, 10451, 10180, 10030, 10178, 10092, 11147, 11919, 10055, 10027, 11917, 10135, 10282, 11347, 10021, 11907, 11922 10186 10017, 10030, 10019 11150, 10474 10886 10154, 10030, 10178, 11926, 10019, 10037, 11910, 10001, 10032, 10056, 11150, 10039 10360 10180, 10179 11034, 10768 10264, 10817 10178 10180, 10030, 10178, 11091, 10056, 10628 11904, 10179 10054 10180, 10030, 10178, 11019, 10056, 10628 11904, 10179 10054 10180, 10030, 10178, 11019, 10056, 10628 11904, 10179 10054 10180, 10030, 10178, 11019, 10056, 10628 11904, 10179 10054 10180, 10030, 10178, 11019, 10056, 10628 11904, 10179 10056 11080, 10628 10156, 10748, 10145 11256, 10156, 10030, 10178, 11145, 10145, 10150, 10056, 11094, 10151, 10165, 10019, 10180, 10032, 10039, 10157, 10016, 10179, 10474 10093, 11910, 10817, 10264	Megatron MEI Meile Memorex Mermaid MGA Midland Minutz Mitsubishi Monivision Motorola MTC Mudan Multitech NAD Nanbao Nansheng National NEC Newave Nikko Nikon Norcent Norcent North Onking Onwa Optimus	10700 10178, 10145, 10003 10185 10264, 11910, 10817 10154, 10463, 10150, 10178, 10179, 11920, 11927, 10016, 11911, 11926, 11924 10037 10150, 10030, 10178, 11907, 10019 10047, 10017, 10051, 10039, 10135, 10032 10021 10154, 10250, 10093, 10236, 10180, 11250, 10150, 10030, 10178, 10381, 10386, 10036, 10179, 10381, 10180, 10199, 10868, 10056, 11917 10843, 10700 10093, 10055 10060, 10030, 10185, 10019, 10056 10051, 10817, 11250, 10474, 10019, 10866 11910, 10264 10180 10156, 10178, 10866 11910, 10264 10817, 10264 1081, 1082, 10818, 10817, 11704, 10170, 10264, 10019, 10497 10093, 10178, 11150, 10092, 10161 10030, 10178, 10824 10018 10092 10280 10180 10154, 10250, 10166, 11924, 11913, 10650, 11927	Shen Ying Shencai Shencai Shencai Sheng Chia Shenyang Shogun Signature Simpson Skygiant Skyworth Sony Soundesign Sowa Spectricon Squareview SSS Starlite Studio Experie Supre-Macy Supreme SVA Sylvania Symphonic Synco Tacico Tai Yi Taishan Tandy Tashiko Tatung Technics	10039, 10165, 10474, 10688, 10787, 10036, 11917 2e 11950 10092, 10003, 10474, 10179 10145, 10264 10093, 10236, 10179, 11150, 10474 10817, 10264 10019 10016 10187, 10186 10180 10748, 10264, 10037, 10817 11100, 10000, 10036, 10650, 11300, 10111, 11925, 10080, 10834, 11904 10180, 10178, 10179, 10186 10156, 10051, 10060, 10178, 10036, 10092, 10474, 11150 10003 10171 10180, 10019 10180 ience 10843 10046 10000 10748, 10587, 10865, 10872, 10768, 10871, 10870 10748, 1030, 10171, 11931, 10381, 11944, 10020, 10096 10180, 10171, 11913, 11904 10000, 10451, 10093, 10060, 10178, 10092, 1036, 10474 10178, 10179, 11150, 10092, 10474 11150 10817, 10391 10093 11150, 10650, 10092 10054, 10154, 10156, 10051, 10060, 11150, 10474, 10056, 10095 10165, 10093 11150, 10650, 10092 10054, 10154, 10156, 10051, 10060, 11150, 10474, 10056, 10055, 11756, 10003 10250, 10051	America Action American High Amoisonic Anam Anam National Asha Audiovox Beaumark Bell & Howell Blaupunkt Broksonic Calix Canon Carver CCE Changhong Citizen Colt Craig Curtis Mathes CyberPower Daewoo Dell Denon DirecTV Dish Network Sy Dishpro Durabrand Dynatech Echostar Electrophonic Emerex	21972 n 20278 h 200278 h 20035 20479 20162, 20037, 20240, 20278, 20226, 21037 il 20162, 20226 20240 20037, 20278 20240 20104 20226 20184, 20121, 20209, 20002, 20348, 20295, 21479, 20479 20035, 21174, 20167 20081 20072, 20278 20048, 20081 20072, 20278, 21278 20072 20035, 20174, 20240, 20072, 20271 20060, 20035, 20162, 20041, 20760, 21035 20240 21972 20045, 20104, 20278, 20210, 20368, 21278, 20637, 20047, 20278 20049 21972 20045, 20104, 20278, 20210, 20368, 21278, 20637, 20048, 20121, 20561 21972 20042 20739, 21989, 21954, 21949 System 21943, 21946, 21945, 21944 21944, 21943 20039, 20038 20000 21943, 21946, 21945, 21944 20037 20037 20037 20037 20037 20037 20037 20037 20037, 20043, 20209, 20002, 20278, 20295, 20295, 20278, 20295, 20295, 20278, 20295, 20295, 20278, 20295, 20295, 20278, 20295, 20295, 20278, 20295, 20295, 20278, 20295, 20295, 20278, 20295, 20295, 20278, 20295, 20295, 20278, 20295, 20295, 20278, 20295, 20295, 20278,	MTC Multitech NAD National NEC Newave Nikko Nikon Noblex Northgate Olympus Onkyo Optimus Optonica Orion Panarex Panasonic Pansat Penney Pentax Philco Philips Pilot Pioneer Polk Audio Profitronic Proscan Protec Pulsar Qisheng	20240, 20000 20000, 20072 20000, 20072 20058 20026 20035, 20037, 20048, 20104, 20067, 20041, 20038, 20040, 20008, 20370 20037 20037 20253, 20034 20240 21972 20035, 20226, 21046 20222 21062, 20162, 20037, 20048, 20104, 21048, 21262, 20162, 20053, 21162, 20058, 20452 20062 20184, 2029, 20002, 20479, 20295, 21479 21950 21062, 20035, 20162, 20077, 20226, 20616, 21162, 20225, 20367, 20227, 21035, 21262 21950 20035, 20037, 20240, 20042, 20038, 21035, 20040, 20054, 21237 20042, 20105 20035, 20000, 20226, 20479 20035, 20081, 20000, 20226, 20739, 21381, 20110, 20618, 21181, 20563, 21081, 21949, 20062 20037 20042, 20067, 20058 20081 20240 20060, 20760, 21954, 20202, 21060, 20761 20072 20039 20060	Wards White Westingh XR-1000 Yamaha Zenith ZT Group Setup Cod ABS Alienware CyberPower Gateway Hewlett Packare Howard Compu HP iBUYPOWER InterVideo Jensen JVC Keyspan KWorld LG Linksys Macro Image Te Media Center Pd Microsoft Mind Motorola MyHD Northgate Panasonic Pinnacle System Pioneer Princeton Rabbit Roku	20060, 20035, 20048, 20047, 20081, 20240, 20000, 20042, 20072, 20062, 20212, 20760 100use 20209, 20072, 20062, 20212, 20760 100use 20209, 20072, 20063, 20212, 20760 100use 20209, 20072, 20637 100use 20209, 20034, 20479, 20479, 20479, 20479, 20479, 20479, 20479, 20479, 20479, 20479, 20479, 20479, 20479, 20479, 20479, 20479, 20472 101272 101272 101272 101272 101272 101272 101272 101272 101393 10165 101384 101403 101415 101344 10403 10415 1036
Proscan 20522 Provision 20778 Qwestar 20651 RcA 20522, 20571, 20717, 20822, 21193, 21974, 21132, 21965, 21022, 21913 Regent 21938 Rio 20869 Rotel 20623 Rowa 20823 Sampo 20752, 20698 Samsung 20490, 20573, 20820, 21932, 21075, 20899, 21979 Sanyo 20695, 20670, 21967, 20873 Sharp 20630, 20752 Sharper Image 21995, 21117 Sherwood 21043, 20770, 20633, 21077 Shinson 20717 Shinson 20717 Shinson 20574 Sonic Blue 20869, 21970, 21099 Sony 20533, 2033, 2033, 20844, 21033, 21904, 22020, 21903, 21904, 22020, 21903, 21934, 20772, 21934 Sungale 21074 Superscan 20821 SVA 20717, 20860, 21105 Sylvania 20821, 20675 Symphonic 20675 Reac 21984, 20809 Technosonic 20730	Voom 00869 Zenith 00856, 01856 Setup Codes for TVs 888 10264 A-Mark 10003 Abex 10032 Addison 11150, 10653, 10092 Admiral 10093, 10463 Adventu 10046 Aiko 10092 Aiwa 11914, 11910 Akai 10812, 10702, 10030, 10672, 11903, 10264 Alaron 10179 Albatron 108343, 10700 Ambassador 10177 America Action 10180 Ampro 10751 Anam 10250, 10180, 10003, 10700, 10161, 10628 Anam National 10051 Ano 10451, 10093, 10180, 10000, 10030, 10178, 10018, 10052, 10474, 10003, 10092, 10179 Aolinpike 10264 Acher 10003 Audiovox 10451, 10180, 10875, 11952, 10802, 11951, 10092, 10623, 11937, 10003 Axion 11937 Baihe 10264 Baile 10001, 10391 Baohuashi 10264	Firstar Fisher Fortress Fujitsu Funai Furi Furi Formai Furi Ganxin Gateway GE General Gibralter Gintai Go Video GoldStar Goodmans Grunpy Haier Haiyan Hallmark Hankook Harley Davidson Harrman/Kardon Harvard Havermy Hello Kitty Himitsu Hisense Hitachi Hongmei Hongyan	10236 10154,10159 10093 10180,10853,10179,10809,10683 10180,10171,10264,11904,10179,10342 10145,10817,10264 10180 10817 11756,11755 11447,10047,11454,10051,10451,10180,10030,10178,10092,11147,11919,10055,10027,11917,10135,10282,11347,10021,11907,11907,11902 10186 10017,10030,10019 11150,10474 10886 10154,10030,10178,11926,10019,10037,11910,10001,10032,10056,11150,10039 10360 10180,10179 11034,10768 101264,10817 10178 10180,10030,10178,11019,10056,10628 11904,10179 11034,10768 101904,10179 10180,10030,10178,10019,10056,10628 11904,10179 10180 10093 10451 10180,10628 10156,10748,10145 11256,10156,10030,10178,11145,10145,10038,11245,10092,10027,10381,10036,11150,10036,11150,10036,11150,10036,11150,10036,11150,10036,11150,10036,11150,10036,11150,10036,11150,10036,11150,10036,11150,10036,11150,10036,11150,10036,11036,10032,10039,10157,10016,10179,10474	Megatron MEI Meile Memorex Mermaid MGA Midland Minutz Mitsubishi Monivision Motorola MTC Mudan Multitech NAD Nanbao Nansheng National NEC Newave Nikko Nikon Norcent Noshi Norcent Noshi Onking Onwa Optomica Optoma Optomica Orion	10700 10178, 10145, 10003 10185 10264, 11910, 10817 10154, 10463, 10150, 10178, 10179, 11920, 11927, 10016, 11911, 11926, 11924 10037 10150, 10030, 10178, 11907, 10019 10047, 10017, 10051, 10039, 10135, 10032 10021 10154, 10250, 10093, 10236, 10180, 11250, 10150, 10030, 10178, 10381, 10386, 10036, 10179, 10817, 11150, 10474, 10019, 10868, 10056, 11917 10843, 10700 10093, 10055 10060, 10030, 10185, 10019, 10056 10051, 10817, 10264 10180 10156, 10178, 10866 11910, 10264 10817, 10264 10817, 10264 10817, 10264 10817, 10264 10817, 10264 1093, 10185, 1019, 10053, 10030, 10178, 10046, 11150, 10056, 10165, 10186, 10474, 10036, 10882, 10381, 10817, 11704, 10170, 10264, 10019, 10497 10093, 10178, 11150, 10092, 10161 10030, 10178, 10150, 10092, 10161 10030, 10178, 10052 10280 10180 10154, 10250, 10166, 11924, 11913, 10650, 11927 10887 10093, 10165 10236, 10463, 11911, 11905, 10179, 11463, 11927	Shen Ying Shencai Shencai Sheng Chia Shenyang Shogun Signature Simpson Skygiant Skyworth Sony Soundesign Sowa Spectricon Squareview SSS Starlite Studio Experie: Supre-Macy Supreme SVA Sylvania Symphonic Synco Tacico Tai Yi Taishan Tandy Tashiko Tatung	10039, 10165, 10474, 10688, 10787, 10036, 11917 ge 11950 10092, 10003, 10474, 10179 10145, 10264 10093, 10236, 10179, 11150, 10474 10817, 10264 10019 10016 10187, 10186 10180 10748, 10264, 10037, 10817 11100, 10000, 10036, 10650, 11300, 10111, 11925, 10080, 10834, 11904 10180, 10178, 10179, 10186 10156, 10051, 10060, 10178, 10036, 10092, 10474, 11150 10003 10171 10180, 10019 10180 10748, 10587, 10865, 10872, 10768, 10871, 10870 10748, 1030, 10171, 11931, 10381, 11944, 10020, 10096 10748, 10587, 10865, 10872, 10768, 10871, 10870 10180, 10171, 11913, 11904 10000, 10451, 10093, 10060, 10178, 10092, 1036, 10474 10178, 10179, 11150, 10092, 10474 11150 10003 11150, 10650, 10092 10054, 10154, 10156, 10051, 10060, 11150, 10474, 10156, 10055, 11756, 10003	America Action American High Amoisonic Anam Anam National Asha Audiovox Beaumark Bell & Howell Blaupunkt Broksonic Calix Canon Carver CCE Changhong Citizen Colt Craig Curtis Mathes Cybernex CyberPower Daewoo Dell Denon DirecTV Dish Network Sy Dishpro Durabrand Dynatech Echostar Electrohome Electrophonic Emerex Emerson	21972 n 20278 h 20278 h 20278 h 20035 20479 20162, 20037, 20240, 20278, 20226, 21037 ll 20162, 20226 20240 20240 20104 20104 20226 20184, 20121, 20209, 20002, 20348, 20295, 21479, 20479 20037 20035, 21174, 20167 20081 20072, 20278 20048, 20081 20072, 20278 20048, 20081 20037, 20078, 21278 20072 20037, 20078, 21278 20072 20037, 20047, 20240, 20072, 20271 20060, 20035, 20162, 20041, 20760, 21035 20240 21972 20045, 20104, 20278, 20210, 20368, 21278, 20637, 20046, 20212, 20561 21972 20049 20739, 21989, 21954, 21949 System 21943, 21946, 21945, 21944 21944, 21943 20039, 20038 20000 21943, 21946, 21945, 21944 20037 20037 20037 20037 20037 20037 20037 20037, 20043, 20209, 20002, 20278, 20295, 20266, 20479, 21278, 20068, 20208, 20479, 21278, 20061, 20212	MTC Multitech NAD National NEC Newave Nikko Nikon Noblex Northgate Olympus Onkyo Optimus Optonica Orion Pansat Penney Pentax Philco Philips Pilot Pioneer Polk Audio Profitronic Proscan Protec Pulsar Qisheng Quarter Quartz Quasar RadioShack	20240, 20000 20000, 20072 20058 20026 20035, 20037, 20048, 20104, 20067, 20041, 20038, 20040, 20008, 20370 20037 20037 20253, 20034 20240 21972 20035, 20226, 21046 20222 21062, 20162, 20037, 20048, 20104, 21048, 21262, 20593, 21162, 20058, 20452 20062 20184, 20209, 20002, 20479, 20295, 21479 21950 21062, 20035, 20162, 20077, 20226, 20616, 21162, 20225, 20367, 20227, 21035, 21262 21950 2035, 20037, 20240, 20042, 20038, 21035, 20040, 20054, 21181, 20563, 21081, 21949, 20062 2035, 20081, 20000, 20226, 20799, 21381, 20110, 20618, 21181, 20563, 21081, 21949, 20062 20037 20042, 20067, 20058 20081 20240 20060 20046 20046 20046 20046 20046 20055, 20162, 21035, 20077, 21162 20000, 21037	Wards White Westingh XR-1000 Yamaha Zenith ZT Group Setup Cod ABS Alienware CyberPower Gateway Hewlett Packare Howard Compu HP IBUYPOWER InterVideo Jensen JVC Keyspan KWorld LG Linksys Macro Image Te Media Center Po Microsoft Mind Motorola MyHD Northgate Panasonic Pinnacle System Pioneer Princeton Rabbit	20060, 20035, 20048, 20047, 20081, 20240, 20000, 20042, 20072, 20062, 20212, 20760 100use 20209, 20072, 20637 20035, 20000, 20072 20041, 20038 20039, 20033, 20000, 20209, 20034, 20479, 21479, 21139, 20637 21972 101272 101272 101272 101272 101272 101272 101272 101272 101393 10165 10184 101403 101415 10365 10403 10415 10403 10415 10403 104172 101272 101272 101272 101272 101384 101344 101403 101415 10165 10185 10186 101105 10188 101101 10110 10113, 00295 100081 101486 101190, 01490
Proscan 20522 Provision 20778 Qwestar 20651 RCA 20522, 20571, 20717, 20822, 21193, 21974, 21132, 21965, 21022, 21913 Regent 21938 Rio 20823 Rowa 20823 Saba 21977 Sampo 20752, 20698 Samsung 20490, 20573, 20820, 21932, 21075, 20899, 21979 Sansu 20695 Sanyo 20695, 20670, 21967, 20873 Sharp 20630, 20752 Sharpen Image 21995, 21117 Sherwood 21043, 20770, 20633, 21077 Shinco 20717 Shinco	Voom	Firstar Fisher Fortress Fujitsu Funai Furi Furi Futuretech Ganxin Gateway GE General Gibralter Gintai Go Video GoldStar Goodmans Grunpy Haier Haiyan Hallmark Hankook Harrey Davidson Harman/Kardon Harvard Havermy Hello Kitty Himitsu Hisense Hitachi Hongmei Hongyan Hua Tun Huafa	10236 10154, 10159 10093 10180, 10853, 10179, 10809, 10683 10180, 10171, 10264, 11904, 10179, 10342 10145, 10817, 10264 10180 10817 11756, 11755 11447, 10047, 11454, 10051, 10451, 10180, 10030, 10178, 10092, 11147, 11919, 10055, 10027, 11917, 10135, 10282, 11347, 10021, 11907, 11907, 11922 10186 10017, 10030, 10019 11150, 10474 10886 10154, 10030, 10178, 11926, 10019, 10037, 11910, 10001, 10032, 10056, 11150, 10039 10360 10180, 10179 11034, 10768 10264, 10817 10178 10180, 10030, 10178, 11019, 10056, 10628 11904, 10179 10054 10180, 10039 10451 11080, 10020, 10178, 11019, 10056, 10628 11904, 10179 10054 10180, 10020, 10178, 11019, 10056, 10628 11904, 10179 10054 10180, 10020, 10079, 10079, 10079, 10079, 10079 10054 10180, 10020, 10079, 10079, 10079, 10079, 10079 10054 10180, 10030, 10178, 11015, 10165, 10093, 11245, 10092, 10027, 10381, 10036, 11150, 10056, 11094, 10151, 10165, 10019, 10186, 10033, 11045, 10092, 10027, 10381, 10036, 11150, 10056, 11904, 10151, 10165, 10019, 10186, 10033, 11047, 10264 10817, 10264 11150, 10145	Megatron MEI Meile Memorex Mermaid MGA Midland Minutz Mitsubishi Monivision Motorola MTC Mudan Multitech NAD Nanbao Nansheng National NEC Newave Nikko Nikon Norcent Noshi NTC Onking Onwa Optimus Optoma Optomica	10700 10178, 10145, 10003 10185 10264, 11910, 10817 10154, 10463, 10150, 10178, 10179, 11920, 11927, 10016, 11911, 11926, 11924 10037 10150, 10030, 10178, 11907, 10019 10047, 10017, 10051, 10039, 10135, 10032 10021 10154, 10250, 10093, 10236, 10180, 11250, 10150, 10030, 10178, 10381, 10836, 10036, 10179, 10817, 11150, 10474, 10019, 10868, 10056, 11917 10843, 10700 10030, 101817, 11150, 10474, 10019, 10868, 10056, 11917 10843, 10700 10031, 10817, 11264 10180 10156, 10178, 10866 11910, 10264 10817, 10264 10817, 10264 10817, 10264 10817, 10264 10817, 10264 10817, 10264 10817, 10264 10817, 10264 10951 10154, 10156, 10051, 10053, 10030, 10178, 10046, 11150, 10056, 10165, 10186, 10474, 10036, 10882, 10381, 10817, 11704, 10170, 10264, 10019, 10497 10093, 10178, 11150, 10092, 10161 10030, 10178, 10092 11910 10748, 10824 10018 10092 10280 10180 10154, 10250, 10166, 11924, 11913, 10650, 11927 10887 10093, 10165 10236, 10463, 11911, 11905, 10179, 11463,	Shen Ying Shencai Shencai Shencai Sheng Chia Shenyang Shogun Signature Simpson Skygiant Skyworth Sony Soundesign Sowa Spectricon Squareview SSS Starlite Studio Experie Supre-Macy Supreme SVA Sylvania Symphonic Synco Tacico Tai Yi Taishan Tandy Tashiko Tatung Technics	10039, 10165, 10474, 10688, 10787, 10036, 11917 3e 11950 10092, 10003, 10474, 10179 10145, 10264 10093, 10236, 10179, 11150, 10474 10817, 10264 10019 10016 10187, 10186 10180 10748, 10264, 10037, 10817 11100, 10000, 10036, 10650, 11300, 10111, 11925, 10080, 10834, 11904 10180, 10178, 10179, 10186 10156, 10051, 10060, 10178, 10036, 10092, 10474, 11150 10003 10171 10180, 10019 10180 ience 10843 10046 10000 10748, 10587, 10865, 10872, 10768, 10871, 10870 10054, 10030, 10171, 11931, 10381, 11944, 10020, 10096 10180, 10171, 11913, 11904 10000, 10451, 10093, 10060, 10178, 10092, 1036, 10474 10178, 10179, 11150, 10092, 10474 11150 10081, 10174, 10195, 10092, 10474 11150 10081, 10174, 10156, 10051, 10060, 11150, 10474, 10036, 10055, 11756, 10003 10250, 10051 10179 10847 10051, 10003, 10056	America Action American High Amoisonic Anam Anam National Asha Audiovox Beaumark Bell & Howell Blaupunkt Broksonic Calix Canon Carver CCE Changhong Citizen Colt Craig Curtis Mathes CyberPower Daewoo Dell Denon DirecTV Dish Network Sy Dishpro Durabrand Dynatech Echostar Electrohome Electrophonic Emerex Emerson	21972 n 20278 h 200278 h 20035 20479 20162, 20037, 20240, 20278, 20226, 21037 ll 20162, 20226 20240 20037, 20278 20240 20104 20226 20184, 20121, 20209, 20002, 20348, 20295, 21479, 20479 20035, 21174, 20167 20081 20072, 20278 20048, 20081 20072, 20278, 21278 20072 20035, 20174, 20240, 20072, 20271 20060, 20035, 20162, 20041, 20760, 21035 20240 21972 20045, 20104, 20278, 20210, 20368, 21278, 20637, 20047, 20274 20045, 20104, 20278, 20210, 20368, 21278, 20637, 20046, 20212, 20561 21972 20042 20739, 21989, 21954, 21949 System 21943, 21946, 21945, 21944 21944, 21943 20039, 20038 20000 21943, 21946, 21945, 21944 20037 20037 20037 20037 20037 20037 20037 20037 20037 20038, 20047, 21278, 20061, 20212 21962	MTC Multitech NAD National NEC Newave Nikko Nikon Noblex Northgate Olympus Onkyo Optimus Optonica Orion Panarex Panasonic Pansat Penney Pentax Philco Philips Pilot Pioneer Polk Audio Profitronic Proscan Protec Pulsar Quarter Quarter Quarter Quarter Quarter RadioShack Radix	20240, 20000 20000, 20072 20058 20256 20035, 20037, 20048, 20104, 20067, 20041, 20038, 20040, 20008, 20370 20037 20253, 20034 20240 21972 20035, 20226, 21046 20222 21662, 20162, 20037, 20048, 20104, 21048, 21262, 20593, 21162, 20058, 20432 20062 20184, 2029, 20002, 20479, 20295, 21479 21950 21062, 20035, 20162, 20077, 20226, 20616, 21162, 20252, 20367, 20227, 21035, 21262 21950 20035, 20037, 20240, 20042, 20038, 21035, 20040, 20054, 21237 20042, 20105 20035, 20081, 20000, 20226, 20739, 21381, 20110, 20618, 21181, 20563, 21081, 21949, 20062 20037 20042, 20067, 20058 20081 20240 20060, 20760, 21954, 20202, 21060, 20761 20072 20039 20060 20046 20046 20046 20047	Wards White Westingh XR-1000 Yamaha Zenith ZT Group Setup Cod ABS Alienware CyberPower Gateway Hewlett Packare Howard Compu HP iBUYPOWER InterVideo Jensen JVC Keyspan KWorld LG Linksys Macro Image Te Media Center Po Microsoft Mind Motorola MyHD Northgate Panasonic Pinnacle System Pioneer Princeton Rabbit Roku Samsung Sensory Science Sharp	20060, 20035, 20048, 20047, 20081, 20240, 20000, 20042, 20072, 20062, 20212, 20760 100use 20209, 20072, 20062, 20212, 20760 100use 20209, 20072, 20063, 20212, 20760 100use 20209, 20072, 20637 10033, 20000, 20072 10041, 20038 101479, 21139, 20637 121972 101272 101272 101272 101272 101272 101272 101272 101272 101272 101272 101393 10165 101384 101344 101403 101415 101365 101365 101365 101365 101365 101365 101363 101363 101363 101363 101363 101272 101272 101272 101272 101272 101272 101272 101272 101363 101363 101363 101363 101363 101363 101363 101363 101363 101372 10120 10120 10120 10130 101486 10110 10113, 00295 100081 101486 101100 10110 10
Proscan 20522 Provision 20778 Qwestar 20651 RCA 20522, 20571, 20717, 20822, 21193, 21974, 21132, 21965, 21022, 21913 Regent 21938 Rio 20823 Rotel 20623 Rowa 20823 Saba 21977 Sampo 20752, 20698 Samsung 20490, 20573, 20820, 21932, 21075, 20899, 21979 Sansui 20695 Sanyo 20695, 20670, 21967, 20873 Sharp 20630, 20752 Sharpe Image 21995, 21117 Sherwood 21043, 20770, 20633, 21077 Shinco 20717 Shinco<	Voom	Firstar Fisher Fortress Fujitsu Funai Furi Furi Fortress Fujitsu Funai Furi Ganxin Gateway GE General Gibralter Gintai Go Video GoldStar Goodmans Grunpy Haier Haiyan Hallmark Hankook Harley Davidson Harman/Kardon Harward Havermy Hello Kitty Himitsu Hisense Hitachi Hongmei Hongyan Hua Tun Huafa Huafa Huafa Huanghe	10236 10154, 10159 10093 10180, 10853, 10179, 10809, 10683 10180, 10171, 10264, 11904, 10179, 10342 10145, 10817, 10264 10180 10817 11756, 11755 11447, 10047, 11454, 10051, 10451, 10180, 10030, 10178, 10092, 11147, 11919, 10055, 10027, 11917, 10135, 10282, 11347, 10021, 11907, 11922 10186 10017, 10030, 10019 11150, 10474 10886 10154, 10030, 10178, 11926, 10019, 10037, 11910, 10001, 10032, 10056, 11150, 10039 10360 10154, 10030, 10178, 11926, 10019, 10037, 11910, 10001, 10032, 10056, 11150, 10039 10360 10180, 10179 11034, 10768 10264, 10817 10178 10180, 10030, 10178, 11091, 10056, 10628 11904, 10179 10054 110180 10093 10451 10180, 10628 10156, 10748, 10145 11256, 10156, 10030, 10178, 11145, 10145, 10038, 11245, 10056, 11094, 10179, 10186, 10032, 10039, 10157, 10016, 10179, 10186, 10032, 10039, 10157, 10016, 10179, 10186, 10032, 10039, 10157, 10016, 10179, 10187, 10264 11150 10031, 11910, 10817, 10264 10817, 10264 11150	Megatron MEI Meile Memorex Mermaid MGA Midland Minutz Mitsubishi Monivision Motorola MTC Mudan Multitech NAD Nanbao Nansheng National NEC Newave Nikko Nikon Norcent Noshi NTC Onking Onwa Optomica Orion Panasonic	10700 10178, 10145, 10003 10185 10185 10264, 11910, 10817 10154, 10463, 10150, 10178, 10179, 11920, 11927, 10016, 11911, 11926, 11924 10037 10150, 10030, 10178, 11907, 10019 10047, 10017, 10051, 10039, 10135, 10032 10021 10154, 10250, 10093, 10236, 10180, 11250, 10150, 10030, 10178, 10381, 10386, 10036, 10179, 10817, 11150, 10474, 10019, 10868, 10056, 11917 10843, 10700 10093, 10055 10060, 10030, 10185, 10019, 10056 10051, 10817, 10264 10180 10156, 10178, 10866 11910, 10264 10817, 10264 10817, 10264 10015 10154, 10156, 10051, 10053, 10030, 10178, 10046, 11150, 10056, 10165, 10186, 10474, 10036, 10882, 10381, 10817, 11704, 10170, 10264, 10019, 10479 10093, 10178, 11150, 10092, 10161 10030, 10178, 10150, 10092, 10161 10030, 10178, 10150, 10092, 10161 10018 10092 10280 10180 10154, 10250, 10166, 11924, 11913, 10650, 11927 10887 10093, 10165 10236, 10463, 11911, 11905, 10179, 11463, 11927 10887 10093, 10165 10236, 10463, 11911, 11905, 10179, 11463, 11927 10887 10034, 10250, 10161, 1161, 11410, 11927, 11947, 10037, 10055, 10650, 11924, 11946, 11919, 11941	Shen Ying Shencai Shencai Shencai Shencai Shencai Sheng Chia Shenyang Shogun Signature Simpson Skygiant Skyworth Sony Soundesign Sowa Spectricon Squareview SSS Starlite Studio Experie Studio Experie Supre-Macy Supreme SVA Sylvania Symphonic Synco Tacico Tai Yi Taishan Tandy Tashiko Tatung Technics Technol Ace Techview	10039, 10165, 10474, 10688, 10787, 10036, 11917 3e 11950 10092, 10003, 10474, 10179 10145, 10264 10093, 10236, 10179, 11150, 10474 10817, 10264 10019 10016 10187, 10186 10180 10748, 10264, 10037, 10817 11100, 10000, 10036, 10650, 11300, 10111, 11925, 10080, 10834, 11904 10180, 10178, 10179, 10186 10156, 10051, 10060, 10178, 10036, 10092, 10474, 11150 10003 10171 10180, 10019 10180 ience 10843 10046 10000 10748, 10587, 10865, 10872, 10768, 10871, 10870 10054, 10030, 10171, 11931, 10381, 11944, 10020, 10096 10180, 10171, 11913, 11904 10000, 10451, 10093, 10060, 10178, 10092, 10036, 10474 10178, 10179, 11150, 10092, 10474 10178, 10179, 11150, 10092, 10474 10178, 10199 10093 11150, 10650, 10092 10054, 10154, 10156, 10051, 10060, 11150, 10474, 10036, 10055, 11756, 10003 10250, 10051	America Action American High Amoisonic Anam Anam National Asha Audiovox Beaumark Bell & Howell Blaupunkt Broksonic Calix Canon Carver CCE Changhong Citizen Colt Craig Curtis Mathes Cybernex CyberPower Daewoo Dell Denon DirecTV Dish Network Sy Dishpro Durabrand Dynatech Echostar Electrohome Electrophonic Emerex Emerson	21972 n 20278 h 20278 h 20278 h 20035 20479 20162, 20037, 20240, 20278, 20226, 21037 ll 20162, 20226 20240 20240 20104 20104 20226 20184, 20121, 20209, 20002, 20348, 20295, 21479, 20479 20037 20035, 21174, 20167 20081 20072, 20278 20048, 20081 20072, 20278 20048, 20081 20037, 20078, 21278 20072 20037, 20078, 21278 20072 20037, 20047, 20240, 20072, 20271 20060, 20035, 20162, 20041, 20760, 21035 20240 21972 20045, 20104, 20278, 20210, 20368, 21278, 20637, 20046, 20212, 20561 21972 20049 20739, 21989, 21954, 21949 System 21943, 21946, 21945, 21944 21944, 21943 20039, 20038 20000 21943, 21946, 21945, 21944 20037 20037 20037 20037 20037 20037 20037 20037, 20043, 20209, 20002, 20278, 20295, 20266, 20479, 21278, 20068, 20208, 20479, 21278, 20061, 20212	MTC Multitech NAD National NEC Newave Nikko Nikon Noblex Northgate Olympus Onkyo Optimus Optonica Orion Pansat Penney Pentax Philco Philips Pilot Pioneer Polk Audio Profitronic Proscan Protec Pulsar Qisheng Quarter Quartz Quasar RadioShack	20240, 20000 20000, 20072 20058 20026 20035, 20037, 20048, 20104, 20067, 20041, 20038, 20040, 20008, 20370 20037 20037 20253, 20034 20240 21972 20035, 20226, 21046 20222 21062, 20162, 20037, 20048, 20104, 21048, 21262, 20593, 21162, 20058, 20452 20062 20184, 20209, 20002, 20479, 20295, 21479 21950 21062, 20035, 20162, 20077, 20226, 20616, 21162, 20225, 20367, 20227, 21035, 21262 21950 2035, 20037, 20240, 20042, 20038, 21035, 20040, 20054, 21181, 20563, 21081, 21949, 20062 2035, 20081, 20000, 20226, 20799, 21381, 20110, 20618, 21181, 20563, 21081, 21949, 20062 20037 20042, 20067, 20058 20081 20240 20060 20046 20046 20046 20046 20046 20055, 20162, 21035, 20077, 21162 20000, 21037	Wards White Westingh XR-1000 Yamaha Zenith ZT Group Setup Cod ABS Alienware CyberPower Gateway Hewlett Packare Howard Compu HP iBUYPOWER InterVideo Jensen JVC Keyspan KWorld LG Linksys Macro Image Te Media Center Pt Microsoft Mind Motorola MyHD Northgate Panasonic Pinnacle System Pioneer Princeton Rabbit Roku Samsung Sensory Science	20060, 20035, 20048, 20047, 20081, 20240, 20000, 20042, 20072, 20062, 20212, 20760 100use 20209, 20072, 20637 20035, 20000, 20072 20041, 20038 20039, 20033, 20000, 20209, 20034, 20479, 21479, 21139, 20637 21972 101272 101272 101272 101272 101272 101272 101272 101272 101272 101384 101403 101415 101365 101403 101415 101365 101403 101415 101365 101403 101415 101365 101403 101415 101365 101403 101415 101365 101403 101415 101365 101405 101405 101505 101272 101272 101305 101405 101505 101605 10172 101363 101383 101272 101272 10120 10100 10113, 00295 100081 101486 10190, 01490 101100 101120 101100 101140 101150 101190, 01490 101101
Proscan 20522 Provision 2078 Qwestar 20651 RcA 20522, 20571, 20717, 20822, 21193, 21974, 21132, 21965, 21022, 21913 Regent 21938 Rio 20869 Rotel 20623 Rowa 20823 Sampo 20752, 20698 Samsung 20490, 20573, 20820, 21932, 21075, 20899, 21979 Sansui 20695 Saryo 20695, 20670, 21967, 20873 Sharp 20630, 20752 Sharper Image 21995, 21117 Sherwood 21043, 20770, 20633, 21077 Shinco 20717 Shinco 20717 Shinsonic 20533, 20839, 21931 Sigma Designs 20674 Sonic Blue 20869, 21970, 21099 Sony 20533, 21981, 20772, 21934 Sungale 21074 Supsale 21074 Supsale 21074 Supsale 21074 Sylvania 20821, 20675 Symphonic 20675	Voom	Firstar Fisher Fortress Fujitsu Funai Furi Furi Futuretech Ganxin Gateway GE General Gibralter Gibralter Gintai Go Video GoldStar Goodmans Grunpy Haier Haiyan Hallmark Hankook Harrley Davidson Harrnan/Kardon Harvard Havermy Hello Kitty Himitsu Hisense Hitachi Hongyan Hua Tun Huafa Huanghe Huanghe Huanghe Huanghe Huanghe Huanghe Huanghe	10236 10154,10159 10093 10180,10853,10179,10809,10683 10180,10171,10264,11904,10179,10342 10145,10817,10264 10180 10817 11756,11755 11447,10047,11454,10051,10451,10180,10030,10178,10092,11147,11919,10055,10027,11917,10135,10282,11347,10021,11907,11907,11902 10186 10017,10030,10019 11150,10474 10886 10154,10030,10178,11926,10019,10037,11910,10001,10032,10056,11150,10039 10360 10180,10179 11034,10768 101264,10817 10178 10180,10030,10178,11019,10056,10628 11904,10179 11034,10768 10180,10030,10178,10119,10056,10628 11904,10179 10180,10030,10178,10119,10056,10628 11904,10179 10054 10180 10093 10451 11150,10030,10178,10119,10156,10019,10056,10628 10156,10748,10145 11256,10748,10145 11256,10748,10145 11256,10748,10145 11256,10748,10145 11256,10748,10145 11256,10156,10030,10178,110165,10019,10186,10032,10039,10177,10016,10179,10474	Megatron MEI Meile Memorex Mermaid MGA Midland Minutz Mitsubishi Monivision Motorola MTC Mudan Multitech NAD Nanbao Nansheng National NEC Newave Nikko Nikon Norcent Noshi Norcent Noshi Onking Onwa Optomica Optoma Optomica Orion	10700 10178, 10145, 10003 10185 10264, 11910, 10817 10154, 10463, 10150, 10178, 10179, 11920, 11927, 10016, 11911, 11926, 11924 10037 10150, 10030, 10178, 11907, 10019 10047, 10017, 10051, 10039, 10135, 10032 10021 10154, 10250, 10093, 10236, 10180, 11250, 10150, 10030, 10178, 10381, 10836, 10036, 10179, 10817, 11150, 10474, 10019, 10868, 10056, 11917 10843, 10700 10030, 101817, 11150, 10474, 10019, 10868, 10056, 11917 10843, 10700 10031, 10187, 11150, 10474, 10019, 10868, 10056, 11917 10843, 10700 10031, 10187, 10264 10180 10156, 10178, 10866 11910, 10264 10817, 10264 10817, 10264 10817, 10264 10817, 10264 109051 10154, 10156, 10051, 10053, 10030, 10178, 10046, 11150, 10056, 10165, 10186, 10474, 10036, 10882, 10381, 10817, 11704, 10170, 10264, 10019, 10497 10093, 10178, 11150, 10092, 10161 10030, 10178, 10092 11910 10748, 10824 10018 10092 10280 10180 10154, 10250, 10166, 11924, 11913, 10650, 11927 10887 10093, 10165 10236, 10463, 11911, 11905, 10179, 11463, 11929 10054, 10250, 10051, 10161, 11410, 11927, 10054, 10250, 10051, 10650, 11924, 11929 10054, 10250, 10051, 10161, 11410, 11927, 11947, 10037, 10055, 10650, 11924, 11946,	Shen Ying Shencai Shencai Shencai Sheng Chia Shenyang Shogun Signature Simpson Skygiant Skyworth Sony Soundesign Sowa Spectricon Squareview SSS Starlite Studio Experie Supre-Macy Supreme SVA Sylvania Symphonic Synco Tacico Tai Yi Taishan Tandy Tashiko Tatung Technics	10039, 10165, 10474, 10688, 10787, 10036, 11917 3e 11950 10092, 10003, 10474, 10179 10145, 10264 10093, 10236, 10179, 11150, 10474 10817, 10264 10019 10016 10187, 10186 10180 10748, 10264, 10037, 10817 11100, 10000, 10036, 10650, 11300, 10111, 11925, 10080, 10834, 11904 10180, 10178, 10179, 10186 10156, 10051, 10060, 10178, 10036, 10092, 10474, 11150 10003 10171 10180, 10019 10180 ience 10843 10046 10000 10748, 10587, 10865, 10872, 10768, 10871, 10870 10054, 10030, 10171, 11931, 10381, 11944, 10020, 10096 10180, 10171, 11913, 11904 10000, 10451, 10093, 10060, 10178, 10092, 1036, 10474 10178, 10179, 11150, 10092, 10474 11150 10817, 10391 10093 11150, 10650, 10092 10054, 10054, 10055, 11756, 10003 10250, 10051 10179 10847 10051, 10003, 10078, 10474, 10036, 10280, 10092, 10264, 10653 10051, 10003, 10178, 10474, 10036, 10280, 10099, 10180, 10178, 10178, 10179, 10361, 10260, 10091, 10056, 10051, 10003, 10056, 10051, 10093, 10178, 10474, 10036, 10280, 10099, 10264, 10653, 10056, 10019, 10056, 10051, 10093, 10178, 10474, 10036, 10280, 10099, 10264, 10653, 10066, 10019, 10056, 10051, 101093, 10178, 10474, 10036, 10280, 10099, 10264, 10653, 10056, 10019, 100156, 10019, 100156, 10019, 100156, 10019, 100156, 10019, 100156, 1	America Action American High Amoisonic Anam Anam National Asha Audiovox Beaumark Bell & Howell Blaupunkt Broksonic Calix Canon Carver CCE Changhong Citizen Colt Craig Curtis Mathes Cybernex CyberPower Daewoo Dell Denon DirecTV Dish Network Sy Dishpro Durabrand Dynatech Echostar Electrohome Electrophonic Emerex Emerson Euro 1 Expressvu Fisher Fuji	21972 n 20278 h 200278 h 20035 20479 20162, 20037, 20240, 20278, 20226, 21037 ll 20162, 20226 20240 20037, 20278 20240 20104 20226 20184, 20121, 20209, 20002, 20348, 20295, 21479, 20479 20035, 21174, 20167 20081 20072, 20278 20048, 20081 20072, 20278 20048, 20081 20073, 20278, 21278 20072 20035, 21174, 20167 20081 20072, 20278 20048, 20081 20072, 20278 20048, 20081 20072, 20278 20048, 20081 20037, 20278, 21278 20072 20035, 20104, 20270, 20271 2060, 20035, 20162, 20041, 20760, 21035 20240 21972 20045, 20104, 20278, 20210, 20368, 21278, 20637, 20046, 20212, 20561 21972 20042 20739, 21989, 21954, 21949 System 21943, 21946, 21945, 21944 21944, 21943 20039, 20038 20000 21943, 21946, 21945, 21944 20037 20047 20104 20104 20104 20104 20104 20104 20104 20104 20104 20104 20	MTC Multitech NAD National NEC Newave Nikko Nikon Noblex Northgate Olympus Onkyo Optimus Optonica Orion Panarex Panasonic Pansat Penney Pentax Philco Philips Pilot Pioneer Polk Audio Profitronic Proscan Protec Pulsar Qisheng Quarter Quartz Quasar RadioShack Radix Randex	20240, 20000 20000, 20072 20058 20256 20035, 20037, 20048, 20104, 20067, 20041, 20038, 20040, 20008, 20370 20037 20037 20253, 20034 20240 21972 20035, 20226, 21046 20222 21662, 20162, 20037, 20048, 20104, 21048, 211262, 20593, 21162, 20058, 20432 20062 20184, 20209, 20002, 20479, 20295, 21479 21950 21062, 20035, 20162, 20077, 20226, 20616, 21162, 20225, 20367, 20227, 21035, 21262 21950 20035, 20037, 20240, 20042, 20038, 21035, 20040, 20054, 21237 20042, 20105 20035, 20081, 20000, 20226, 20739, 21381, 20110, 20618, 21181, 20563, 21081, 21949, 20062 20037 20042, 20067, 20058 20081 20240 20060, 20760, 21954, 20202, 21060, 20761 20072 20039 20060 20046 20046 20046 20047, 20067, 20158, 20077, 21162 200007 20037 20037 20037 20037 20037 20037 20060, 21939, 20106, 20761, 21035, 20058, 20060, 20780, 21989, 20106, 20761, 21035, 20058, 20067, 21060, 21989, 20106, 20761, 21035, 20058, 20067, 21989, 20106, 20761, 21035, 20058, 20067, 21060, 21989, 20106, 20761, 21035, 20058, 20066, 21989, 20106, 20761, 21035, 20058, 20066, 21989, 20106, 20761, 21035, 20058, 20068, 21989, 20106, 20761, 21035, 20058, 20068, 21989, 20106, 20761, 21035, 20058, 20060, 21989, 20106, 20761, 21035, 20058, 20068, 21081, 21989, 20106, 20761, 21035, 20058, 20068, 21081, 21082, 20067, 21060, 21989, 20106, 20761, 21035, 20058, 20068, 20060, 21989, 20106, 20761, 21035, 20058, 20068, 20060, 21989, 20106, 20761, 21035, 20058, 20068, 20060, 21089, 20106, 20761, 21035, 20058, 20068, 20060, 21089, 20106, 20761, 21035, 20058, 20068, 20060, 20060, 21089, 20106, 20761, 21035, 20058, 20068, 20060	Wards White Westingh XR-1000 Yamaha Zenith ZT Group Setup Cod ABS Alienware CyberPower Gateway Hewlett Packare Howard Compu HP iBUYPOWER InterVideo Jensen JVC Keyspan KWorld LG Linksys Macro Image Te Media Center Pe Microsoft Mind Motorola MyHD Northgate Panasonic Pinnacle System Pioneer Princeton Rabbit Roku Samsung Sensory Science Sharp SMC Sony Streamzap	20060, 20035, 20048, 20047, 20081, 20240, 20000, 20042, 20072, 20062, 20212, 20760 100use 20209, 20072, 20637 20035, 20000, 20072 20041, 20038 20039, 20033, 20000, 20209, 20034, 20479, 21479, 21139, 20637 21972 1les for Video Accessories 01272 01272 01272 01272 01272 01272 01272 01272 01272 01272 01272 01393 01165 01384 01344 01403 01415 01365 echnology 01383 CO1272 01272 01272 01272 01363 01383 01383 01383 01272 01272 01272 01272 01272 01272 01272 01363 01383 01383 01395 01010 00113, 00295 00081 01466 01100 01456 01010 01456 01010 01456 01010 01456 01010 01456 01010 01456 01272, 01324, 01364 01309
Proscan 20522 Provision 20778 Qwestar 20651 RCA 20522, 20571, 20717, 20822, 21193, 21974, 21132, 21965, 21022, 21913 Regent 21938 Rio 20829 Rotel 20623 Rowa 20823 Saba 21977 Sampo 20752, 20698 Samsung 20490, 20573, 20820, 21932, 21075, 20899, 21979 Sansui 20695 Sanyo 20695, 20670, 21967, 20873 Sharp 20630, 20752 Sharpe Image 21995, 21117 Sherwood 21043, 20770, 20633, 21077 Shinco 20717 Shinco<	Voom	Firstar Fisher Fortress Fortress Fujitsu Funai Furi Furi Furetech Ganxin Gateway GE General Gibralter Gintai Go Video GoldStar Goodmans Grunpy Haier Haiyan Hallmark Hankook Harley Davidson Harrand/Kardon Harrvard Havermy Hello Kitty Himitsu Hisense Hitachi Hongmei Hongyan Huafa Huanghe Huanghan Huanyu Huafa	10236 10154, 10159 10093 10180, 10853, 10179, 10809, 10683 10180, 10171, 10264, 11904, 10179, 10342 10145, 10817, 10264 10180 10817 11756, 11755 11447, 10047, 11454, 10051, 10451, 10180, 10030, 10178, 10092, 11147, 11919, 10055, 10027, 11917, 10135, 10282, 11347, 10021, 11907, 11922 10186 10017, 10030, 10019 11150, 10474 10886 10154, 10030, 10178, 11926, 10019, 10037, 11910, 10001, 10032, 10056, 11150, 10039 10360 10180, 10179 11034, 10768 10264, 10817 10178 10180, 10030, 10178, 11019, 10056, 10628 11904, 10179 10054 10180, 10030, 10178, 11019, 10056, 10628 11904, 10179 10054 10180, 10030, 10178, 11019, 10056, 10628 11904, 10179 10054 10180, 10030, 10178, 11019, 10056, 10628 11904, 10179 10054 10180, 10628 10156, 10748, 10145 11256, 10156, 10030, 10178, 11145, 10145, 10180, 10033, 11245, 10092, 10027, 10381, 10036, 11150, 10056, 11094, 10151, 10165, 10019, 10186, 10032, 10039, 10157, 10016, 10179, 10474 10093, 11910, 10817, 10264 11150 10145 10817 10264, 10817 11910, 10817, 10264 10264	Megatron MEI Meile Memorex Mermaid MGA Midand Minutz Mitsubishi Monivision Motorola MTC Mudan Multitech NAD Nanbao Nansheng National NEC Newave Nikko Nikon Norcent Noshi NTC Onking Onwa Optimus Optoma Optonica Orion Panasonic	10700 10178, 10145, 10003 10185 10185 10264, 11910, 10817 10154, 10463, 10150, 10178, 10179, 11920, 11927, 10016, 11911, 11926, 11924 10037 10150, 10030, 10178, 11907, 10019 10047, 10017, 10051, 10039, 10135, 10032 10021 10154, 10250, 10093, 10236, 10180, 11250, 10150, 10030, 10178, 10381, 10386, 10036, 10179, 10817, 11150, 10474, 10019, 10868, 10056, 11917 10843, 10700 10093, 10055 10060, 10030, 10185, 10019, 10056 10051, 10817, 10264 10180 10156, 10178, 10866 11910, 10264 10817, 10264 10817, 10264 10817, 10264 10051 10154, 10156, 10051, 10053, 10030, 10178, 10046, 11150, 10056, 10165, 10186, 10474, 10036, 10882, 10381, 10817, 11704, 10170, 10264, 10019, 10497 10093, 10178, 11150, 10092, 10161 10030, 10178, 10092 11910 10748, 10824 10018 10092 10280 10180 10154, 10250, 10166, 11924, 11913, 10650, 11927 10887 10093, 10165 10236, 10463, 11911, 11905, 10179, 11463, 11929 10251, 10706, 10817, 10264, 11910 10051, 10706, 10817, 10264, 11910 10051, 10706, 10817, 10264, 11910 10074, 1036, 10361, 10061, 10072, 10039, 10178, 11910 10051, 10706, 10817, 10264, 11910 10074, 10156, 10051, 10060, 10030, 10178, 11915, 11347, 11936, 11055, 11347, 11926, 11910	Shen Ying Shencai Signature Simpson Skygiant Skyworth Sony Soundesign Sowa Spectricon Squareview SSS Starlite Studio Experie Supre-Macy Supreme SVA Sylvania Symphonic Synco Tacico Tai Yi Taishan Tandy Tashiko Tatung Technics Technol Ace Techview Techwood Teco Techview Techwood Teco Teknika	10039, 10165, 10474, 10688, 10787, 10036, 11917 3e 11950 10092, 10003, 10474, 10179 10145, 10264 10093, 10236, 10179, 11150, 10474 10817, 10264 10019 10016 10187, 10186 10180 10748, 10264, 10037, 10817 11100, 10000, 10036, 10650, 11300, 10111, 11925, 10080, 10834, 11904 10180, 10178, 10179, 10186 10156, 10051, 10060, 10178, 10036, 10092, 10474, 11150 10003 10171 10180, 10179 10180 10004 1019000 10748, 10587, 10865, 10872, 10768, 10871, 10870 10054, 10030, 10171, 11931, 10381, 11944, 10020, 10096 10180, 10171, 11913, 11904 10000, 10451, 10093, 10060, 10178, 10092, 1036, 10474 10178, 10179, 11150, 10092, 10474 11150 10817, 10391 10093 11150, 10650, 10092 10054, 10154, 10156, 10051, 10060, 11150, 10474, 10036, 10055, 11756, 10003 10250, 10051, 10093 10151, 10093, 10178, 10474, 10036, 10280, 10091, 10095, 10079 10847 10051, 10093, 10178, 10474, 10036, 10280, 10092, 10264, 10653	America Action American High Amoisonic Anam Anam National Asha Audiovox Beaumark Bell & Howell Blaupunkt Broksonic Calix Canon Carver CCE Changhong Citizen Colt Craig Curtis Mathes Cybernex CyberPower Daewoo Dell Denon DirecTV Dish Network Sy Dishpro Durabrand Dynatech Echostar Electrohome Electrophonic Emerex Emerson	21972 n 20278 h 20278 h 20035 20479 20162, 20037, 20240, 20278, 20226, 21037 ll 20162, 20226 20240 20037, 20278 20240 20104 20126 20184, 20121, 20209, 20002, 20348, 20295, 21479, 20479 20037 20035, 21174, 20167 20081 20072, 20278 20048, 20081 20072, 20278 20037, 20278, 21278 20072 20037, 20047, 20240, 20072, 20271 20060, 20035, 20162, 20041, 20760, 21035 20240 21972 20045, 20104, 20278, 20210, 20368, 21278, 20637, 20048, 20212, 20561 21972 20045, 20104, 20278, 20210, 20368, 21278, 20637, 20046, 20212, 20561 21972 20049 20739, 21989, 21954, 21949 System 21943, 21946, 21945, 21944 21944, 21943 20039, 20038 20000 21943, 21946, 21945, 21944 20037 20037 20037 20037 20037 20037 20037 20037 20037 20037 20037 20037 20038, 20037, 20184, 20240, 20045, 20000, 20121, 20043, 20209, 20002, 20278, 20295, 20036, 20367, 21598, 20061, 20212 21962 21944 20047, 20104, 20066, 20054	MTC Multitech NAD National NEC Newave Nikko Nikon Noblex Northgate Olympus Onkyo Optimus Optonica Orion Panarex Panasonic Pansat Penney Pentax Philco Philips Pilot Pioneer Polk Audio Profitronic Proscan Protec Pulsar Quartz Quartz Quartz Quartz Quartz Quasar RadioShack Radix Randex RCA	20240, 20000 20000, 20072 20058 20026 20035, 20037, 20048, 20104, 20067, 20041, 20038, 20040, 20008, 20370 20037 20037 20253, 20034 20240 21972 20035, 20226, 21046 20222 21062, 20162, 20037, 20048, 20104, 21048, 21262, 20593, 21162, 20058, 20452 20062 20184, 20209, 20002, 20479, 20295, 21479 21950 21062, 20035, 20162, 20077, 20226, 20616, 21162, 20225, 20367, 20227, 21035, 21262 21950 20035, 20037, 20240, 20042, 20038, 21035, 20040, 20054, 21237 20042, 20105 20035, 20000, 20226, 20479 20035, 20081, 20000, 20226, 20739, 21381, 20110, 20618, 21181, 20563, 21081, 21949, 20062 20037 20042, 20067, 20058 20081 20240 20060, 20760, 21954, 20202, 21060, 20761 20072 20039 20060 20046 20046 20046 20046 20055, 20162, 21035, 20077, 21162 20000, 21037 20042 20037 20060, 20035, 20240, 20000, 20242, 20807, 21060, 21989, 20106, 20761, 21035, 20058, 21964, 20105, 20226, 20760, 20880, 21954, 20077, 20202, 2045, 20077, 21162 200037 20060, 20035, 20240, 20000, 20042, 20807, 21060, 21989, 20106, 20761, 21035, 20058, 21964, 20105, 20226, 20760, 20880, 21954, 20077, 20202, 20453	Wards White Westingh XR-1000 Yamaha Zenith ZT Group Setup Cod ABS Alienware CyberPower Gateway Hewlett Packare Howard Compu HP IBUYPOWER InterVideo Jensen JVC Keyspan KWorld LG Linksys Macro Image Te Media Center Po Microsoft Mind Motorola MyHD Northgate Panasonic Pinnacle System Pioneer Princeton Rabbit Roku Samsung Sensory Science Sharp SMC Sony Streamzap Systemax	20060, 20035, 20048, 20047, 20081, 20240, 20000, 20042, 20072, 20062, 20212, 20760 100use 20209, 20072, 20637 20035, 20000, 20072 20041, 20038 20039, 20033, 20000, 20209, 20034, 20479, 21479, 21139, 20637 21972 1les for Video Accessories 01272 01272 01272 01272 01272 01272 01272 01272 01393 01165 01384 011344 01403 01415 01365 10365 10365 10360 10372 10272 10272 10272 10272 10272 10272 10393 10165 10384 10165 10384 10165 10384 10172 10165 10184 10165 10186 10165 10186 10190 10466 10100 10110 10110 101466 10110 101466 10110 101466 10110 101456 101272, 01324, 01364 101309 101272
Proscan 20522 Provision 20778 Qwestar 20651 RCA 20522, 20571, 20717, 20822, 21193, 21974, 21132, 21965, 21022, 21913 Regent 21938 Rio 20869 Rotel 20623 Rowa 20823 Saba 21977 Sampo 20752, 20698 Samsung 20490, 20573, 20820, 21932, 21075, 20899, 21979 Sansui 20695 Sanyo 20695, 20670, 21967, 20873 Sharp 20630, 20752 Sharper Image 21995, 21117 Sherwood 21043, 20700, 20633, 21077 Shinco 20717 Shinco	Voom	Firstar Fisher Fortress Fortress Fujitsu Funai Furi Furi Ganxin Gateway GE General Gibralter Gintai Go Video GoldStar Goodmans Grunpy Haier Haiyan Hallmark Hankook Harley Davidson Harman/Kardon Harward Havermy Hello Kitty Himitsu Hisense Hitachi Hongmei Hongyan Hua Tun Hua Tun Huafa Huanghe Huanghe Huanghe Huanghe Huangian Huanyu Huaqiang Huari	10236 10154,10159 10093 10180,10853,10179,10809,10683 10180,10171,10264,11904,10179,10342 10145,10817,10264 10180 10817 11756,11755 11447,10047,11454,10051,10451,10180,10030,10178,10092,11147,11919,10055,10027,11917,10135,10282,11347,10021,11907,11907,11902 10186 10017,10030,10019 11150,10474 10886 10154,10030,10178,11926,10019,10037,11910,10001,10032,10056,11150,10039 10360 10180,10179 11034,10768 101264,10817 10178 10180,10030,10178,11019,10056,10628 11904,10179 11034,10768 10180,10030,10178,10119,10056,10628 11904,10179 10180,10030,10178,10119,10056,10628 11904,10179 10054 10180 10093 10451 11150,10030,10178,10119,10156,10019,10056,10628 10156,10748,10145 11256,10748,10145 11256,10748,10145 11256,10748,10145 11256,10748,10145 11256,10748,10145 11256,10156,10030,10178,110165,10019,10186,10032,10039,10177,10016,10179,10474	Megatron MEI Meile Memorex Mermaid MGA Midand Minutz Mitsubishi Monivision Motorola MTC Mudan Multitech NAD Nanbao Nansheng National NEC Newave Nikko Nikon Norcent Noshi NTC Onking Onwa Optimus Optoma Optonica Orion Panasonic	10700 10178, 10145, 10003 10185 10264, 11910, 10817 10154, 10463, 10150, 10178, 10179, 11920, 11927, 10016, 11911, 11926, 11924 10037 10150, 10030, 10178, 11907, 10019 10047, 10017, 10051, 10039, 10135, 10032 10021 10154, 10250, 10093, 10236, 10180, 11250, 10150, 10030, 10178, 10381, 10836, 10036, 10179, 10817, 11150, 10474, 10019, 10868, 10056, 11917 10843, 10700 10030, 101817, 11150, 10474, 10019, 10868, 10056, 11917 10843, 10700 10031, 10817, 10264 10180 10156, 10178, 10866 11910, 10264 10817, 10264 10817, 10264 10817, 10264 10817, 10264 10817, 10264 10817, 10264 10817, 10264 10817, 10264 10817, 10264 10951 10154, 10156, 10051, 10053, 10030, 10178, 10046, 11150, 10056, 10165, 10186, 10474, 10036, 10882, 10381, 10817, 11704, 10170, 10264, 10019, 10497 10093, 10178, 11150, 10092, 10161 10030, 10178, 10092 11910 10748, 10824 10018 10092 10280 10180 10154, 10250, 10166, 11924, 11913, 10650, 11927 10887 10933, 10165 10236, 10463, 11911, 11905, 10179, 11463, 11929 10054, 10250, 10051, 10161, 11410, 11927, 11947, 10037, 10055, 10650, 11924, 11946, 11919, 11941	Shen Ying Shencai Shencai Shencai Shencai Shencai Shencai Shencai Shencai Shencai Signature Signature Simpson Skygiant Skyworth Sony Soundesign Sowa Spectricon Squareview SSS Starlite Studio Experie Supre-Macy Supre-Macy Supreme SVA Sylvania Symphonic Synco Tacico Tai Yi Taishan Tandy Tashiko Tatung Technics Technol Ace Techview Techwood Teco Telefunken Telefunken Tera	10039, 10165, 10474, 10688, 10787, 10036, 11917 2e 11950 10092, 10003, 10474, 10179 10145, 10264 10093, 10236, 10179, 11150, 10474 10817, 10264 10019 10016 10187, 10186 10180 10748, 10264, 10037, 10817 11100, 10000, 10036, 10650, 11300, 10111, 11925, 10080, 10834, 11904 10180, 10178, 10179, 10186 10156, 10051, 10060, 10178, 10036, 10092, 10474, 11150 10003 10171 10180, 10019 10180 ience 10843 10046 10000 10748, 10587, 10865, 10872, 10768, 10871, 10870 10054, 10030, 10171, 11931, 10381, 11944, 10020, 10096 10180, 10171, 11913, 11904 10000, 10451, 10093, 10060, 10178, 10092, 1036, 10474 10178, 10179, 11150, 10092, 10474 11150 10817, 10391 10093 11150, 10650, 10092 10054, 10154, 10156, 10051, 10060, 11150, 10474, 10036, 10055, 11756, 10003 10250, 10051 10179 10847 10051, 10003, 10078, 1078, 1079, 10036, 10092, 10079, 10079, 10036, 10055, 11756, 10003 10051, 10003, 10178, 10474, 10036, 10280, 10092, 10264, 10653 10051, 10093, 10178, 10474, 10036, 10280, 10092, 10064, 10180, 10179, 10065, 10060, 1019, 10056, 10061, 10092, 10079, 10079, 10079, 10079, 10079, 10079, 10079, 10079, 10079, 10079, 10079, 10079, 10079, 10079, 10079, 10079, 10180, 10179, 10060, 10199, 10056, 10061, 10092, 10039, 10179	America Action American High Amoisonic Anam Anam National Asha Audiovox Beaumark Bell & Howell Blaupunkt Broksonic Calix Canon Carver CCE Changhong Citizen Colt Craig Curtis Mathes CyberPower Daewoo Dell Denon DirecTV Dish Network Sy Dishpro Durabrand Dynatech Ecthostar Electrohome Electrophonic Emerex Emerson Euro 1 Expressvu Fisher Fuji Fujitsu Funai Garrard	21972 n 20278 h 200278 h 20035 20479 20162, 20037, 20240, 20278, 20226, 21037 ll 20162, 20226 20240 20037, 20278 20240 20104 20104 20126 20184, 20121, 20209, 20002, 20348, 20295, 21479, 20479 20035 20037 20035, 21174, 20167 20081 20072, 20278 20048, 20081 20072, 20278 20048, 20081 20037, 20278, 21278 20072 20037, 20047, 20240, 20072, 20271 20060, 20035, 20162, 20041, 20760, 21035 20240 21972 20045, 20104, 20278, 20210, 20368, 21278, 20637, 20046, 20212, 20561 21972 20045, 20104, 20278, 20210, 20368, 21278, 20637, 20046, 20212, 20561 21972 20049 20739, 21989, 21954, 21949 System 21943, 21946, 21945, 21944 21944, 21943 20039, 20038 20000 21943, 21946, 21945, 21944 20037 20037 20037 20037 20037 20037 20037 20037 20038, 20037, 20184, 20240, 20045, 20000, 20121, 20043, 20209, 20002, 20278, 20295, 20036, 20367, 21593, 20561, 21479, 20068, 20208, 20479, 21278, 20061, 20212 21962 21944 20047, 20104, 20066, 20054 20003, 20593, 21593 20000	MTC Multitech NAD National NEC Newave Nikko Nikon Noblex Northgate Olympus Onkyo Optimus Optonica Orion Panarex Panasonic Pansat Penney Pentax Philco Philips Pilot Pioneer Polk Audio Profitronic Proscan Protec Pulsar Qisheng Quarter Quartz Quasar RadioShack Radix Randex	20240, 20000 20000, 20072 20058 20256 20035, 20037, 20048, 20104, 20067, 20041, 20038, 20040, 20008, 20370 20037 20037 20253, 20034 20240 21972 20035, 20226, 21046 20222 21062, 20162, 20037, 20048, 20104, 21048, 21262, 20162, 20162, 20058, 20432 20062 20184, 2029, 20002, 20479, 20295, 21479 21950 21062, 20035, 20162, 20077, 20226, 20616, 21162, 20225, 20367, 20227, 21035, 21262 21950 20035, 20037, 20240, 20042, 20038, 21035, 20040, 20054, 21237 20042, 20054, 21237 20042, 20055, 20061, 20079, 20226, 2079, 21381, 20100, 20618, 21181, 20563, 21081, 21949, 20062 20037 20042, 20067, 20058 20081 20240 20060, 20760, 21954, 20202, 21060, 20761 20072 20039 20060 20046 20046 20046 20046 20046 20047, 20058, 20166, 20777, 21162 200097 20037 20062 20037 20060 20046 20046 20046 20055, 20162, 21035, 20077, 21162 200099 20060 20046 20046 20035, 20162, 21035, 20077, 21162 200097 20037 20061, 21989, 20106, 20761, 21035, 20058, 21964, 20105, 20226, 20760, 20880, 21954, 20077, 20202, 20453 20037, 20047, 20060, 20880, 21954, 20077, 20202, 20453 20035, 20037, 200448, 20047, 20000, 20104, 20077, 20202, 20453 20035, 20037, 200448, 20047, 20000, 20104, 20077, 20202, 20453 20035, 20037, 200448, 20047, 20000, 20104, 20077, 20022, 20453 20035, 20037, 200448, 20047, 20000, 20104, 20075, 20075, 20075, 20076, 20080, 21954, 20077, 20022, 20760, 20880, 21954, 20077, 20222, 20760, 20880, 21954, 20077, 20022, 20453 20035, 20037, 200448, 20047, 20000, 20104, 20075, 20075, 20075, 20075, 20076, 2007	Wards White Westingh XR-1000 Yamaha Zenith ZT Group Setup Cod ABS Alienware CyberPower Gateway Hewlett Packare Howard Compu HP iBUYPOWER InterVideo Jensen JVC Keyspan KWorld LG Linksys Macro Image Te Media Center Pe Microsoft Mind Motorola MyHD Northgate Panasonic Pinnacle System Pioneer Princeton Rabbit Roku Samsung Sensory Science Sharp SMC Sony Streamzap	20060, 20035, 20048, 20047, 20081, 20240, 20000, 20042, 20072, 20062, 20212, 20760 100use 20209, 20072, 20637 20035, 20000, 20072 20041, 20038 20039, 20033, 20000, 20209, 20034, 20479, 21479, 21139, 20637 21972 1les for Video Accessories 01272 01272 01272 01272 01272 01272 01272 01272 01393 01165 01384 011344 01403 01415 01365 10365 10365 10360 10372 10272 10272 10272 10272 10272 10272 10393 10165 10384 10165 10384 10165 10384 10172 10165 10184 10165 10186 10165 10186 10190 10466 10100 10110 10110 101466 10110 101466 10110 101466 10110 101456 101272, 01324, 01364 101309 101272
Proscan 20522 Provision 20778 Qwestar 20651 RCA 20522, 20571, 20717, 20822, 21193, 21974, 21132, 21965, 21022, 21913 Regent 21938 Rio 20869 Rotel 20623 Rowa 20823 Sampo 20752, 20698 Samsung 20490, 20573, 20820, 21932, 21075, 20899, 21979 Sansui 20695 Samyo 20695, 20670, 21967, 20873 Sharp 20630, 20752 Sharper Image 21995, 21117 Sherwood 21043, 20770, 20633, 21077 Shinco 20717 Shinco 20717 Shinsonic 20533, 20839, 21931 Sigma Designs 20674 Sonic Blue 20869, 21970, 21099 Sony 20533, 21981, 20772, 21934 Sungale 21074 Supserscan 20821 SVA 20717, 20860, 21105 Sylvania 20821, 20675 Symphonic 20675 Teac 21984, 20809 <td> Voom</td> <td>Firstar Fisher Fortress Fujitsu Funai Furi Furi Futuretech Ganxin Gateway GE General Gibralter Gintai Go Video GoldStar Goodmans Grunpy Haier Haiyan Hallmark Hankook Harrley Davidson Harman/Kardon Harvard Havermy Hello Kitty Himitsu Hisense Hitachi Hongmei Hongyan Hua Tun Huafa Huanghe Huanghe Huanghe Huanyu Huaqiang Huari Huodateji Hyundai</td> <td>10236 10154, 10159 10093 10180, 10853, 10179, 10809, 10683 10180, 10171, 10264, 11904, 10179, 10342 10145, 10817, 10264 10180 10817 11756, 11755 11447, 10047, 11454, 10051, 10451, 10180, 10030, 10178, 10092, 11147, 11919, 10055, 10027, 11917, 10135, 10282, 11347, 10021, 11907, 11907, 11902 10186 10017, 10030, 10019 11150, 10474 10886 10154, 10030, 10178, 11926, 10019, 10037, 11910, 10001, 10032, 10056, 11150, 10039 10360 10180, 10179 11034, 10768 10264, 10817 10180, 10030, 10178, 11910, 10056, 10628 11904, 10179 10054 10180, 10030, 10178, 11019, 10056, 10628 11904, 10179 10054 10180, 10030, 10178, 11019, 10056, 10628 11904, 10179 10054 10180, 10030, 10178, 10019, 10056, 10628 11904, 10179 10054 10180, 10628 10156, 10748, 10145 11256, 10156, 10030, 10178, 11145, 10145, 10038, 11245, 10092, 10027, 10381, 10036, 1150, 10056, 11904, 10151, 10165, 10019, 10186, 10032, 10039, 10157, 10016, 10179, 10474 10093, 11910, 10817, 10264 10145, 10264 10145, 10264 10145, 10264 10145, 10264 10051 10849</td> <td>Megatron MEI Meile Memorex Mermaid MGA Midland Minutz Mitsubishi Monivision Motorola MTC Mudan Multitech NAD Nanbao Nansheng National NEC Newave Nikko Nikon Norcent Noshi NTC Onking Omwa Optimus Optoma Optonica Orion Panasonic</td> <td>10700 10178, 10145, 10003 10185 10264, 11910, 10817 10154, 10463, 10150, 10178, 10179, 11920, 11927, 10016, 11911, 11926, 11924 10037 10150, 10030, 10178, 11907, 10019 10047, 10017, 10051, 10039, 10135, 10032 10021 10154, 10250, 10093, 10236, 10180, 11250, 10150, 10030, 10178, 10381, 10386, 10036, 10179, 10817, 11150, 10474, 10019, 10868, 10056, 11917 10843, 10700 10093, 10055 10060, 10030, 10185, 10019, 10056 10051, 10817, 10264 10180 10156, 10178, 10866 11910, 10264 10817, 10264 10817, 10264 10051 10154, 10156, 10051, 10053, 10030, 10178, 10046, 11150, 10056, 10165, 10186, 10474, 10036, 10882, 10381, 10817, 11704, 10170, 10264, 10019, 10497 10033, 10178, 11150, 10092, 10161 10030, 10178, 10190 10748, 10824 10018 10092 10280 10180 10154, 10250, 10166, 11924, 11913, 10650, 11927 10887 10093, 10165 10236, 10463, 11911, 11905, 10179, 11463, 11929 10251, 10706, 10817, 10264, 11910 10051, 10706, 10817, 10264, 11910 10051, 10706, 10817, 10264, 11910 10047, 10156, 10051, 10060, 10030, 10178, 11919, 11941 10051, 10706, 10817, 10264, 11910 10047, 10156, 10051, 10060, 10030, 10178, 10135, 11347, 11926, 10018, 10027, 10039, 11919, 11094, 11097, 11097, 11099, 11091, 11094, 11097, 11099, 11097, 11099, 11097, 11099, 11091, 11097, 11099, 11097, 11099, 11091, 11097, 11091, 11097, 11099, 11091, 11097, 11099, 11097, 11099, 11091, 11097, 11099, 11097, 11099, 11097, 11099, 11097, 11099, 11097, 11099, 11091, 11097, 11099, 11091, 11097, 11099, 11091, 11097, 11099, 11091, 11097, 11099, 11091, 11097, 11099, 11091, 11097, 11099, 11091, 11097, 11099, 11091, 11097, 11099, 11091, 11097, 11099, 11097, 11099, 11091, 11097, 11099, 11091, 11097, 11099, 11097, 11099, 11097, 11099, 11091, 11097, 11099, 11091, 11097, 11099, 11091, 11097, 11099, 11091, 11097, 11099, 11091, 11097, 11099, 11091, 11097, 11099, 11091, 11097, 11099, 11091, 1109</td> <td>Shen Ying Shencai Shencai Shencai Shencai Sheng Chia Shenyang Shogun Signature Simpson Skygiant Skyworth Sony Soundesign Sowa Spectricon Squareview SSS Starlite Studio Experie Supre-Macy Supreme SVA Sylvania Symphonic Synco Tacico Tai Yi Taishan Tandy Tashiko Tatung Technics Technol Ace Techview Techwood Teco Teknika Telefunken Tera Thomas</td> <td>10039, 10165, 10474, 10688, 10787, 10036, 11917 3e 11950 10092, 10003, 10474, 10179 10145, 10264 10093, 10236, 10179, 11150, 10474 10817, 10264 10019 10016 10187, 10186 10180 10748, 10264, 10037, 10817 11100, 10000, 10036, 10650, 11300, 10111, 11925, 10080, 10834, 11904 10180, 10178, 10179, 10186 10156, 10051, 10060, 10178, 10036, 10092, 10474, 11150 10003 10171 10180, 10019 10180 ience 10843 10046 10000 10748, 10587, 10865, 10872, 10768, 10871, 10870 10054, 10030, 10171, 11931, 10381, 11944, 10020, 10096 10180, 10171, 11913, 11904 10000, 10451, 10093, 10060, 10178, 10092, 1036, 10474 10178, 10179, 11150, 10092, 10474 11150 10817, 10391 10093 11150, 10650, 10092 10054, 10054, 10055, 11056, 10051, 10060, 11150, 10474, 10036, 10055, 11756, 10003 10250, 10051 10179 10847 10051, 10003, 10078, 10474, 10036, 10280, 10092, 10246, 10180, 10178, 10179, 10056, 10051, 10003, 10178, 10474, 10036, 10250, 10051 10179 10847 10051, 10003, 10076 10051, 10003, 10178, 10474, 10036, 10280, 10092, 10264, 101653 10054, 10180, 10150, 10060, 10019, 10056, 10186, 10016, 10092, 10039, 10179 10702, 10056 10030, 10466, 10474 11904</td> <td>America Action American High Amoisonic Anam Anam National Asha Audiovox Beaumark Bell & Howell Blaupunkt Broksonic Calix Canon Carver CCE Changhong Citizen Colt Craig Curtis Mathes Cybernex CyberPower Daewoo Dell Denon DirecTV Dish Network Sy Dishpro Durabrand Dynatech Echostar Electrophonic Emerex Emerson Euro 1 Expressvu Fisher Fuji Fujitsu Funai Garrard Gateway</td> <td>21972 n 20278 h 200278 h 20035 20479 20162, 20037, 20240, 20278, 20226, 21037 ll 20162, 20226 20240 20037, 20278 20240 20104 20226 20184, 20121, 20209, 20002, 20348, 20295, 21479, 20479 20035, 21174, 20167 20081 20072, 20278 20048, 20081 20072, 20278 20048, 20081 20037, 20278, 21278 20072 20035, 20174, 2026, 20072, 20271 20060, 20035, 20162, 20041, 20760, 21035 20240 21972 20045, 20104, 20278, 20210, 20368, 21278, 20637, 20046, 20212, 20561 21972 20042 20739, 21989, 21954, 21949 20739, 21989, 21954, 21949 21944, 21943, 21946, 21945, 21944 21944, 21943, 21946, 21945, 21944 21944, 21943 20039, 20038 20000 21943, 21946, 21945, 21944 20037 20037 20037 20037 20037 20037 20037 20037 20037 20037 20037 20037 20038 20000 21943, 21946, 21945, 21944 21944, 21944, 20240, 20045, 20000, 20121, 20043, 20209, 20078, 20278, 20295, 20036, 20637, 21593, 20561, 21479, 20068, 20208, 20479, 21278, 20661, 20212 21962 21944 20047, 20104, 20066, 20054 20035, 20033 20045, 20052, 20366 20000, 20593, 21593 20000 21972</td> <td>MTC Multitech NAD National NEC Newave Nikko Nikon Noblex Northgate Olympus Onkyo Optimus Optonica Orion Panarex Panasonic Pansat Penney Pentax Philco Philips Pilot Pioneer Polk Audio Profitronic Proscan Protec Pulsar Quartz Quartz Quartz Quartz Quartz Quasar RadioShack Radix Randex RCA</td> <td>20240, 20000 20000, 20072 20058 20026 20035, 20037, 20048, 20104, 20067, 20041, 20038, 20040, 20008, 20370 20037 20037 20253, 20034 20240 21972 20035, 20226, 21046 20222 21062, 20162, 20037, 20048, 20104, 21048, 21262, 20593, 21162, 20058, 20452 20062 20184, 20209, 20002, 20479, 20295, 21479 21950 21062, 20035, 20162, 20077, 20226, 20616, 21162, 20225, 20367, 20227, 21035, 21262 21950 20035, 20037, 20240, 20042, 20038, 21035, 20040, 20054, 21237 20042, 20105 20035, 20000, 20226, 20479 20035, 20081, 20000, 20226, 20739, 21381, 20110, 20618, 21181, 20563, 21081, 21949, 20062 20037 20042, 20067, 20058 20081 20240 20060, 20760, 21954, 20202, 21060, 20761 20072 20039 20060 20046 20046 20046 20046 20055, 20162, 21035, 20077, 21162 20000, 21037 20042 20037 20060, 20035, 20240, 20000, 20242, 20807, 21060, 21989, 20106, 20761, 21035, 20058, 21964, 20105, 20226, 20760, 20880, 21954, 20077, 20202, 2045, 20077, 21162 200037 20060, 20035, 20240, 20000, 20042, 20807, 21060, 21989, 20106, 20761, 21035, 20058, 21964, 20105, 20226, 20760, 20880, 21954, 20077, 20202, 20453</td> <td>Wards White Westingh XR-1000 Yamaha Zenith ZT Group Setup Cod ABS Alienware CyberPower Gateway Hewlett Packare Howard Compu HP IBUYPOWER InterVideo Jensen JVC Keyspan KWorld LG Linksys Macro Image Te Media Center Pe Microsoft Mind Motorola MyHD Northgate Panasonic Pinnacle System Pioneer Princeton Rabbit Roku Samsung Sensory Science Sharp SMC Sony Streamzap Systemax Tagar Systems TeleCaption Toshiba</td> <td>20060, 20035, 20048, 20047, 20081, 20240, 20000, 20042, 20072, 20062, 20212, 20760 100use 20209, 20072, 20062, 20212, 20760 120035, 20000, 20072 120041, 20038 120039, 20033, 20000, 20209, 20034, 20479, 21479, 21139, 20637 121972 18es for Video Accessories 1272 101272 101272 101272 101272 101272 101272 101272 101393 10165 101384 101344 101403 101415 101365 101405 101365 101405 101405 101405 101505 101272 101272 101272 101372 101383 10145 101405 101405 101505 101606 101100 10113, 00295 100081 101466 10100 101466 10100 101456 101272 101272 101272 101272 101272 101272 101272 10120 10100 101466 10100 10456 10100 10456 101272, 01324, 01364 101309 101272 1012</td>	Voom	Firstar Fisher Fortress Fujitsu Funai Furi Furi Futuretech Ganxin Gateway GE General Gibralter Gintai Go Video GoldStar Goodmans Grunpy Haier Haiyan Hallmark Hankook Harrley Davidson Harman/Kardon Harvard Havermy Hello Kitty Himitsu Hisense Hitachi Hongmei Hongyan Hua Tun Huafa Huanghe Huanghe Huanghe Huanyu Huaqiang Huari Huodateji Hyundai	10236 10154, 10159 10093 10180, 10853, 10179, 10809, 10683 10180, 10171, 10264, 11904, 10179, 10342 10145, 10817, 10264 10180 10817 11756, 11755 11447, 10047, 11454, 10051, 10451, 10180, 10030, 10178, 10092, 11147, 11919, 10055, 10027, 11917, 10135, 10282, 11347, 10021, 11907, 11907, 11902 10186 10017, 10030, 10019 11150, 10474 10886 10154, 10030, 10178, 11926, 10019, 10037, 11910, 10001, 10032, 10056, 11150, 10039 10360 10180, 10179 11034, 10768 10264, 10817 10180, 10030, 10178, 11910, 10056, 10628 11904, 10179 10054 10180, 10030, 10178, 11019, 10056, 10628 11904, 10179 10054 10180, 10030, 10178, 11019, 10056, 10628 11904, 10179 10054 10180, 10030, 10178, 10019, 10056, 10628 11904, 10179 10054 10180, 10628 10156, 10748, 10145 11256, 10156, 10030, 10178, 11145, 10145, 10038, 11245, 10092, 10027, 10381, 10036, 1150, 10056, 11904, 10151, 10165, 10019, 10186, 10032, 10039, 10157, 10016, 10179, 10474 10093, 11910, 10817, 10264 10145, 10264 10145, 10264 10145, 10264 10145, 10264 10051 10849	Megatron MEI Meile Memorex Mermaid MGA Midland Minutz Mitsubishi Monivision Motorola MTC Mudan Multitech NAD Nanbao Nansheng National NEC Newave Nikko Nikon Norcent Noshi NTC Onking Omwa Optimus Optoma Optonica Orion Panasonic	10700 10178, 10145, 10003 10185 10264, 11910, 10817 10154, 10463, 10150, 10178, 10179, 11920, 11927, 10016, 11911, 11926, 11924 10037 10150, 10030, 10178, 11907, 10019 10047, 10017, 10051, 10039, 10135, 10032 10021 10154, 10250, 10093, 10236, 10180, 11250, 10150, 10030, 10178, 10381, 10386, 10036, 10179, 10817, 11150, 10474, 10019, 10868, 10056, 11917 10843, 10700 10093, 10055 10060, 10030, 10185, 10019, 10056 10051, 10817, 10264 10180 10156, 10178, 10866 11910, 10264 10817, 10264 10817, 10264 10051 10154, 10156, 10051, 10053, 10030, 10178, 10046, 11150, 10056, 10165, 10186, 10474, 10036, 10882, 10381, 10817, 11704, 10170, 10264, 10019, 10497 10033, 10178, 11150, 10092, 10161 10030, 10178, 10190 10748, 10824 10018 10092 10280 10180 10154, 10250, 10166, 11924, 11913, 10650, 11927 10887 10093, 10165 10236, 10463, 11911, 11905, 10179, 11463, 11929 10251, 10706, 10817, 10264, 11910 10051, 10706, 10817, 10264, 11910 10051, 10706, 10817, 10264, 11910 10047, 10156, 10051, 10060, 10030, 10178, 11919, 11941 10051, 10706, 10817, 10264, 11910 10047, 10156, 10051, 10060, 10030, 10178, 10135, 11347, 11926, 10018, 10027, 10039, 11919, 11094, 11097, 11097, 11099, 11091, 11094, 11097, 11099, 11097, 11099, 11097, 11099, 11091, 11097, 11099, 11097, 11099, 11091, 11097, 11091, 11097, 11099, 11091, 11097, 11099, 11097, 11099, 11091, 11097, 11099, 11097, 11099, 11097, 11099, 11097, 11099, 11097, 11099, 11091, 11097, 11099, 11091, 11097, 11099, 11091, 11097, 11099, 11091, 11097, 11099, 11091, 11097, 11099, 11091, 11097, 11099, 11091, 11097, 11099, 11091, 11097, 11099, 11091, 11097, 11099, 11097, 11099, 11091, 11097, 11099, 11091, 11097, 11099, 11097, 11099, 11097, 11099, 11091, 11097, 11099, 11091, 11097, 11099, 11091, 11097, 11099, 11091, 11097, 11099, 11091, 11097, 11099, 11091, 11097, 11099, 11091, 11097, 11099, 11091, 1109	Shen Ying Shencai Shencai Shencai Shencai Sheng Chia Shenyang Shogun Signature Simpson Skygiant Skyworth Sony Soundesign Sowa Spectricon Squareview SSS Starlite Studio Experie Supre-Macy Supreme SVA Sylvania Symphonic Synco Tacico Tai Yi Taishan Tandy Tashiko Tatung Technics Technol Ace Techview Techwood Teco Teknika Telefunken Tera Thomas	10039, 10165, 10474, 10688, 10787, 10036, 11917 3e 11950 10092, 10003, 10474, 10179 10145, 10264 10093, 10236, 10179, 11150, 10474 10817, 10264 10019 10016 10187, 10186 10180 10748, 10264, 10037, 10817 11100, 10000, 10036, 10650, 11300, 10111, 11925, 10080, 10834, 11904 10180, 10178, 10179, 10186 10156, 10051, 10060, 10178, 10036, 10092, 10474, 11150 10003 10171 10180, 10019 10180 ience 10843 10046 10000 10748, 10587, 10865, 10872, 10768, 10871, 10870 10054, 10030, 10171, 11931, 10381, 11944, 10020, 10096 10180, 10171, 11913, 11904 10000, 10451, 10093, 10060, 10178, 10092, 1036, 10474 10178, 10179, 11150, 10092, 10474 11150 10817, 10391 10093 11150, 10650, 10092 10054, 10054, 10055, 11056, 10051, 10060, 11150, 10474, 10036, 10055, 11756, 10003 10250, 10051 10179 10847 10051, 10003, 10078, 10474, 10036, 10280, 10092, 10246, 10180, 10178, 10179, 10056, 10051, 10003, 10178, 10474, 10036, 10250, 10051 10179 10847 10051, 10003, 10076 10051, 10003, 10178, 10474, 10036, 10280, 10092, 10264, 101653 10054, 10180, 10150, 10060, 10019, 10056, 10186, 10016, 10092, 10039, 10179 10702, 10056 10030, 10466, 10474 11904	America Action American High Amoisonic Anam Anam National Asha Audiovox Beaumark Bell & Howell Blaupunkt Broksonic Calix Canon Carver CCE Changhong Citizen Colt Craig Curtis Mathes Cybernex CyberPower Daewoo Dell Denon DirecTV Dish Network Sy Dishpro Durabrand Dynatech Echostar Electrophonic Emerex Emerson Euro 1 Expressvu Fisher Fuji Fujitsu Funai Garrard Gateway	21972 n 20278 h 200278 h 20035 20479 20162, 20037, 20240, 20278, 20226, 21037 ll 20162, 20226 20240 20037, 20278 20240 20104 20226 20184, 20121, 20209, 20002, 20348, 20295, 21479, 20479 20035, 21174, 20167 20081 20072, 20278 20048, 20081 20072, 20278 20048, 20081 20037, 20278, 21278 20072 20035, 20174, 2026, 20072, 20271 20060, 20035, 20162, 20041, 20760, 21035 20240 21972 20045, 20104, 20278, 20210, 20368, 21278, 20637, 20046, 20212, 20561 21972 20042 20739, 21989, 21954, 21949 20739, 21989, 21954, 21949 21944, 21943, 21946, 21945, 21944 21944, 21943, 21946, 21945, 21944 21944, 21943 20039, 20038 20000 21943, 21946, 21945, 21944 20037 20037 20037 20037 20037 20037 20037 20037 20037 20037 20037 20037 20038 20000 21943, 21946, 21945, 21944 21944, 21944, 20240, 20045, 20000, 20121, 20043, 20209, 20078, 20278, 20295, 20036, 20637, 21593, 20561, 21479, 20068, 20208, 20479, 21278, 20661, 20212 21962 21944 20047, 20104, 20066, 20054 20035, 20033 20045, 20052, 20366 20000, 20593, 21593 20000 21972	MTC Multitech NAD National NEC Newave Nikko Nikon Noblex Northgate Olympus Onkyo Optimus Optonica Orion Panarex Panasonic Pansat Penney Pentax Philco Philips Pilot Pioneer Polk Audio Profitronic Proscan Protec Pulsar Quartz Quartz Quartz Quartz Quartz Quasar RadioShack Radix Randex RCA	20240, 20000 20000, 20072 20058 20026 20035, 20037, 20048, 20104, 20067, 20041, 20038, 20040, 20008, 20370 20037 20037 20253, 20034 20240 21972 20035, 20226, 21046 20222 21062, 20162, 20037, 20048, 20104, 21048, 21262, 20593, 21162, 20058, 20452 20062 20184, 20209, 20002, 20479, 20295, 21479 21950 21062, 20035, 20162, 20077, 20226, 20616, 21162, 20225, 20367, 20227, 21035, 21262 21950 20035, 20037, 20240, 20042, 20038, 21035, 20040, 20054, 21237 20042, 20105 20035, 20000, 20226, 20479 20035, 20081, 20000, 20226, 20739, 21381, 20110, 20618, 21181, 20563, 21081, 21949, 20062 20037 20042, 20067, 20058 20081 20240 20060, 20760, 21954, 20202, 21060, 20761 20072 20039 20060 20046 20046 20046 20046 20055, 20162, 21035, 20077, 21162 20000, 21037 20042 20037 20060, 20035, 20240, 20000, 20242, 20807, 21060, 21989, 20106, 20761, 21035, 20058, 21964, 20105, 20226, 20760, 20880, 21954, 20077, 20202, 2045, 20077, 21162 200037 20060, 20035, 20240, 20000, 20042, 20807, 21060, 21989, 20106, 20761, 21035, 20058, 21964, 20105, 20226, 20760, 20880, 21954, 20077, 20202, 20453	Wards White Westingh XR-1000 Yamaha Zenith ZT Group Setup Cod ABS Alienware CyberPower Gateway Hewlett Packare Howard Compu HP IBUYPOWER InterVideo Jensen JVC Keyspan KWorld LG Linksys Macro Image Te Media Center Pe Microsoft Mind Motorola MyHD Northgate Panasonic Pinnacle System Pioneer Princeton Rabbit Roku Samsung Sensory Science Sharp SMC Sony Streamzap Systemax Tagar Systems TeleCaption Toshiba	20060, 20035, 20048, 20047, 20081, 20240, 20000, 20042, 20072, 20062, 20212, 20760 100use 20209, 20072, 20062, 20212, 20760 120035, 20000, 20072 120041, 20038 120039, 20033, 20000, 20209, 20034, 20479, 21479, 21139, 20637 121972 18es for Video Accessories 1272 101272 101272 101272 101272 101272 101272 101272 101393 10165 101384 101344 101403 101415 101365 101405 101365 101405 101405 101405 101505 101272 101272 101272 101372 101383 10145 101405 101405 101505 101606 101100 10113, 00295 100081 101466 10100 101466 10100 101456 101272 101272 101272 101272 101272 101272 101272 10120 10100 101466 10100 10456 10100 10456 101272, 01324, 01364 101309 101272 1012
Proscan 20522 ProVision 20778 Qwestar 20651 RCA 20522, 20571, 20717, 20822, 21193, 21974, 21132, 21965, 21022, 21913 Regent 21938 Rio 20869 Rotel 20623 Rowa 20823 Saba 21977 Sampo 20752, 20698 Samsung 20490, 20573, 20820, 21932, 21075, 20899, 21979 Sansui 20695 Sanyo 20695, 20670, 21967, 20873 Sharp 20630, 20752 Sharper Image 21995, 21117 Sherwood 20143, 20770, 20633, 21077 Shinco 20717 Shinsonic 20533, 20839, 21931 Sigma Designs 20674 Sonic Blue 20689, 21970, 21099 Sony 20533, 21533, 20864, 21033, 21904, 22020, 21903, 21903, 21981, 20772, 21934 Sungale 21074 Sylvania 20821, 20675 Symphonic 20675 Teac 21984, 20809 Technosonic 20730 Techn	Voom	Firstar Fisher Fortress Fujitsu Funai Furi Furi Furi Ganxin Gateway GE General Gibralter Gintai Go Video GoldStar Goodmans Grunpy Haier Haiyan Hallmark Hankook Harley Davidson Harrand/Kardon Harrvard Hawermy Hello Kitty Himitsu Hisense Hitachi Hongmei Hongyan Hua Tun Huafa Huanghe Huangshan Huanghe Huangshan Huanju Huaqiang Huari Huodateji Hyundai Imperial Crown	10236 10154, 10159 10093 10180, 10853, 10179, 10809, 10683 10180, 10171, 10264, 11904, 10179, 10342 10145, 10817, 10264 10180 10817 11756, 11755 11447, 10047, 11454, 10051, 10451, 10180, 10030, 10178, 10092, 11147, 11919, 10055, 10027, 11917, 10135, 10282, 11347, 10021, 11907, 11922 10186 10017, 10030, 10019 11150, 10474 10886 10154, 10030, 10178, 11926, 10019, 10037, 11910, 10001, 10032, 10056, 11150, 10039 10360 10180, 10179 11034, 10768 10264, 10817 10178 10180, 10030, 10178, 11092, 10019, 10056, 10628 11904, 10179 10054 10180, 10030, 10178, 11019, 10056, 10628 11904, 10179 10054 10180, 10030, 10178, 11019, 10056, 10628 11904, 10179 10054 10180, 10030, 10178, 10019, 10056, 10628 11904, 10179 10054 10180, 10030, 10178, 10019, 10056, 10628 11905, 10748, 10145 11256, 10156, 10030, 10178, 11145, 10145, 10038, 11245, 10092, 10027, 10381, 10036, 11150, 10056, 11094, 10151, 10165, 10019, 10186, 10032, 10033, 10157, 10016, 10179, 10474 10093, 11910, 10817, 10264 10145, 10264 10145, 10264 10145, 10264 103849 10001, 10391, 10264	Megatron MEI Meile Memorex Mermaid MGA Midland Minutz Mitsubishi Monivision Motorola MTC Mudan Multitech NAD Nanbao Nansheng National NEC Newave Nikko Nikon Norcent Noshi NTC Onking Omwa Optimus Optoma Optonica Orion Panasonic	10700 10178, 10145, 10003 10185 10264, 11910, 10817 10154, 10463, 10150, 10178, 10179, 11920, 11927, 10016, 11911, 11926, 11924 10037 10150, 10030, 10178, 11907, 10019 10047, 10017, 10051, 10039, 10135, 10032 10021 10154, 10250, 10093, 10236, 10180, 11250, 10150, 10030, 10178, 10381, 10836, 10036, 10179, 10817, 11150, 10474, 10019, 10868, 10056, 11917 10843, 10700 10030, 101817, 11150, 10474, 10019, 10868, 10056, 11917 10843, 10700 10031, 10187, 11150, 10474, 10019, 10868, 10056, 11917 10843, 10700 10031, 10187, 10264 10180 10156, 10178, 10866 11910, 10264 10817, 10264 10817, 10264 10817, 10264 10817, 10264 10951 10154, 10156, 10051, 10053, 10030, 10178, 10046, 11150, 10056, 10165, 10186, 10474, 10036, 10882, 10381, 10817, 11704, 10170, 10264, 10019, 10497 10093, 10178, 11150, 10092, 10161 10030, 10178, 10092 11910 10748, 10824 10018 10092 10280 10180 10154, 10250, 10166, 11924, 11913, 10650, 11927 10887 1093, 10165 10236, 10463, 11911, 11905, 10179, 11463, 11929 10054, 10250, 10051, 10161, 11410, 11927, 10947, 10037, 10055, 10650, 11924, 11946, 11919, 11941 10051, 10706, 10817, 10264, 11910 10074, 10156, 10051, 10060, 10030, 10178, 10135, 11347, 11926, 10018, 10027, 10039, 11919, 10003, 100178, 10135, 11035, 11035, 11035, 11037, 11926, 10018, 10027, 10039, 11919, 10003, 100178, 10135, 1103	Shen Ying Shencai Shencai Shencai Shencai Shencai Shencai Shencai Shencai Shencai Signature Signature Simpson Skygiant Skyworth Sony Soundesign Sowa Spectricon Squareview SSS Starlite Studio Experie Supre-Macy Supre-Macy Supreme SVA Sylvania Symphonic Synco Tacico Tai Yi Taishan Tandy Tashiko Tatung Technics Technol Ace Techview Techwood Teco Telefunken Telefunken Tera	10039, 10165, 10474, 10688, 10787, 10036, 11917 3e 11950 10092, 10003, 10474, 10179 10145, 10264 10093, 10236, 10179, 11150, 10474 10817, 10264 10019 10016 10187, 10186 10180 10748, 10264, 10037, 10817 11100, 10000, 1036, 10650, 11300, 10111, 11925, 10080, 10834, 11904 10180, 10178, 10179, 10186 10156, 10051, 10060, 10178, 10036, 10092, 10474, 11150 10003 10171 10180, 10019 10180 10004 10748, 10587, 10865, 10872, 10768, 10871, 10870 10054, 10030, 10171, 11931, 10381, 11944, 10020, 10096 10180, 10171, 11913, 11904 10000, 10451, 10093, 10060, 10178, 10092, 10036, 10474 10178, 10179, 11150, 10092, 10474 11150 10817, 10391 10093 11150, 10650, 10092 10054, 10154, 10156, 10051, 10060, 11150, 10474, 10036, 10055, 11756, 10003 10250, 10051 10179 10847 10051, 10003, 10056 10051, 10003, 10178, 10474, 10036, 10280, 10092, 10264, 10653 10054, 10180, 10151, 10060, 10019, 10056, 10186, 10016, 10018, 10079, 10076, 10086, 10018, 10016, 10019, 10076, 10186, 10016, 10019, 10056, 10186, 10016, 10019, 10056, 10180, 10150, 10056, 10030, 10466, 10474	America Action American High Amoisonic Anam Anam National Asha Audiovox Beaumark Bell & Howell Blaupunkt Broksonic Calix Canon Carver CCE Changhong Citizen Colt Craig Curtis Mathes Cybernex CyberPower Daewoo Dell Denon DirecTV Dish Network Sy Dishpro Durabrand Dynatech Echostar Electrophonic Emerex Emerson Euro 1 Expressvu Fisher Fuji Fujitsu Funai Garrard Gateway GE	21972 n 20278 h 200278 h 20035 20479 20162, 20037, 20240, 20278, 20226, 21037 ll 20162, 20226 20240 20037, 20278 20240 20104 20104 20126 20184, 20121, 20209, 20002, 20348, 20295, 21479, 20479 20035, 21174, 20167 20081 20072, 20278 20048, 20081 20072, 20278 20037, 20278, 21278 20072 20037, 20047, 20240, 20072, 20271 20060, 20035, 20162, 20041, 20760, 21035 20240 21972 20045, 20104, 20278, 20210, 20368, 21278, 20637, 20046, 20212, 20561 21972 20042 20739, 21899, 21954, 21949 System 21943, 21946, 21945, 21944 21944, 21943 20039, 20038 20000 21943, 21946, 21945, 21944 20037 20037 20037 20037 20038 20000 21943, 21946, 21945, 21944 20037 20037 20039 20039, 20038 20000 21943, 21946, 21945, 21944 20037 20037 20032 20035, 20037, 20184, 20240, 20045, 20000, 20121, 20043, 20209, 20002, 20278, 20295, 20036, 20637, 21593, 20561, 21479, 20068, 20208, 20479, 21278, 20061, 20212 21962 21944 20047, 20104, 20066, 20054 20035, 20035, 20033 20045, 20052, 20366 20000, 20593, 21593 20000 21972 20060, 20035, 20240, 21060, 20202, 20760, 21035, 20807, 20226, 20761	MTC Multitech NAD National NEC Newave Nikko Nikon Noblex Northgate Olympus Onkyo Optimus Optonica Orion Panarex Panasonic Pansat Penney Pentax Philco Philips Pilot Pioneer Polk Audio Profitronic Proscan Protec Pulsar Quartz Quartz Quartz Quartz Quartz Quartz Quartz Quartz Quartz Quasar RadioShack Radix Randex RCA Realistic ReplayTV Ricoh	20240, 20000 20000, 20072 20058 20026 20035, 20037, 20048, 20104, 20067, 20041, 20038, 20040, 20008, 20370 20037 20037 20253, 20034 20240 21972 20035, 20226, 21046 20222 21062, 20162, 20037, 20048, 20104, 21048, 21262, 20593, 21162, 20058, 20432 20062 20184, 20209, 20002, 20479, 20295, 21479 21950 21062, 20035, 20162, 20077, 20226, 20616, 21162, 20225, 20367, 20227, 21035, 21262 21950 20035, 20037, 20240, 20042, 20038, 21035, 20040, 20054, 211237 20042, 20105 20035, 200081, 20000, 20226, 20739, 21381, 20110, 20618, 21181, 20563, 21081, 21949, 20062 20037 20042, 20067, 20058 20081 20240 20060, 20760, 21954, 20202, 21060, 20761 20072 20039 20060 20046 20046 20046 20046 20058, 20162, 21035, 20077, 21162 200097 20037 20042, 20169, 20169, 2077, 21162 200007 20039 20060 20046 20046 20046 20055, 20162, 21035, 20077, 21162 200007 20060, 20760, 21954, 20202, 21060, 20761 20072 20037 20060, 20760, 21954, 20202, 21060, 20761 20072 20039 20060 20046 20046 20055, 20162, 21035, 20077, 21162 200007 20057, 20202, 2026, 20760, 20880, 21954, 20105, 20226, 20760, 20880, 21954, 20107, 202062, 20750, 20880, 21954, 20107, 202062, 20753, 20081, 20061 20046, 20046, 20062 20048, 20047, 20000, 20042, 20807, 21060, 21989, 20106, 20761, 21035, 20058, 21644, 20105, 20226, 20760, 20880, 21954, 20077, 20202, 20453 20035, 20037, 20048, 20047, 20000, 20104, 20066, 20046, 20062 20044, 20166 20253, 20034	Wards White Westingh XR-1000 Yamaha Zenith ZT Group Setup Cod ABS Alienware CyberPower Gateway Hewlett Packare Howard Compu HP IBUYPOWER InterVideo Jensen JVC Keyspan KWorld LG Linksys Macro Image Te Media Center Po Microsoft Mind Motorola MyHD Northgate Panasonic Pinnacle System Pioneer Princeton Rabbit Roku Samsung Sensory Science Sharp SMC Sony Streamzap Systemax Tagar Systems TeleCaption Toshiba Touch	20060, 20035, 20048, 20047, 20081, 20240, 20000, 20042, 200772, 20062, 20212, 20760 100use 20209, 20072, 20637 20035, 20000, 20072 20041, 20038 20039, 20033, 20000, 20209, 20034, 20479, 21479, 21139, 20637 21972 1les for Video Accessories 01272 01272 01272 01272 01272 01272 01272 01272 01393 01165 01384 01344 01403 01415 01365 10365 10365 10366 10366 10372 01272 01272 01272 01393 01165 01384 01134 01403 01415 01365 10383 01272 01272 01272 01272 01272 01272 01272 01272 01272 01272 01363 01383 001272 01120 10100 00113, 00295 00081 001486 01190, 01490 101106 011456 01272, 01324, 01364 01309 01272 01272 00171 01272 00171 01272 00172 00172 00172 00172 00172 00172 00172 00172 00172 00171 01272 00177 01272 00177 01272 00177 01272 00177 01272 00177 01272 00177 01272 00177 01272 00177 01272 00177 01272 00177 01272 00177 01272 00177 01272 00177 01272 00177 01272 00177 01272 00177 01272 00177 01272 00177 0
Proscan 20522 ProVision 20778 Qwestar 20651 RCA 20522, 20571, 20717, 20822, 21193, 21974, 21132, 21965, 21022, 21913 Regent 21938 Rio 20689 Rotel 20623 Rowa 20823 Sampo 20752, 20698 Sampo 20752, 20698 Samsung 20490, 20573, 20820, 21932, 21075, 20899, 21979 Sansui 20695 Sanyo 20695, 20670, 21967, 20873 Sharp 20630, 20752 Sharpe Image 21995, 21117 Sherwood 21043, 20770, 20633, 21077 Shinco 20717 Shinco 20717 Shinco 20717 Sonic Blue 20869, 21970, 21099 Sony 20533, 20834, 21931 Sigma Designs 20674 Song 20533, 21931, 20772, 21934 Sungale 21074 Superscan 20821 SVA 20717, 20860, 21105 Sylvania 20821, 20675 <t< td=""><td> Voom</td><td>Firstar Fisher Fortress Fujitsu Funai Furi Furi Formai Furi Ganxin Gateway GE General Gibralter Gintai Go Video GoldStar Goodmans Grunpy Haier Haiyan Hallmark Hankook Harley Davidson Harman/Kardon Harward Havermy Hello Kitty Himitsu Hisense Hitachi Hongmei Hongyan Hua Tun Huafa Huanghe Huanghe Huanghe Huanghe Huangh Huari Huodateji Hyundai Imperial Crown Infinity</td><td>10236 10154, 10159 10093 10180, 10853, 10179, 10809, 10683 10180, 10171, 10264, 11904, 10179, 10342 10145, 10817, 10264 10180 10817 11756, 11755 11447, 10047, 11454, 10051, 10451, 10180, 10030, 10178, 10092, 11147, 11919, 10055, 10027, 11917, 10135, 10282, 11347, 10021, 11907, 11907, 11902 10186 10017, 10030, 10019 11150, 10474 10886 10154, 10030, 10178, 11926, 10019, 10037, 11910, 10001, 10032, 10056, 11150, 10039 10360 10180, 10179 11034, 10768 10264, 10817 10180, 10030, 10178, 11910, 10056, 10628 11904, 10179 10054 10180, 10030, 10178, 11019, 10056, 10628 11904, 10179 10054 10180, 10030, 10178, 11019, 10056, 10628 11904, 10179 10054 10180, 10030, 10178, 10019, 10056, 10628 11904, 10179 10054 10180, 10628 10156, 10748, 10145 11256, 10156, 10030, 10178, 11145, 10145, 10038, 11245, 10092, 10027, 10381, 10036, 1150, 10056, 11904, 10151, 10165, 10019, 10186, 10032, 10039, 10157, 10016, 10179, 10474 10093, 11910, 10817, 10264 10145, 10264 10145, 10264 10145, 10264 10145, 10264 10051 10849</td><td>Megatron MEI Meile Memorex Mermaid MGA Midland Minutz Mitsubishi Monivision Motorola MTC Mudan Multitech NAD Nanbao Nansheng National NEC Newave Nikko Nikon Norcent Noshi NTC Onking Onwa Optimus Optoma Optomica Orion Panasonic</td><td>10700 10178, 10145, 10003 10185 10264, 11910, 10817 10154, 10463, 10150, 10178, 10179, 11920, 11927, 10016, 11911, 11926, 11924 10037 10150, 10030, 10178, 11907, 10019 10047, 10017, 10051, 10039, 10135, 10032 10021 10154, 10250, 10093, 10236, 10180, 11250, 10150, 10030, 10178, 10381, 10386, 10036, 10179, 10381, 10386, 10036, 10179, 10381, 101836, 10036, 10179, 10381, 101836, 10036, 10179, 10381, 101843, 10700 10093, 10055 10060, 10030, 10185, 10019, 10056 10051, 10817, 11264 10180 10156, 10178, 10866 11910, 10264 10817, 10264 10817, 10264 10051 10154, 10156, 10051, 10053, 10030, 10178, 10046, 11150, 10056, 10165, 10186, 10474, 10036, 10882, 10381, 10817, 11704, 10170, 10264, 10019, 10497 10093, 10178, 11150, 10092, 10161 10030, 10178, 10092 11910 10748, 10824 10018 10092 10280 10180 10154, 10250, 10166, 11924, 11913, 10650, 11927 10887 10093, 10165 10236, 10463, 11911, 11905, 10179, 11463, 11929 10254, 10250, 10051, 10051, 10161, 11410, 11927, 11947, 10037, 10055, 10650, 11924, 11946, 11919, 11941 10051, 10706, 10817, 10264, 11910 10047, 10156, 10051, 10060, 10030, 10178, 10153, 11347, 11926, 10018, 10027, 10039, 11919, 11094, 11097, 11097, 11099, 10019 10054, 10250, 10051, 10061, 10074, 10019, 10032, 10056, 10186, 100774, 10019, 10032, 10036, 10186, 100774, 10019, 10032, 10056, 10186, 10774, 10019, 10032, 10056, 10186, 10774, 10019, 10032, 10056, 10186, 10774, 10019, 10032, 10056, 10186, 10774, 10019, 10032, 10056, 10186, 10774, 10019, 10032, 10056, 10186, 10774, 10019, 10032, 10056, 10186, 10774, 10019, 10032, 10056, 10186, 10774, 10019, 10032, 10056, 10186, 10774, 10019, 10032, 10054, 10076, 10186, 10774, 10019, 10032, 10054, 10074, 10019, 10154, 10076, 10186, 10774, 10019, 10032, 10076, 10186, 10774, 10019, 10032, 10076, 10186, 10774, 10019, 10032, 10076, 10186, 10774, 10019, 10154, 10076, 10186, 10774, 10019, 10032, 10076, 10186, 10774, 10019, 10032, 10076, 10186, 10774, 10019, 10054, 10000, 10051, 10030, 10178, 10054, 10000, 10051, 10060, 10076, 10186, 10774, 10019, 10054, 10000, 10051, 10076, 10187, 1077</td><td>Shen Ying Shencai Signature Signature Simpson Skygiant Skyworth Sony Soundesign Sowa Spectricon Squareview SSS Starlite Studio Experie Supre-Macy Supreme SVA Sylvania Symphonic Synco Tacico Tai Yi Taishan Tandy Tashiko Tatung Technics Technol Ace Techview Techwood Teco Teknika Telefunken Tera Thomas Tiane Tiane TMK TNCi</td><td>10039, 10165, 10474, 10688, 10787, 10036, 11917 ge 11950 10092, 10003, 10474, 10179 10145, 10264 10093, 10236, 10179, 11150, 10474 10817, 10264 10019 10016 10187, 10186 10180 10748, 10264, 10037, 10817 11100, 10000, 10036, 10650, 11300, 10111, 11925, 10080, 10834, 11904 10180, 10178, 10179, 10186 10156, 10051, 10060, 10178, 10036, 10092, 10474, 11150 10003 10171 10180, 10019 10180 10006 10748, 10587, 10865, 10872, 10768, 10871, 108870 100046 10000 10748, 1030, 10171, 11931, 10381, 11944, 10020, 10096 10180, 10171, 11913, 11904 10000, 10451, 10093, 10060, 10178, 10092, 1036, 10474 10178, 10179, 11150, 10092, 10474 11150 10817, 10391 10093 11150, 10650, 10092 10054, 10154, 10156, 10051, 10060, 11150, 10474, 10036, 10055, 11756, 10003 10250, 10051 10179 10847 10051, 10003, 10076 10071, 10093, 10178, 10474, 10036, 10280, 10092, 10264, 1053, 10756, 10003 10250, 10051 10179 10847 10051, 10003, 10056 10051, 10093, 10178, 10474, 10036, 10280, 10099, 10264, 10536, 10074, 10179, 10079, 10056, 10186, 10016, 10092, 10039, 10179 10702, 10056 10030, 10466, 10474 11904 10093, 10817 10178, 10177, 10056</td><td>America Action American High Amoisonic Anam Anam National Asha Audiovox Beaumark Bell & Howell Blaupunkt Broksonic Calix Canon Carver CCE Changhong Citizen Colt Craig Curtis Mathes Cybernex CyberPower Daewoo Dell Denon DirecTV Dish Network Sy Dishpro Durabrand Dynatech Echostar Electrohome Electrophonic Emerex Emerson Euro 1 Expressvu Fisher Fuji Fujitsu Funai Garrard Gateway GE General</td><td>21972 n 20278 h 200278 h 20035 20479 20162, 20037, 20240, 20278, 20226, 21037 ll 20162, 20226 20240 20037, 20278 20240 20104 20226 20184, 20121, 20209, 20002, 20348, 20295, 21479, 20479 20035, 21174, 20167 20081 20072, 20278 20048, 20081 20072, 20278 20048, 20081 20037, 20278, 21278 20072 20035, 20174, 2026, 20072, 20271 20060, 20035, 20162, 20041, 20760, 21035 20240 21972 20045, 20104, 20278, 20210, 20368, 21278, 20637, 20038, 20122, 20561 21972 20045, 20104, 20278, 20210, 20368, 21278, 20637, 20948, 20948, 20949 20739, 21989, 21954, 21949 System 21943, 21946, 21945, 21944 21944, 21943 20039, 20038 20000 21943, 21946, 21945, 21944 20037 20037 20037 20037 20037 20037 20037 20038 20000 21943, 21946, 21945, 21944 20037 20037, 20184, 20240, 20045, 20000, 20121, 20043, 20209, 20002, 20278, 20295, 20036, 20637, 21593, 20561, 21479, 20068, 20208, 20479, 21278, 20661, 20212 21962 21944 20047, 20104, 20066, 20054 20035, 20033 20045, 20052, 20366 20000, 20593, 21593 20000 21972 20060, 20035, 20226, 20761 20045, 20366, 20052</td><td>MTC Multitech NAD National NEC Newave Nikko Nikon Noblex Northgate Olympus Onkyo Optimus Optonica Orion Panarex Panasonic Pansat Penney Pentax Philco Philips Pilot Pioneer Polk Audio Profitronic Prostar Quarter Quarter Quarter Quarter Quarter Quarter Quarter Quarter RadioShack Radix Randex RCA Realistic ReplayTV Ricoh Runco</td><td>20240, 20000 20000, 20072 20058 20256 2026 20035, 20037, 20048, 20104, 20067, 20041, 20038, 20040, 20008, 20370 20037 20253, 20034 20253, 20034 20240 21972 20035, 20226, 21046 20222 21062, 20162, 20037, 20048, 20104, 21048, 21262, 20593, 21162, 20058, 20432 20062 20184, 20209, 20002, 20479, 20295, 21479 21950 21062, 20035, 20162, 20077, 20226, 20616, 21162, 20225, 20367, 20227, 21035, 21262 21950 20035, 20035, 20162, 20077, 20226, 20616, 21162, 20225, 20367, 20227, 21035, 21262 21950 20035, 20037, 20240, 20042, 20038, 21035, 20040, 20054, 21237 20042, 20105 20035, 20061, 20000, 20226, 20739, 21381, 20110, 20618, 21181, 20563, 21081, 21949, 20062 20037 20042, 20067, 20058 20081 20240 20060, 20760, 21954, 20202, 21060, 20761 20072 20039 20060 20046 20046 20046 20046 20045, 20162, 21035, 20077, 21162 20000, 21037 20037 20061 20046 20046 20046 20046, 20053, 20162, 21035, 20077, 21162 20009 20046 20046 20037, 20022, 2040, 20000, 20042, 20807, 21060, 21989, 20106, 20761, 21035, 20058, 21964, 20105, 20226, 20760, 20880, 21954, 20077, 20222, 20153, 20034, 20046, 20066, 20046, 20062, 20761, 21035, 20058, 21964, 20105, 20226, 20760, 20880, 21954, 20077, 20222, 20153, 20034, 20044, 20016, 20061, 20</td><td>Wards White Westingh XR-1000 Yamaha Zenith ZT Group Setup Cod ABS Alienware CyberPower Gateway Hewlett Packare Howard Compu HP IBUYPOWER InterVideo Jensen JVC Keyspan KWorld LG Linksys Macro Image Te Media Center Pe Microsoft Mind Motorola MyHD Northgate Panasonic Pinnacle System Pioneer Princeton Rabbit Roku Samsung Sensory Science Sharp SMC Sony Streamzap Systemax Tagar Systems TeleCaption Toshiba</td><td>20060, 20035, 20048, 20047, 20081, 20240, 20000, 20042, 200772, 20062, 20212, 20760 100use 20209, 20072, 20637 20035, 20000, 20072 20041, 20038 20039, 20033, 20000, 20209, 20034, 20479, 21479, 21139, 20637 21972 1les for Video Accessories 01272 01272 01272 01272 01272 01272 01272 01272 01272 01393 01165 01384 01344 01403 01415 01365 10403 01415 01365 10403 10415 01365 10403 10416 01365 10500 1</td></t<>	Voom	Firstar Fisher Fortress Fujitsu Funai Furi Furi Formai Furi Ganxin Gateway GE General Gibralter Gintai Go Video GoldStar Goodmans Grunpy Haier Haiyan Hallmark Hankook Harley Davidson Harman/Kardon Harward Havermy Hello Kitty Himitsu Hisense Hitachi Hongmei Hongyan Hua Tun Huafa Huanghe Huanghe Huanghe Huanghe Huangh Huari Huodateji Hyundai Imperial Crown Infinity	10236 10154, 10159 10093 10180, 10853, 10179, 10809, 10683 10180, 10171, 10264, 11904, 10179, 10342 10145, 10817, 10264 10180 10817 11756, 11755 11447, 10047, 11454, 10051, 10451, 10180, 10030, 10178, 10092, 11147, 11919, 10055, 10027, 11917, 10135, 10282, 11347, 10021, 11907, 11907, 11902 10186 10017, 10030, 10019 11150, 10474 10886 10154, 10030, 10178, 11926, 10019, 10037, 11910, 10001, 10032, 10056, 11150, 10039 10360 10180, 10179 11034, 10768 10264, 10817 10180, 10030, 10178, 11910, 10056, 10628 11904, 10179 10054 10180, 10030, 10178, 11019, 10056, 10628 11904, 10179 10054 10180, 10030, 10178, 11019, 10056, 10628 11904, 10179 10054 10180, 10030, 10178, 10019, 10056, 10628 11904, 10179 10054 10180, 10628 10156, 10748, 10145 11256, 10156, 10030, 10178, 11145, 10145, 10038, 11245, 10092, 10027, 10381, 10036, 1150, 10056, 11904, 10151, 10165, 10019, 10186, 10032, 10039, 10157, 10016, 10179, 10474 10093, 11910, 10817, 10264 10145, 10264 10145, 10264 10145, 10264 10145, 10264 10051 10849	Megatron MEI Meile Memorex Mermaid MGA Midland Minutz Mitsubishi Monivision Motorola MTC Mudan Multitech NAD Nanbao Nansheng National NEC Newave Nikko Nikon Norcent Noshi NTC Onking Onwa Optimus Optoma Optomica Orion Panasonic	10700 10178, 10145, 10003 10185 10264, 11910, 10817 10154, 10463, 10150, 10178, 10179, 11920, 11927, 10016, 11911, 11926, 11924 10037 10150, 10030, 10178, 11907, 10019 10047, 10017, 10051, 10039, 10135, 10032 10021 10154, 10250, 10093, 10236, 10180, 11250, 10150, 10030, 10178, 10381, 10386, 10036, 10179, 10381, 10386, 10036, 10179, 10381, 101836, 10036, 10179, 10381, 101836, 10036, 10179, 10381, 101843, 10700 10093, 10055 10060, 10030, 10185, 10019, 10056 10051, 10817, 11264 10180 10156, 10178, 10866 11910, 10264 10817, 10264 10817, 10264 10051 10154, 10156, 10051, 10053, 10030, 10178, 10046, 11150, 10056, 10165, 10186, 10474, 10036, 10882, 10381, 10817, 11704, 10170, 10264, 10019, 10497 10093, 10178, 11150, 10092, 10161 10030, 10178, 10092 11910 10748, 10824 10018 10092 10280 10180 10154, 10250, 10166, 11924, 11913, 10650, 11927 10887 10093, 10165 10236, 10463, 11911, 11905, 10179, 11463, 11929 10254, 10250, 10051, 10051, 10161, 11410, 11927, 11947, 10037, 10055, 10650, 11924, 11946, 11919, 11941 10051, 10706, 10817, 10264, 11910 10047, 10156, 10051, 10060, 10030, 10178, 10153, 11347, 11926, 10018, 10027, 10039, 11919, 11094, 11097, 11097, 11099, 10019 10054, 10250, 10051, 10061, 10074, 10019, 10032, 10056, 10186, 100774, 10019, 10032, 10036, 10186, 100774, 10019, 10032, 10056, 10186, 10774, 10019, 10032, 10056, 10186, 10774, 10019, 10032, 10056, 10186, 10774, 10019, 10032, 10056, 10186, 10774, 10019, 10032, 10056, 10186, 10774, 10019, 10032, 10056, 10186, 10774, 10019, 10032, 10056, 10186, 10774, 10019, 10032, 10056, 10186, 10774, 10019, 10032, 10056, 10186, 10774, 10019, 10032, 10054, 10076, 10186, 10774, 10019, 10032, 10054, 10074, 10019, 10154, 10076, 10186, 10774, 10019, 10032, 10076, 10186, 10774, 10019, 10032, 10076, 10186, 10774, 10019, 10032, 10076, 10186, 10774, 10019, 10154, 10076, 10186, 10774, 10019, 10032, 10076, 10186, 10774, 10019, 10032, 10076, 10186, 10774, 10019, 10054, 10000, 10051, 10030, 10178, 10054, 10000, 10051, 10060, 10076, 10186, 10774, 10019, 10054, 10000, 10051, 10076, 10187, 1077	Shen Ying Shencai Signature Signature Simpson Skygiant Skyworth Sony Soundesign Sowa Spectricon Squareview SSS Starlite Studio Experie Supre-Macy Supreme SVA Sylvania Symphonic Synco Tacico Tai Yi Taishan Tandy Tashiko Tatung Technics Technol Ace Techview Techwood Teco Teknika Telefunken Tera Thomas Tiane Tiane TMK TNCi	10039, 10165, 10474, 10688, 10787, 10036, 11917 ge 11950 10092, 10003, 10474, 10179 10145, 10264 10093, 10236, 10179, 11150, 10474 10817, 10264 10019 10016 10187, 10186 10180 10748, 10264, 10037, 10817 11100, 10000, 10036, 10650, 11300, 10111, 11925, 10080, 10834, 11904 10180, 10178, 10179, 10186 10156, 10051, 10060, 10178, 10036, 10092, 10474, 11150 10003 10171 10180, 10019 10180 10006 10748, 10587, 10865, 10872, 10768, 10871, 108870 100046 10000 10748, 1030, 10171, 11931, 10381, 11944, 10020, 10096 10180, 10171, 11913, 11904 10000, 10451, 10093, 10060, 10178, 10092, 1036, 10474 10178, 10179, 11150, 10092, 10474 11150 10817, 10391 10093 11150, 10650, 10092 10054, 10154, 10156, 10051, 10060, 11150, 10474, 10036, 10055, 11756, 10003 10250, 10051 10179 10847 10051, 10003, 10076 10071, 10093, 10178, 10474, 10036, 10280, 10092, 10264, 1053, 10756, 10003 10250, 10051 10179 10847 10051, 10003, 10056 10051, 10093, 10178, 10474, 10036, 10280, 10099, 10264, 10536, 10074, 10179, 10079, 10056, 10186, 10016, 10092, 10039, 10179 10702, 10056 10030, 10466, 10474 11904 10093, 10817 10178, 10177, 10056	America Action American High Amoisonic Anam Anam National Asha Audiovox Beaumark Bell & Howell Blaupunkt Broksonic Calix Canon Carver CCE Changhong Citizen Colt Craig Curtis Mathes Cybernex CyberPower Daewoo Dell Denon DirecTV Dish Network Sy Dishpro Durabrand Dynatech Echostar Electrohome Electrophonic Emerex Emerson Euro 1 Expressvu Fisher Fuji Fujitsu Funai Garrard Gateway GE General	21972 n 20278 h 200278 h 20035 20479 20162, 20037, 20240, 20278, 20226, 21037 ll 20162, 20226 20240 20037, 20278 20240 20104 20226 20184, 20121, 20209, 20002, 20348, 20295, 21479, 20479 20035, 21174, 20167 20081 20072, 20278 20048, 20081 20072, 20278 20048, 20081 20037, 20278, 21278 20072 20035, 20174, 2026, 20072, 20271 20060, 20035, 20162, 20041, 20760, 21035 20240 21972 20045, 20104, 20278, 20210, 20368, 21278, 20637, 20038, 20122, 20561 21972 20045, 20104, 20278, 20210, 20368, 21278, 20637, 20948, 20948, 20949 20739, 21989, 21954, 21949 System 21943, 21946, 21945, 21944 21944, 21943 20039, 20038 20000 21943, 21946, 21945, 21944 20037 20037 20037 20037 20037 20037 20037 20038 20000 21943, 21946, 21945, 21944 20037 20037, 20184, 20240, 20045, 20000, 20121, 20043, 20209, 20002, 20278, 20295, 20036, 20637, 21593, 20561, 21479, 20068, 20208, 20479, 21278, 20661, 20212 21962 21944 20047, 20104, 20066, 20054 20035, 20033 20045, 20052, 20366 20000, 20593, 21593 20000 21972 20060, 20035, 20226, 20761 20045, 20366, 20052	MTC Multitech NAD National NEC Newave Nikko Nikon Noblex Northgate Olympus Onkyo Optimus Optonica Orion Panarex Panasonic Pansat Penney Pentax Philco Philips Pilot Pioneer Polk Audio Profitronic Prostar Quarter Quarter Quarter Quarter Quarter Quarter Quarter Quarter RadioShack Radix Randex RCA Realistic ReplayTV Ricoh Runco	20240, 20000 20000, 20072 20058 20256 2026 20035, 20037, 20048, 20104, 20067, 20041, 20038, 20040, 20008, 20370 20037 20253, 20034 20253, 20034 20240 21972 20035, 20226, 21046 20222 21062, 20162, 20037, 20048, 20104, 21048, 21262, 20593, 21162, 20058, 20432 20062 20184, 20209, 20002, 20479, 20295, 21479 21950 21062, 20035, 20162, 20077, 20226, 20616, 21162, 20225, 20367, 20227, 21035, 21262 21950 20035, 20035, 20162, 20077, 20226, 20616, 21162, 20225, 20367, 20227, 21035, 21262 21950 20035, 20037, 20240, 20042, 20038, 21035, 20040, 20054, 21237 20042, 20105 20035, 20061, 20000, 20226, 20739, 21381, 20110, 20618, 21181, 20563, 21081, 21949, 20062 20037 20042, 20067, 20058 20081 20240 20060, 20760, 21954, 20202, 21060, 20761 20072 20039 20060 20046 20046 20046 20046 20045, 20162, 21035, 20077, 21162 20000, 21037 20037 20061 20046 20046 20046 20046, 20053, 20162, 21035, 20077, 21162 20009 20046 20046 20037, 20022, 2040, 20000, 20042, 20807, 21060, 21989, 20106, 20761, 21035, 20058, 21964, 20105, 20226, 20760, 20880, 21954, 20077, 20222, 20153, 20034, 20046, 20066, 20046, 20062, 20761, 21035, 20058, 21964, 20105, 20226, 20760, 20880, 21954, 20077, 20222, 20153, 20034, 20044, 20016, 20061, 20	Wards White Westingh XR-1000 Yamaha Zenith ZT Group Setup Cod ABS Alienware CyberPower Gateway Hewlett Packare Howard Compu HP IBUYPOWER InterVideo Jensen JVC Keyspan KWorld LG Linksys Macro Image Te Media Center Pe Microsoft Mind Motorola MyHD Northgate Panasonic Pinnacle System Pioneer Princeton Rabbit Roku Samsung Sensory Science Sharp SMC Sony Streamzap Systemax Tagar Systems TeleCaption Toshiba	20060, 20035, 20048, 20047, 20081, 20240, 20000, 20042, 200772, 20062, 20212, 20760 100use 20209, 20072, 20637 20035, 20000, 20072 20041, 20038 20039, 20033, 20000, 20209, 20034, 20479, 21479, 21139, 20637 21972 1les for Video Accessories 01272 01272 01272 01272 01272 01272 01272 01272 01272 01393 01165 01384 01344 01403 01415 01365 10403 01415 01365 10403 10415 01365 10403 10416 01365 10500 1
Proscan 20522 ProVision 20778 Qwestar 20651 RCA 20522, 20571, 20717, 20822, 21193, 21974, 21132, 21965, 21022, 21913 Regent 21938 Rio 20689 Rotel 20623 Rowa 20823 Sampo 20752, 20698 Sampo 20490, 20573, 20820, 21932, 21075, 20899, 21979 Sansui 20695 Sanyo 20695, 20670, 21967, 20873 Sharp 20630, 20752 Sharpe Image 21995, 21117 Sherwood 21043, 20770, 20633, 21077 Shinco 20717 Shinco 20717 Shinco 20717 Shinco Blue 20869, 21970, 21099 Sony 20533, 20839, 21931 Sigma Designs 20674 Sonic Blue 20869, 21970, 21099 Sony 20533, 20864, 21033, 21944, 22020, 21903, 21934, 2072, 21934 Sungale 21074 Svalid 20717, 20860, 21105 Sylvania 20821 SVA	Voom	Firstar Fisher Fortress Fujitsu Funai Furi Furi Furi Futuretech Ganxin Gateway GE General Gibralter Gintai Go Video GoldStar Goodmans Grunpy Haier Haiyan Hallmark Hankook Harley Davidson Harrnan/Kardon Harvard Havermy Hello Kitty Himitsu Hisense Hitachi Hongyan Hua Tun Huafa Huanghe Huanghe Huanghe Huanghan Huanyu Huaqiang Huaqiang Huodateji Hyundai Imperial Crown Infinity Inteq	10236 10154, 10159 10093 10186, 10853, 10179, 10809, 10683 10180, 10171, 10264, 11904, 10179, 10342 10145, 10817, 10264 10180 10817 11756, 11755 11447, 10047, 11454, 10051, 10451, 10180, 10030, 10178, 10092, 11147, 11919, 10055, 10027, 11917, 10135, 10282, 11347, 10021, 11907, 11922 10186 10017, 10030, 10019 11150, 10474 10886 10017, 10030, 10178, 11926, 10019, 10037, 11910, 10031, 10032, 10056, 11150, 10039 10360 10154, 10030, 10178, 11926, 10019, 10037, 11910, 10001, 10032, 10056, 11150, 10039 10360 10160, 10179 11034, 10768 10264, 10817 10178 10180, 10030, 10178, 11019, 10056, 10628 11904, 10179 11054 11050, 10054 110180, 10030, 10178, 11018, 110145, 10039 10451 10180, 10030, 10178, 11145, 10145, 10039 10451 10180, 10030, 10178, 11145, 10145, 10038, 11245, 10092, 10027, 10381, 10036, 11150, 10056, 11904, 1015, 10165, 10019, 10145, 10038, 11245, 10092, 10027, 10381, 10019, 10474 10093, 11910, 10817, 10264 10817 10264, 10817 11910, 10817, 10264 10051 10849 10001, 10391, 10264 10051	Megatron MEI Meile Memorex Mermaid MGA Midland Minutz Mitsubishi Monivision Motorola MTC Mudan Multitech NAD Nanbao Nansheng National NEC Newave Nikko Nikon Norcent Noshi NTC Onking Onwa Optimus Optoma Optomica Orion Panasonic	10700 10178, 10145, 10003 10185 10264, 11910, 10817 10154, 10463, 10150, 10178, 10179, 11920, 11927, 10016, 11911, 11926, 11924 10037 10150, 10030, 10178, 11907, 10019 10047, 10017, 10051, 10039, 10135, 10032 10021 10154, 10250, 10093, 10236, 10180, 11250, 10150, 10030, 10178, 10381, 10836, 10036, 10179, 10817, 11150, 10474, 10019, 10868, 10056, 11917 10843, 10700 10093, 10055 10060, 10030, 10185, 10019, 10056 10051, 10817, 10264 10180 10156, 10178, 10866 11910, 10264 10817, 10264 10817, 10264 10817, 10264 10817, 10264 10051 1055, 10178, 10866 11910, 10264 10817, 10264 10817, 10264 10051 1051, 10178, 10866 11910, 10264 10817, 10264 10817, 10264 10019, 10497 10093, 10178, 11150, 10092, 10161 10030, 10178, 10992 10280 10180 10154, 10250, 10166, 11924, 11913, 10650, 11927 10887 10093, 10165 10236, 10463, 11911, 11905, 10179, 11463, 11929 10054, 10250, 10166, 11924, 11913, 10650, 11927 10887 10093, 10165 10236, 10463, 11911, 11905, 10179, 11463, 11929 10054, 10250, 10051, 10161, 11410, 11927, 10947, 10037, 10055, 10650, 11924, 11946, 11919, 11941 10051, 10706, 10817, 10264, 11910 10074, 10156, 10051, 10061, 10161, 11410, 11927, 11947, 10037, 10055, 10650, 11924, 11946, 11919, 11041 10051, 10706, 10817, 10264, 11910 10074, 10156, 10051, 10060, 10030, 10178, 10135, 11347, 11926, 10018, 10027, 10039, 10199, 10003, 100178, 10050, 10178, 10050, 10178, 10050, 10178, 10050, 10178, 10050, 10178, 10050, 10178, 10150, 100774, 10019	Shen Ying Shencai Signature Signature Simpson Skygiant Skyworth Sony Soundesign Sowa Spectricon Squareview SSS Starlite Studio Experie Supre-Macy Supre-Macy Supreme SVA Sylvania Symphonic Synco Tacico Tai Yi Taishan Tandy Tashiko Tatung Technics Technol Ace Techview Techwood Teco Teknika Telefunken Tera Thomas Tiane Time	10039, 10165, 10474, 10688, 10787, 10036, 11917 3e 11950 10092, 10003, 10474, 10179 10145, 10264 10093, 10236, 10179, 11150, 10474 10817, 10264 10019 10016 10187, 10186 10180 10748, 10264, 10037, 10817 11100, 10000, 1036, 10650, 11300, 10111, 11925, 10080, 10834, 11904 10180, 10178, 10179, 10186 10156, 10051, 10060, 10178, 10036, 10092, 10474, 11150 10003 10171 10180, 10019 10180 ience 10843 10046 10000 10748, 10587, 10865, 10872, 10768, 10871, 10870 10054, 10030, 10171, 11931, 10381, 11944, 10020, 10096 10180, 10171, 11913, 11904 10000, 10451, 10093, 10060, 10178, 10092, 10036, 10474 10178, 10179, 11150, 10092, 10474 10178, 10179, 11150, 10092, 10474 10178, 10179, 11150, 10092, 10474 10179, 10154, 10156, 10051, 10060, 11150, 10474, 10036, 10055, 11756, 10003 10250, 10051 10054, 10154, 10156, 10051, 10060, 11150, 10474, 10036, 10055, 11756, 10003 10250, 10051 10051, 10003, 10178, 10474, 10036, 10280, 10092, 10054, 10180, 10150, 10060, 10019, 10056, 10166, 100474 11090 10054, 10180, 10150, 10060, 10019, 10056, 10166, 10046, 10077, 10056 10030, 10466, 10474 11904 10093, 10817	America Action American High Amoisonic Anam Anam National Asha Audiovox Beaumark Bell & Howell Blaupunkt Broksonic Calix Canon Carver CCE Changhong Citizen Colt Craig Curtis Mathes Cybernex CyberPower Daewoo Dell Denon DirecTV Dish Network Sy Dishpro Durabrand Dynatech Echostar Electrophonic Emerex Emerson Euro 1 Expressvu Fisher Fuji Fujitsu Funai Garrard Gateway GE	21972 n 20278 h 200278 h 20035 20479 20162, 20037, 20240, 20278, 20226, 21037 ll 20162, 20226 20240 20037, 20278 20240 20104 20104 20126 20184, 20121, 20209, 20002, 20348, 20295, 21479, 20479 20035, 21174, 20167 20081 20072, 20278 20048, 20081 20072, 20278 20037, 20278, 21278 20072 20037, 20047, 20240, 20072, 20271 20060, 20035, 20162, 20041, 20760, 21035 20240 21972 20045, 20104, 20278, 20210, 20368, 21278, 20637, 20046, 20212, 20561 21972 20042 20739, 21899, 21954, 21949 System 21943, 21946, 21945, 21944 21944, 21943 20039, 20038 20000 21943, 21946, 21945, 21944 20037 20037 20037 20037 20038 20000 21943, 21946, 21945, 21944 20037 20037 20039 20039, 20038 20000 21943, 21946, 21945, 21944 20037 20037 20032 20035, 20037, 20184, 20240, 20045, 20000, 20121, 20043, 20209, 20002, 20278, 20295, 20036, 20637, 21593, 20561, 21479, 20068, 20208, 20479, 21278, 20061, 20212 21962 21944 20047, 20104, 20066, 20054 20035, 20035, 20033 20045, 20052, 20366 20000, 20593, 21593 20000 21972 20060, 20035, 20240, 21060, 20202, 20760, 21035, 20807, 20226, 20761	MTC Multitech NAD National NEC Newave Nikko Nikon Noblex Northgate Olympus Onkyo Optimus Optonica Orion Panarex Panasonic Pansat Penney Pentax Philco Philips Pilot Pioneer Polk Audio Profitronic Proscan Protec Pulsar Quartz Quartz Quartz Quartz Quartz Quartz Quartz Quartz Quartz Quasar RadioShack Radix Randex RCA Realistic ReplayTV Ricoh	20240, 20000 20000, 20072 20058 20026 20035, 20037, 20048, 20104, 20067, 20041, 20038, 20040, 20008, 20370 20037 20037 20253, 20034 20240 21972 20035, 20226, 21046 20222 21062, 20162, 20037, 20048, 20104, 21048, 21262, 20593, 21162, 20058, 20432 20062 20184, 20209, 20002, 20479, 20295, 21479 21950 21062, 20035, 20162, 20077, 20226, 20616, 21162, 20225, 20367, 20227, 21035, 21262 21950 20035, 20037, 20240, 20042, 20038, 21035, 20040, 20054, 211237 20042, 20105 20035, 200081, 20000, 20226, 20739, 21381, 20110, 20618, 21181, 20563, 21081, 21949, 20062 20037 20042, 20067, 20058 20081 20240 20060, 20760, 21954, 20202, 21060, 20761 20072 20039 20060 20046 20046 20046 20046 20058, 20162, 21035, 20077, 21162 200097 20037 20042, 20169, 20169, 2077, 21162 200007 20039 20060 20046 20046 20046 20055, 20162, 21035, 20077, 21162 200007 20060, 20760, 21954, 20202, 21060, 20761 20072 20037 20060, 20760, 21954, 20202, 21060, 20761 20072 20039 20060 20046 20046 20055, 20162, 21035, 20077, 21162 200007 20057, 20202, 2026, 20760, 20880, 21954, 20105, 20226, 20760, 20880, 21954, 20107, 202062, 20750, 20880, 21954, 20107, 202062, 20753, 20081, 20061 20046, 20046, 20062 20048, 20047, 20000, 20042, 20807, 21060, 21989, 20106, 20761, 21035, 20058, 21644, 20105, 20226, 20760, 20880, 21954, 20077, 20202, 20453 20035, 20037, 20048, 20047, 20000, 20104, 20066, 20046, 20062 20044, 20166 20253, 20034	Wards White Westingh XR-1000 Yamaha Zenith ZT Group Setup Cod ABS Alienware CyberPower Gateway Hewlett Packare Howard Compu HP IBUYPOWER InterVideo Jensen JVC Keyspan KWorld LG Linksys Macro Image Te Media Center Po Microsoft Mind Motorola MyHD Northgate Panasonic Pinnacle System Pioneer Princeton Rabbit Roku Samsung Sensory Science Sharp SMC Sony Streamzap Systemax Tagar Systems TeleCaption Toshiba Touch Viewsonic	20060, 20035, 20048, 20047, 20081, 20240, 20000, 20042, 20072, 20062, 20212, 20760 100use 20209, 20072, 20062, 20212, 20760 100use 20209, 20072, 20637 20035, 20000, 20072 20041, 20038 20039, 20033, 20000, 20209, 20034, 20479, 21479, 21139, 20637 21972 101272 101272 101272 101272 101272 101272 101272 101384 101384 101384 101384 101415 101365 104165 104165 104172 104272 104272 104272 10438 104415 10468 10568 1060 10772 10120 10138 10120 10138 10127 10127 10127 10127 10127 10127 10127 10127 10127 10127 10127 10127 10127 10127 10127 101363 101383 101272 101363 101384 101486 10100 10113, 00295 100081 10486 10190, 01490 101126 10100 101150 101456 101272, 01324, 01364 10309 101272 1